BURR-BROWN®



UAF42

UNIVERSAL ACTIVE FILTER

FEATURES

- VERSATILE— LOW-PASS, HIGH-PASS BAND-PASS, BAND-REJECT
- SIMPLE DESIGN PROCEDURE
- ACCURATE FREQUENCY AND Q — INCLUDES ON CHIP 1000pF ±0.5% CAPACITORS

APPLICATIONS

- TEST EQUIPMENT
- COMMUNICATIONS EQUIPMENT
- MEDICAL INSTRUMENTATION
- DATA ACQUISITION SYSTEMS
- MONOLITHIC REPLACEMENT FOR UAF41

DESCRIPTION

The UAF42 is a universal active filter which can be configured for a wide range of low-pass, high-pass, and band-pass filters. It uses a classical state-variable analog architecture with an inverting amplifier and two integrators. The integrators include on-chip 1000pF capacitors trimmed to 0.5%. This solves one of the most difficult problems of active filter design—obtaining tight tolerance, low-loss capacitors.

A DOS-compatible filter design program allows easy implementation of many filter types such as Butterworth, Bessel, and Chebyshev. A fourth, uncommitted FET-input op amp (identical to the other three) can be used to form additional stages, or for special filters such as band-reject and Inverse Chebyshev.

The classical topology of the UAF42 forms a time-continuous filter, free from the anomalies and switching noise associated with switched-capacitor filter types.

The UAF42 is available in 14-pin plastic DIP and SOL-16 surface-mount packages, specified for the –25°C to +85°C temperature range.



International Airport Industrial Park • Mailing Address: PO Box 11400, Tucson, AZ 85734 • Street Address: 6730 S. Tucson Blvd., Tucson, AZ 85706 • Tel: (520) 746-1111 • Twx: 910-952-1111
Internet: http://www.burr-brown.com/ • FAXLine: (800) 548-6133 (US/Canada Only) • Cable: BBRCORP • Telex: 066-6491 • FAX: (520) 889-1510 • Immediate Product Info: (800) 548-6132

©1990 Burr-Brown Corporation
PDS-1070H
Printed in U.S.A. January, 1998

SBFS002

SPECIFICATIONS

ELECTRICAL

At T_A = +25°C, V_S = ±15V, unless otherwise noted.

PARAMETER	CONDITIONS	UAF42AP, AU MIN	UAF42AP, AU TYP	UAF42AP, AU MAX	UNITS
FILTER PERFORMANCE					
Frequency Range, fn			0 to 100		kHz
Frequency Accuracy	f = 1kHz			1	%
vs Temperature			0.01		%/°C
Maximum Q			400		—
Maximun (Q • Frequency) Product			500		kHz
Q vs Temperature	$(f_O \bullet Q) < 10^4$		0.01		%/°C
	$(f_O \bullet Q) < 10^5$		0.025		%/°C
Q Repeatability	$(f_O \bullet Q) < 10^5$		2		%
Offset Voltage, Low-Pass Output				±5	mV
Resistor Accuracy			0.5	1%	%
OFFSET VOLTAGE[1]					
Input Offset Voltage			±0.5	±5	mV
vs Temperature			±3		µV/°C
vs Power Supply	V_S = ±6 to ±18V	80	96		dB
INPUT BIAS CURRENT[1]					
Input Bias Current	V_{CM} = 0V		10	50	pA
Input Offset Current	V_{CM} = 0V		5		pA
NOISE					
Input Voltage Noise					
Noise Density: f = 10Hz			25		nV/√Hz
f = 10kHz			10		nV/√Hz
Voltage Noise: BW = 0.1 to 10Hz			2		µVp-p
Input Bias Current Noise					
Noise Density: f = 10kHz			2		fA/√Hz
INPUT VOLTAGE RANGE[1]					
Common-Mode Input Range			±11.5		V
Common-Mode Rejection	V_{CM} = ±10V	80	96		dB
INPUT IMPEDANCE[1]					
Differential			10^{13} || 2		Ω || pF
Common-Mode			10^{13} || 6		Ω || pF
OPEN-LOOP GAIN[1]					
Open-Loop Voltage Gain	V_O = ±10V, R_L = 2kΩ	90	126		dB
FREQUENCY RESPONSE[1]					
Slew Rate			10		V/µs
Gain-Bandwidth Product	G = +1		4		MHz
Total Harmonic Distortion	G = +1, f = 1kHz		0.0004		%
OUTPUT[1]					
Voltage Output	R_L = 2kΩ	±11	±11.5		V
Short Circuit Current			±25		mA
POWER SUPPLY					
Specified Operating Voltage			±15		V
Operating Voltage Range		±6		±18	V
Current			±6	±7	mA
TEMPERATURE RANGE					
Specification		–25		+85	°C
Operating		–25		+85	°C
Storage		–40		+125	°C
Thermal Resistance, θ_{JA}			100		°C/W

* Same as specification for UAF42AP.

NOTES: (1) Specifications apply to uncommitted op amp, A_4. The three op amps forming the filter are identical to A_4 but are tested as a complete filter.

The information provided herein is believed to be reliable; however, BURR-BROWN assumes no responsibility for inaccuracies or omissions. BURR-BROWN assumes no responsibility for the use of this information, and all use of such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. BURR-BROWN does not authorize or warrant any BURR-BROWN product for use in life support devices and/or systems.

PIN CONFIGURATION

Top View

Plastic DIP, P



U Package
SOL-16, 16-Pin SOIC



NOTE: NC: No Connection. For best performance connect all "NC" pins to ground to minimize inter-lead capacitance.

ABSOLUTE MAXIMUM RATINGS

Power Supply Voltage	±18V
Input Voltage	$\pm V_S$ ±0.7V
Output Short Circuit	Continuous
Operating Temperature:	
Plastic DIP, P; SOIC, U	–40°C to +85°C
Storage Temperature:	
Plastic DIP, P; SOIC, U	–40°C to +125°C
Junction Temperature:	
Plastic DIP, P; SOIC, U	+125°C
Lead Temperature (soldering, 10s)	+300°C

PACKAGE/ORDERING INFORMATION

PRODUCT	PACKAGE	PACKAGE DRAWING NUMBER(1)	TEMPERATURE RANGE
UAF42AP	Plastic 14-pin DIP	010	–25°C to +85°C
UAF42AU	SOL-16	211	–25°C to +85°C

NOTE: (1) For detailed drawing and dimension table, please see end of data sheet, or Appendix C of Burr-Brown IC Data Book.

ELECTROSTATIC DISCHARGE SENSITIVITY

This integrated circuit can be damaged by ESD. Burr-Brown recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

APPLICATIONS INFORMATION

The UAF42 is a monolithic implementation of the proven state-variable analog filter topology. Pin-compatible with the popular UAF41 Analog Filter, it provides several improvements.

Slew Rate of the UAF42 has been increased to 10V/μs versus 1.6V/μs for the UAF41. Frequency • Q product of the UAF42 has been improved, and the useful natural frequency extended by a factor of four to 100kHz. FET-input op amps on the UAF42 provide very low input bias current. The monolithic construction of the UAF42 provides lower cost and improved reliability.

DESIGN PROGRAM

Application Bulletin AB-035 and a computer-aided design program, available from Burr-Brown, make it easy to design and implement many kinds of active filters. The DOS-compatible program guides you through the design process and automatically calculates component values.

Low-pass, high-pass, band-pass and band-reject (notch) filters can be designed. The program supports the three most commonly used all-pole filter types: Butterworth, Chebyshev and Bessel. The less-familiar Inverse Chebyshev is also supported, providing a smooth passband response with ripple in the stop-band.

With each data entry, the program automatically calculates and displays filter performance. This allows a spreadsheet-like "what if" design approach. For example, you can quickly determine, by trial and error, how many poles are required for a desired attenuation in the stopband. Gain/phase plots may be viewed for any response type.

The basic building element of the most commonly used filter types is the second-order section. This section provides a complex-conjugate pair of poles. The natural frequency, ω_n, and Q of the pole pair determines the characteristic response of the section. The low-pass transfer function is

$$\frac{V_O(s)}{V_I(s)} = \frac{A_{LP}\omega_n^2}{s^2 + s\,\omega_n/Q + \omega_n^2} \qquad (1)$$

The high-pass transfer function is

$$\frac{V_{HP}(s)}{V_I(s)} = \frac{A_{HP}s^2}{s^2 + s\,\omega_n/Q + \omega_n^2} \qquad (2)$$

The band-pass transfer function is

$$\frac{V_{BP}(s)}{V_I(s)} = \frac{A_{BP}(\omega_n/Q)\ \ s}{s^2 + s\,\omega_n/Q + \omega_n^2} \qquad (3)$$

A band-reject response is obtained by summing the low-pass and high-pass outputs, yielding the transfer function

$$\frac{V_{BR}(s)}{V_I(s)} = \frac{A_{BR}(s^2 + \omega_n^2)}{s^2 + s\,\omega_n/Q + \omega_n^2} \qquad (4)$$

The most commonly used filter types are formed with one or more cascaded second-order sections. Each section is designed for ω_n and Q according to the filter type (Butterworth, Bessel, Chebyshev, etc.) and cutoff frequency. While tabulated data can be found in virtually any filter design text, the design program eliminates this tedious procedure.

Second-order sections may be non-inverting (Figure 1) or inverting (Figure 2). Design equations for these two basic configurations are shown for reference. The design program solves these equations, providing complete results, including component values.



Design Equations

1. $$\omega_n^2 = \frac{R_2}{R_1 R_{F1} R_{F2} C_1 C_2}$$

2. $$Q = \frac{1 + \frac{R_4 (R_G + R_Q)}{R_G R_Q}}{1 + \frac{R_2}{R_1}} \left(\frac{R_2 R_{F1} C_1}{R_1 R_{F2} C_2} \right)^{1/2}$$

3. $$QA_{LP} = QA_{HP} \left(\frac{R_1}{R_2} \right) = A_{BP} \left(\frac{R_1 R_{F1} C_1}{R_2 R_{F2} C_2} \right)^{1/2}$$

4. $$A_{LP} = \frac{1 + \frac{R_1}{R_2}}{R_G \left(\frac{1}{R_G} + \frac{1}{R_Q} + \frac{1}{R_4} \right)}$$

5. $$A_{HP} = \frac{R_2}{R_1} \quad A_{LP} = \frac{1 + \frac{R_2}{R_1}}{R_G \left(\frac{1}{R_G} + \frac{1}{R_Q} + \frac{1}{R_4} \right)}$$

6. $$A_{BP} = \frac{R_4}{R_G}$$

FIGURE 1. Non-Inverting Pole-Pair.



Design Equations

1. $$\omega_n^2 = \frac{R_2}{R_1 R_{F1} R_{F2} C_1 C_2}$$

2. $$Q = \left(1 + \frac{R_4}{R_Q}\right) \frac{1}{\left(\frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_G}\right)} \left(\frac{R_{F1} C_1}{R_1 R_2 R_{F2} C_2}\right)^{1/2}$$

3. $$QA_{LP} = QA_{HP} \left(\frac{R_1}{R_2}\right) = A_{BP} \left(\frac{R_1 R_{F1} C_1}{R_2 R_{F2} C_2}\right)^{1/2}$$

4. $$A_{LP} = \frac{R_1}{R_G}$$

5. $$A_{HP} = \frac{R_2}{R_1} \quad A_{LP} = \frac{R_2}{R_G}$$

6. $$A_{BP} = \left(1 + \frac{R_4}{R_Q}\right) \frac{1}{R_G \left(\frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_G}\right)}$$

FIGURE 2. Inverting Pole-Pair.

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish	MSL Peak Temp (3)
UAF42AP	ACTIVE	PDIP	N	14	25	Pb-Free (RoHS)	Call TI	Level-NC-NC-NC
UAF42AP-1	OBSOLETE	PDIP	N	14		None	Call TI	Call TI
UAF42AU	ACTIVE	SOIC	DW	16	48	None	CU SNPB	Level-3-260C-168 HR
UAF42AU-1	OBSOLETE	SOIC	DW	16		None	Call TI	Call TI

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - May not be currently available - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.
None: Not yet available Lead (Pb-Free).
Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.
Green (RoHS & no Sb/Br): TI defines "Green" to mean "Pb-Free" and in addition, uses package materials that do not contain halogens, including bromine (Br) or antimony (Sb) above 0.1% of total product weight.

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDECindustry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
		Telephony	www.ti.com/telephony
		Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments
Post Office Box 655303 Dallas, Texas 75265

Copyright © 2005, Texas Instruments Incorporated

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.

Texas Instruments

http://www.ti.com

This file is the datasheet for the following electronic components:

- UAF42AP-1 - http://www.ti.com/product/uaf42ap-1?HQS=TI-null-null-dscatalog-df-pf-null-wwe
- UAF42AU - http://www.ti.com/product/uaf42au?HQS=TI-null-null-dscatalog-df-pf-null-wwe
- UAF42AP - http://www.ti.com/product/uaf42ap?HQS=TI-null-null-dscatalog-df-pf-null-wwe
- UAF42AU-1 - http://www.ti.com/product/uaf42au-1?HQS=TI-null-null-dscatalog-df-pf-null-wwe

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.