14+1 Channel Voltage Buffers for TFT LCD

■ FEATURES

- Wide supply voltage range 6.5V ~ 18V
- Rail-to-rail output swing (The highest two stage & lowest two stage)
- High slew rate 1V/μs
- GBWP 1 MHz
- 2 MHz -3dB Bandwidth
- Large Vcom Drive Current: ±100mA(Max)
- Ultra-small Package TQFP-48

■ APPLICATIONS

- TFT-LCD Reference Driver

■ GENERAL DESCRIPTION

The EC5575 is a 14+1 channel voltage buffers that buffers reference voltage for gamma correction in a thin film transistor liquid crystal display (TFT LCD). This device incorporating a Vcom amplifier circuits, four rail to rail buffer amplifier circuits (the highest two stage and lowest two stage) and 10 buffer amplifiers circuits. The EC5575 is available in a space saving 48-pin TQFP package, and the operating temperature is from –20°C to +85°C.

■ PIN ASSIGNMENT (E Type)



A, B, M, N: Rail to Rail OPAMPs

■ PIN ASSIGNMENT (E2 Type)



■ Ordering Information

Part No.	Top Mark	Package	Description
EC5575-F	AS15-F	TQFP48	14+1 lead-free
EC5575-G	AS15-G	TQFP48	14+1 Green Package
EC5575-FR	AS15-F	TQFP48	14+1 lead-free; (R) : Tape & reel
EC5575-GR	AS15-G	TQFP48	14+1 Green Package; (R) : Tape & reel
EC5575-HF	AS15-HF	TQFP48	14+1 lead-free (H)
EC5575-HG	AS15-HG	TQFP48	14+1 Green Package (H)
EC5575E2-F	AS15E2-F	TQFP48	14+1 (pin40 is Vcom-) lead-free
EC5575E2-G	AS15E2-G	TQFP48	14 channel (pin40 is Vcom-)Green Package
EC5575E2-HF	AS15E2-HF	TQFP48	14+1 (pin40 is Vcom-) lead-free (H)
EC5575E2-HG	AS15E2-HG	TQFP48	14 channel (pin40 is Vcom-)Green Package (H)

Note: (H): Exposed pad (3.05x3.05 mm) ; (R) : Tape & reel

■ ABSOLUTE MAXIMUM RATINGS (T_A = 25 °C)

Values beyond absolute maximum ratings may cause permanent damage to the device. These are stress ratings only; functional device operation is not implied. Exposure to AMR conditions for extended periods may affect device reliability.

Supply Voltage between V_{S+} and V_{S-}	+18V	Storage Temperature	-65°C to +150°C
Input Voltage (For rail-to-rail)	V_{S-}－0.5V, V_{S+}＋0.5V	Operating Temperature	-20°C to +85°C
Maximum Continuous Output Current (A ~ N uffers)	30mA	Lead Temperature	260°C
Maximum Continuous Output Current(Com Buffer)	100mA	ESD Voltage	2kV
Maximum Die Temperature	+150°C		

Important Note:

All parameters having Min/Max specifications are guaranteed. Typical values are for information purposes only. Unless otherwise noted, all tests are at the specified temperature and are pulsed tests, therefore: TJ = TC = TA

■ ELECTRICAL CHARACTERISTICS

V_{S+}= +5V, V_{S-} = -5V, R_L = 10kΩ and C_L = 10pF to 0V, T_A = 25°C unless otherwise specified.

Parameter	Description	Condition	Min	Typ	Max	Units
Input Characteristics						
V_{OS}	Input Offset Voltage	V_{CM}= 0V		2	12	mV
TCV_{OS}	Average Offset Voltage Drift	[1]		5		µV/°C
I_B	Input Bias Current	V_{CM}= 0V		2	50	nA
R_{IN}	Input Impedance			1		G
C_{IN}	Input Capacitance			1.35		pF
Output Characteristics						
V_{OL}	Output Swing Low	I_L= -5mA (A, B, M, N rail-to-rail Buffers)		-4.92	-4.85	V
V_{OH}	Output Swing High	I_L= 5mA (A, B, M, N rail-to-rail Buffers)	4.85	4.92		V
V_{OL}	Output Swing Low	I_L= -5mA (C ~ L Buffers)	-3.5			V
V_{OH}	Output Swing High	I_L= 5mA (C ~ L Buffers)	3.5			V
I_{SC}	Short Circuit Current	(A ~ N Buffers)		±120		mA
I_{OUT}	Output Current	(A ~ N Buffers)		±30		mA
$I_{SC(Com)}$	Short Circuit Current	(Com Buffer)		±300		mA
$I_{OUT(Com)}$	Output Current	(Com Buffer)		±100		mA
Power Supply Performance						
PSRR	Power Supply Rejection Ratio	V_S is moved from ±3.25V to ±7.75V	60	80		dB
I_S	Supply Current (Per Amplifier)	No Load (A ~ N Buffers)		500	750	µA
$I_{S(Com)}$	Supply Current	(Com Buffer)		5		mA
Dynamic Performance						
SR	Slew Rate [2]	-4.0V≦V_{OUT}≦4.0V, 20% to 80%		1		V/µs
t_S	Settling to +0.1% (AV = +1)	(AV = +1), V_O=2V Step		5		µs
BW	-3dB Bandwidth	RL = 10KΩ, CL = 10PF		2		MHz
PM	Phase Margin	RL = 10KΩ, CL = 10PF		60		Degrees
CS	Channel Separation	f = 1 MHz		75		dB

1. Measured over operating temperature range
2. Slew rate is measured on rising and falling edges

■ TYPICAL PERFORMANCE CURVES



Figure (a) Input Offset Voltage Distribution



Figure (b) Input beyond the rails



Figure (c) Rail to Rail Capability



igure (d) Large Signal Transient Response



Figure (e) Large Signal Transient Response



Figure (f) Small Signal Transient Response

■ TYPICAL PERFORMANCE CURVES



Figure (g) Open Loop Gain & Phase vs. Frequency



Figure (h) Frequency Response for Various C_L



Figure (h) Frequency Response for Various R_L

■ APPLICATIONS INFORMATION

Product Description

The EC5575 rail-to-rail quad channels amplifier is built on an advanced high voltage CMOS process. It's beyond rails input capability and full swing of output range made itself an ideal amplifier for use in a wide range of general-purpose applications. The features of 1μS high slew rate, fast settling time, 2MHz of GBWP as well as high output driving capability have proven the EC5575 a good voltage reference buffer in TFT-LCD for grayscale reference applications. High phase margin and extremely low power consumption (500μA per amplifier) make the EC5575 ideal for Connected in voltage follower mode for low power high drive applications

Supply Voltage, Input Range and Output Swing

The EC5575 can be operated with a single nominal wide supply voltage ranging from 6.5V to 18V with stable performance over operating temperatures of -20 °C to +85 °C.

With 500mV greater than rail-to-rail input common mode voltage range and 75dB of Common Mode Rejection Ratio, the EC5575 allows a wide range sensing among many applications without having any concerns over exceeding the range and no compromise in accuracy. The output swings of the EC5575 typically extend to within 80mV of positive and negative supply rails with load currents of 5mA. The output voltage swing can be even closer to the supply rails by merely decreasing the load current. Figure 1 shows the input and output waveforms for the device in the unity-gain configuration. The amplifier is operated under ±5V supply with a 10k. load connected to GND. The input is a 10Vp-p sinusoid. An approximately 9.985 Vp-p of output voltage swing can be easily achieved.



Figure 1. Operation with Rail-to-Rail Input and Output

Output Short Circuit Current Limit

A +/-120mA short circuit current will be limited by the EC5575 if the output is directly shorted to the positive or the negative supply. For an indefinitely output short circuit, the power dissipation could easily increase such that the device may be damaged. The internal metal interconnections are well designed to prevent the output continuous current from exceeding +/-30 mA such that the maximum reliability can be well maintained.

Output Phase Reversal

The EC5575 is designed to prevent its output from being phase reversal as long as the input voltage is limited from $V_{S-}-0.5V$ to $V_{S+}+0.5V$. Figure 2 shows a photo of the device output with its input voltage driven beyond the supply rails. Although the phase of the device's output will not be reversed, the input's over-voltage should be avoided. An improper input voltage exceeds supply range by more than 0.6V may result in an over stress damage.



Figure 2. Operation with Beyond-the Rails Input

Power Dissipation

The EC5575 is designed for maximum output current capability. Even though momentary output shorted to ground causes little damage to the device.

For the high drive amplifier EC5575, it is possible to exceed the 'absolute-maximum junction temperature' under certain load current conditions. Therefore, it is important to calculate the maximum junction temperature for the application to determine if load conditions need to be modified for the amplifier to remain in the safe operating area. The maximum power dissipation allowed in a package is determined according to:

$$P_{Dmax} = \frac{T_{Jmax} - T_{Amax}}{\Theta_{JA}}$$

Where:

T_{Jmax} = Maximum Junction Temperature

T_{Amax} = Maximum Ambient Temperature

Θ_{JA} = Thermal Resistance of the Package

P_{Dmax} = Maximum Power Dissipation in the Package.

The maximum power dissipation actually produced by an IC is the total quiescent supply current times the total power supply voltage, plus the power in the IC due to the loads, or:

$P_{Dmax} = \sum_i [V_S * I_{Smax} + (V_{S+} - V_O) * I_L]$
When sourcing, and

$P_{Dmax} = \sum_i [V_S * I_{Smax} + (V_O - V_{S-}) * I_L]$
When sinking.

Where:
i = 1 to 4

V_S = Total Supply Voltage

I_{Smax} = Maximum Supply Current Per Amplifier

V_O = Maximum Output Voltage of the Application

I_L = Load current

R_L = Load Resistance = $(V_{S+} - V_O)/I_L = (V_O - V_{S-})/ I_L$

A calculation for R_L to prevent device from overheat can be easily solved by setting the two P_{Dmax} equations equal to each other.

Pin Count	Θja (oC/W)	Θjc (C/W)	
TQFP-48	67	31	Normal
TQFP-48	31	15	EXPOSED PAD

Driving Capacitive Loads
The EC5575 is designed to drive a wide range of capacitive loads. In addition, the output current handling capability of the device allows for good slewing characteristics even with large capacitive loads. The combination of these features make the EC5575 ideally for applications such as TFT LCD panel grayscale reference voltage buffers, ADC input amplifiers, etc.

As load capacitance increases, however, the -3dB bandwidth of the device will decrease and the peaking increase. The amplifiers drive 10pF loads in parallel with10KΩ. with just 1.5dB of peaking, and 100pF with 6.4dB of peaking. If less peaking is desired in these applications, a small series resistor (usually between 5Ω and 50Ω) can be placed in series with the output. However, this will obviously reduce the gain slightly. Another method of reducing peaking is to add a "snubber" circuit at the output. A snubber is a shunt load consisting of a resistor in series with a capacitor. Values of 150Ω and 10nF are typical. The advantage of a snubber is that it improves the settling and overshooting performance while does not draw any DC load current or reduce the gain.

Power Supply Bypassing and Printed Circuit Board Layout
With high phase margin, the EC5575 performs stable gain at high frequency. Like any high-frequency device, good layout of the printed circuit board usually comes with optimum performance. Ground plane construction is highly recommended, lead lengths should be as short as possible and the power supply pins must be well bypassed to reduce the risk of oscillation. For normal single supply operation, where the V_S- pin is connected to ground, a 0.1 μF ceramic capacitor should be placed from V_{S+} pin to V_{S-} pin as a bypassing capacitor. A 4.7μF tantalum capacitor should then be connected in parallel, placed in the region of the amplifier. One 4.7μF capacitor may be used for multiple devices. This same capacitor combination should be placed at each supply pin to ground if split supplies are to be used.

■ Application Circuits



■ PACKAGE MARKING INDICATION (PACKAGE TYPE TQFP 48)





LEAD FREE TQFP48 (MAKING)

■ OUTLINE DIMENSIONS (Dimensions shown in millimeters)



OUTLINE DIMENSIONS

H: Exposed pad (3.05x3.05 mm)



VARIATIONS (ALL DIMENSIONS SHOWN IN MM)

SYMBOLS	MIN.	NOM.	MAX.
A	---	---	1.20
A1	0.05	---	0.15
A2	0.95	1.00	1.05
b	0.17	0.20	0.23
c	0.09	---	0.16
D	9.00 BSC		
D1	7.00 BSC		
E	9.00 BSC		
E1	7.00 BSC		
e	0.50 BSC		
L	0.45	0.60	0.75
L1	1.00 REF		
θ	0°	3.5°	7°

⚠ THERMALLY ENHANCED DIMENSIONS(SHOWN IN MM)

PAD SIZE	E2		D2	
	MIN.	MAX.	MIN.	MAX.
160x16E	3.05	4.06	3.05	4.06

NOTES:
1.JEDEC OUTLINE :
MS-026 ABC
MS-026 ABC-HD(THERMALLY ENHANCED VARIATIONS ONLY)
2.DATUM PLANE ⓗ IS LOCATED AT THE BOTTOM OF THE MOLD PARTING LINE COINCIDENT WITH WHERE THE LEAD EXITS THE BODY.
3.DIMENSIONS D1 AND E1 DO NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.25 mm PER SIDE. DIMENSIONS D1 AND E1 DO INCLUDE MOLD MISMATCH AND ARE DETERMINED AT DATUM PLANE ⓗ.
4.DIMENSION b DOES NOT INCLUDE DAMBAR PROTRUSION.

E-CMOS CORPORATION

DWN: Berlin		SIZE:	
CHK: Tina		DWG NO: J1-C0048-001	
APPD: Erik		FILE: J1-C0048-001-02	REV: 02
			SHT: 1

16L THIN PLASTIC QUAD FLAT PACKAGE OUTLINE
7X7X1.0 BODY 4RL DATA SHEET
(FOOTPRINT: 2.0 mm)

General Disclaimer:

1. Product information and specifications furnished by E-CMOS in this data sheets are in effect as of the publication date shown and are believed to be accurate and reliable. However, no responsibility is assumed by E-CMOS for the use of any information shown herein, nor for any patent or other rights infringement.
2. No license is granted by implication or otherwise under any patent or industrial properties owned by E-CMOS or any third party through this document.
3. The information herein is subject to change at any time without notice.
4. Neither reproduction nor duplication of this document, in any form, the whole or part is allowed without the prior written approval from E-CMOS.
5. Products of E-CMOS Corp., unless otherwise specified, are not authorized for use as critical components of any device or equipment in applications that demand extremely high reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aircraft, vehicles, nuclear power, radiation resistant system, transportation, disaster prevention equipment, gas related equipment, physical exercise equipment, safety equipment and medical equipment for life support, etc.
6. Although E-CMOS makes every attempt to ensure that its products are of high quality and reliability, thorough consideration of safety design and operating within the ranges guaranteed are strongly recommended to prevent any accident and damage that may ensue. E-CMOS bares no responsibility for failure or damage when abused or used beyond the guaranteed ranges.
7. Products applied to life support devices and systems are strongly requested to contact E-CMOS Corporation headquarter for the written approval to establish suitable terms & conditions. E-CMOS' warranty is limited to replacement of defective components. Any personal injury or death or any other consequential damages of property are not covered.

Copyright © 2002 by E-CMOS Corporation.

E-CMOS CORPORATION IC DATASHEET
ADDRESS: NO.1, CREATION RD. 2ND, SCIENCE-BASED INDUSTRIAL PARK, HSIN-CHU 300, TAIWAN, R.O.C.
WEBSITE: http://www.ecmos.com.tw
E-MAIL: mailto:sales@ecmos.com.tw
TEL: 886-3-5785888
FAX: 886-3-5783630

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.