Low Output Voltage Low Dropout Regulator

■ GENERAL DESCRIPTION

The NJM2841 is a low output voltage, low drop out regulators.
It delivers up to 500mA output current with the output voltage of 0.8 to 2.5V.
The use of an external bias voltage can improve the transient response and the ripple rejection characteristics while maintaining minimum input to output voltage.

■ PACKAGE OUTLINE



NJM2841F



NJM2841U2

■ FEATURES

- Output Voltage Range 0.8V to 2.5V
- High Ripple Rejection 86 dB typ. (V_O=1.2V version)
- Output Noise Voltage V_{NO}=40μVrms(V_O=1.2V version)
- Output Current I_O(min)=500mA
- High Precision Output V_O±1.0%
- Dual Supply Voltage Type V_{IN}, V_{BIAS}(sequence free)
- High Stability for Load 0.002%/mA (max)
- Output Capacitor with 4.7μF ceramic capacitor
- Low Dropout Voltage 0.1V typ. @I_O=300mA
- ON/OFF Control
- Built-in Thermal Overload Protection and Over Current Protection
- Bipolar Technology
- Package Outline SOT-23-5, SOT-89-5

■ PIN CONNECTION



1. CONTROL
2. GND
3. V_{OUT}
4. V_{IN}
5. V_{BIAS}

NJM2841F



1. V_{OUT}
2. GND
3. CONTROL
4. V_{BIAS}
5. V_{IN}

NJM2841U2

■ BLOCK DIAGRAM



■ OUTPUT VOLTAGE RANK LIST

Device Name	V_{out}	Device Name	V_{out}	Device Name	V_{out}
NJM2841F008	0.8V	NJM2841F017	1.7V	NJM2841U2-012	1.2V
NJM2841F009	0.9V	NJM2841F018	1.8V		
NJM2841F010	1.0V	NJM2841F019	1.9V		
NJM2841F011	1.1V	NJM2841F020	2.0V		
NJM2841F012	1.2V	NJM2841F021	2.1V		
NJM2841F013	1.3V	NJM2841F022	2.2V		
NJM2841F014	1.4V	NJM2841F023	2.3V		
NJM2841F015	1.5V	NJM2841F024	2.4V		
NJM2841F016	1.6V	NJM2841F025	2.5V		

Output Voltage Range: 0.8V to 2.5V (0.1V step)

■ ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

PARAMETER	SYNBOL	RATINGS		UNIT
Input Voltage	V_{IN}	+10		V
Bias Voltage	V_{BIAS}	+10		V
Control Voltage	V_{CONT}	+10		V
Power Dissipation	P_D	SOT-23-5	480(*1)	mW
			640(*2)	
		SOT-89-5	625(*3)	
			2400(*4)	
Operating Temperature	Topr	-40 ~ +85		°C
Storage Temperature	Tstg	-50 ~ +150		°C

(*1): Mounted on glass epoxy board. (76.2 × 114.3 × 1.6mm:based on EIA/JDEC standard, 2Layers)

(*2): Mounted on glass epoxy board. (76.2 × 114.3 × 1.6mm:based on EIA/JDEC standard, 4Layers), internal Cu area: 74.2 × 74.2mm

(*3): Mounted on glass epoxy board. (76.2 × 114.3 × 1.6mm:based on EIA/JDEC standard size, 2Layers, Cu area 100mm^2)

(*4): Mounted on glass epoxy board. (76.2 × 114.3 × 1.6mm:based on EIA/JDEC standard, 4Layers)

(For 4Layers: Applying 74.2 × 74.2mm inner Cu area and a thermal via hole to a board based on JEDEC standard JESD51-5)

■ BIAS VOLTAGE RANGE

V_{BIAS}= +2.5V to +10V (V_O<1.5V)

V_{BIAS}= V_O+1V to +10V (V_O≥1.5V)

■ ELECTRICAL CHARACTERISTICS

(V_{BIAS}=2.5V(V_O≥1.5V : V_{BIAS}=V_O+1V), V_{IN}=V_O+1V, C_{BIAS}=0.1µF, C_{IN}=4.7µF, Co=4.7µF, Ta=25˚C)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Voltage	V_O	I_O=30mA	-1.0%	-	+1.0%	V
Unloaded Bias Current	I_{BIAS}	I_O=0mA, except I_{CONT}	-	180	300	µA
Unloaded Input Current	I_{IN}	I_O=0mA, except I_{CONT}	-	-	20	µA
Bias Current at Control OFF	$I_{BIAS(OFF)}$	V_{CONT}=0V	-	-	100	nA
Input Current at Control OFF	$I_{IN(OFF)}$	V_{CONT}=0V	-	-	100	nA
Output Current	I_O	V_O x 0.9V	500	650	-	mA
Line Regulation 1 (V_{BIAS})	$\Delta V_O/\Delta V_{BIAS}$	V_{BIAS}=2.5V to V_O+6V(V_O<1.5V) V_{BIAS}=V_O+1V to V_O+6V(V_O≥1.5V) I_O=30mA	-	-	0.10	%/V
Line Regulation 2 (V_{IN})	$\Delta V_O/\Delta V_{IN}$	V_{IN}=V_O+1V to V_O+6V, I_O=30mA	-	-	0.10	%/V
Load Regulation	$\Delta V_O/\Delta I_O$	I_O=30 to 500mA	-	-	0.002	%/mA
Dropout Voltage	ΔV_{I-O}	I_O=300mA	-	0.10	0.18	V
Ripple Rejection Ratio 1 (V_{BIAS})	RR1(V_{BIAS})	V_{BIAS}=3.5V, e_{BIAS}=200mVrms, f=1kHz, I_O=10mA	Refer to Table 1			dB
Ripple Rejection Ratio 2 (V_{IN})	RR2(V_{IN})	e_{IN}=200mVrms, f=1kHz, I_O=10mA	Refer to Table 1			dB
Average Temperature Coefficient of Output Voltage	$\Delta V_O/\Delta Ta$	Ta=0 to +85°C, I_O=10mA	-	±50	-	ppm/°C
Output Noise Voltage	V_{NO}	f=10Hz to 80kHz, I_O=10mA	Refer to Table 1			µVrms
Control Current	I_{CONT}	V_{CONT}=1.6V	-	3	12	µA
Control Voltage for ON-state	$I_{CONT(ON)}$		1.6	-	-	V
Control Voltage for OFF-state	$V_{CONT(ON)}$		-	-	0.6	V
Bias Voltage	V_{BIAS}		-	-	10	V
Input Voltage	V_{IN}		-	-	9	V

• Table1

PARAMETER	SYMBOL	TEST CONDITION		MIN.	TYP.	MAX.	UNIT
Ripple Rejection Ratio 1 (V_{BIAS})	RR(V_{BIAS})	V_{BIAS}=3.5V, e_{BIAS}=200mVrms, f=1kHz, Io=10mA	V_O=0.8V	-	80	-	dB
			V_O=0.9V	-	80	-	
			V_O=1.0V	-	79	-	
			V_O=1.2V	-	77	-	
			V_O=1.5V	-	75	-	
		V_{BIAS}=4.5V, e_{BIAS}=200mVrms, f=1kHz, Io=10mA	V_O=2.5V	-	70	-	
Ripple Rejection Ratio 2 (V_{IN})	RR(V_{IN})	e_{in}=200mVrms, f=1kHz, Io=10mA	V_O=0.8V	-	87	-	dB
			V_O=0.9V	-	87	-	
			V_O=1.0V	-	87	-	
			V_O=1.2V	-	86	-	
			V_O=1.5V	-	85	-	
			V_O=2.5V	-	75	-	
Output Noise Voltage	V_{NO}	f=10Hz~80kHz, Io=10mA,	V_O=0.8V	-	27	-	µVrms
			V_O=0.9V	-	30	-	
			V_O=1.0V	-	34	-	
			V_O=1.2V	-	40	-	
			V_O=1.5V	-	48	-	
			V_O=2.5V	-	75	-	

■ POWER DISSIPATION vs. AMBIENT TEMPERATURE





■ TEST CIRCUIT



■ TYPICAL APPLICATION

a) In case of where ON/OFF control is not required:



Connect control pin to V_{BIAS} pin.
Though the I_{CONT} decreases by inserting "R" to between Control pin and V_{BIAS} pin, the minimum operating voltage is increased due to the resistor "R".

b) In use of ON/OFF control:



State of control pin:
"H" → output is enabled.
"L" or "open" → output is disabled.

* Bias Capacitor C_{BIAS} and an Input Capacitor C_{IN}

C_{BIAS} and C_{IN} are required to prevent oscillation and reduce power supply ripple for applications when high power supply impedance or a long power supply line.

Therefore, use recommended C_{BIAS} and C_{IN} value (refer to conditions of ELECTRIC CHARACTERISTIC) or larger and should connect between V_{BIAS} - GND, V_{IN} - GND as shortest path as possible to avoid the problem.

*Output Capacitor C_O

Output capacitor (C_O) will be required for a phase compensation of the internal error amplifier.

The capacitance and the equivalent series resistance (ESR) influence to stable operation of the regulator.

Use of a smaller C_O may cause excess output noise or oscillation of the regulator due to lack of the phase compensation.

On the other hand, Use of a larger C_O reduces output noise and ripple output, and also improves output transient response when rapid load change.

Therefore, use the recommended C_O value (refer to conditions of ELECTRIC CHARACTERISTIC) or larger and should connect between GND and V_{OUT} as shortest path as possible for stable operation

In addition, you should consider varied characteristics of capacitor (a frequency characteristic, a temperature characteristic, a DC bias characteristic and so on) and unevenness peculiar to a capacitor supplier enough.

When selecting C_O, recommend that have withstand voltage margin against output voltage and superior temperature characteristic though this product is designed stability works with wide range ESR of capacitor including low ESR products.

■ TYPICAL CHRACTERISTICS

NJM2841_1.2V
Output Voltage vs. Input Voltage



NJM2841_1.2V
Output Voltage vs. Input Voltage



NJM2841_1.2V
Output Voltage vs. Output Current



NJM2841_1.2V
Ground Pin Current vs. Output Current



NJM2841_1.2V
Control Current vs. Control Voltage



NJM2841_1.2V
Output Voltage vs. Control Voltage



NJM2841_1.2V
Load Regulation vs. Output Current



NJM2841_1.2V
Peak Output Current vs. Input Voltage



NJM2841_1.2V
Quiescent Current v.s. Input Voltage



NJM2841_1.2V
Quiescent Current v.s. Input Voltage



NJM2841_1.2V
Dropout Voltage vs. Output Current



NJM2841_1.2V
Output Noise Voltage vs. Output Current



NJM2841_1.2V
Ripple Rejection Ratio[Vbias] v.s. Frequency



NJM2841_1.2V
Ripple Rejection(Vin-Vout) vs. Output Current



NJM2841_1.2V
Ripple Rejection(Vbias-Vout) vs. Output Current



NJM2841_1.2V
Equivalent Serise Resistance vs. Output Current



NJM2841_1.2V
Control Voltage v.s. Temperature



NJM2841_1.2V
Output Voltage v.s. Temperature



NJM2841_1.2V
Peak Output Current v.s. Temperature



NJM2841_1.2V
Quiescent Current v.s. Temperature



NJM2841_1.2V
Line Regulation(VIN) v.s. Temperature



NJM2841_1.2V
Line Regulation(VBIAS) v.s. Temperature



NJM2841_1.2V
Load Regulation v.s. Temperature



NJM2841_1.2V
Output Voltage v.s. Temperature



NJM2841_1.2V
Short Circuit Current v.s. Temperature



NJM2841 1.2V
ON/OFF Transient Response



NJM2841 1.2V
ON/OFF Transient Response Without Load



NJM2841 1.2V
Load Transient Response



NJM2841 1.2V
Line Transient Response



NJM2841 1.2V
Line Transient Response



[CAUTION]
The specifications on this datasheet are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this datasheet are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.