Good Transient Response Low Voltage 500mA LDO

NO.EA-241-190523

OUTLINE

The RP111x Series are CMOS-based LDO regulators featuring 500mA output current. The input voltage is as low as 1.4V and the output voltage can be set from 0.7V. Due to a built-in 0.46Ω (at V_{OUT}=2.8V) on-resistor, RP111x can provide a low dropout voltage. RP111x also features an excellent line transient response, ripple rejection at 75dB, and low noise. The output voltage accuracy is as high as ±0.8% and the temperature drift coefficient of output voltage is low at ±30ppm/°C. The accuracy of the output voltage of RP111x includes the temperature characteristics and the load transient response has been improved. The typ. and max value of under/overshoot for various output current are shown in the typical characteristics in the datasheet, therefore the accuracy of the output voltage estimation will be easy on the actual operating cases.

In addition to a fold-back protection circuit built into conventional regulators, RP111x contains a thermal shutdown circuit and an inrush current limit circuit. SOT-23-5 and SOT-89-5 packages, a 1.2mm square DFN1212-6 package are available.

FEATURES


- Supply Current ..... Typ. 80μA
- Standby Current ..... Typ. 0.1μA
- Dropout Voltage ..... Typ. 0.23V (I_{OUT}=500mA, V_{OUT}=2.5V)
- Ripple Rejection ..... Typ. 75dB (f=1kHz)
  Typ. 70dB (f=10kHz)
- Output Voltage Accuracy ..... ±0.8% (V_{OUT} ≥1.8V)
- Output Voltage Temperature Coefficient ..... Typ. ±30ppm/°C (V_{OUT} ≥1.8V)
- Line Regulation ..... Typ. 0.02%/V
- Packages DFN1212-6, SOT-23-5, SOT-89-5,
- Input Voltage Range ..... 1.4V to 5.25V
- Output Voltage Range ..... 0.7V to 3.6V (0.1V steps)
  (For other voltages, please refer to MARK INFORMATIONS.)
- Built-in Foldback Protection Circuit ..... Typ. 50mA (Current at short mode)
- Thermal Shutdown Temperature ..... 165°C
- Inrush Current Limit ..... Typ.400mA (for 180μs after start-up)
- Ceramic capacitors are recommended to be used with this IC .....1.0μF or more

APPLICATIONS


- Power source for portable communication equipment.
- Power source for electrical appliances such as cameras, VCRs and camcorders.
- Power source for battery-powered equipments.
- Power source for electrical home appliances.

BLOCK DIAGRAMS

RP111xxx1B



RP111xxx1D



SELECTION GUIDE

The output voltage, auto discharge function, package for the ICs can be selected at the user's request.

Product Name	Package	Quantity per Reel	Pb Free	Halogen Free
RP111Lxx1∗-TR	DFN1212-6	5,000 pcs	Yes	Yes
RP111Nxx1∗-TR-FE	SOT-23-5	3,000 pcs	Yes	Yes
RP111Hxx1∗-T1-FE	SOT-89-5	1,000 pcs	Yes	Yes


xxx: The output voltage can be designated in the range of 0.7V(07)to 3.6V(36)in 0.1V steps.
(For other voltages, please refer to MARK INFORMATIONS.)

∗ : Auto discharge function at off state are options as follows.
(B) without auto discharge function at off state
(D) with auto discharge function at off state


PIN CONFIGURATIONS

DFN1212-6


Top View




Bottom View



SOT-23-5



SOT-89-5



PIN DESCRIPTIONS

- **DFN1212-6**

Pin No.	Symbol	Description
1	V_{OUT}	Output Pin
2	V_{FB}	Feed Back Pin
3	GND	Ground Pin
4	CE	Chip Enable Pin ("H" Active)
5	NC	No connection
6	V_{DD}	Input Pin

∗) Tab is GND level. (They are connected to the reverse side of this IC.)
The tab is better to be connected to the GND, but leaving it open is also acceptable.

- **SOT-23-5**

Pin No	Symbol	Pin Description
1	V_{DD}	Input Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin ("H" Active)
4	V_{FB}	Feed Back Pin
5	V_{OUT}	Output Pin

- **SOT-89-5**

Pin No	Symbol	Pin Description
1	V_{FB}	Feed Back Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin ("H" Active)
4	V_{DD}	Input Pin
5	V_{OUT}	Output Pin

Under normal conditions, please connect the V_{OUT} pin to the V_{FB} pin. However, in the case of adjusting the output voltage with the V_{FB} pin, please follow the " ADJUSTABLE OUTPUT VOLTAGE SETTING".

ABSOLUTE MAXIMUM RATINGS

Symbol	Item	Rating	Unit
V_{IN}	Input Voltage	6.0	V
V_{CE}	Input Voltage (CE Pin)	-0.3～6.0	V
V_{OUT}	Output Voltage	−0.3 to V_{IN}+0.3	V
I_{OUT}	Output Current	510	mA
P_D	Power Dissipation (DFN1212-6)*	600	mW
	Power Dissipation (SOT-23-5) *	420	
	Power Dissipation (SOT-89-5)*	900	
Ta	Operating Temperature Range	−40 to 85	°C
Tstg	Storage Temperature Range	−55 to 125	°C

∗) For Power Dissipation, please refer to PACKAGE INFORMATION.

ABSOLUTE MAXIMUM RATINGS

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause permanent damage and may degrade the life time and safety for both device and system using the device in the field. The functional operation at or over these absolute maximum ratings is not assured.

ELECTRICAL CHARACTERISTICS

Unless otherwise noted, V_{IN}=Set V_{OUT} +1.0V(V_{OUT} >1.5), V_{IN}=2.5V(V_{OUT} ≤ 1.5V), I_{OUT}=1mA, C_{IN}=C_{OUT}=1.0μF.
The specifications surrounded by ▭ are guaranteed by Design Engineering at −40°C ≤ Ta ≤ 85°C.

- RP111xxx1B/D

Ta=25°C

Symbol	Item	Conditions		Min.	Typ.	Max.	Unit
V_{OUT}	Output Voltage	Ta=25°C	V_{OUT} ≥ 1.8V	×0.992		×1.008	V
			V_{OUT} < 1.8V	−18		+18	mV
		-40°C ≤ Ta ≤ 85°C	V_{OUT} ≥ 1.8V	×0.985		×1.015	V
			V_{OUT} < 1.8V	−55		50	mV
I_{OUT}	Output Current			500			mA
$\Delta V_{OUT}/\Delta I_{OUT}$	Load Regulation	1mA ≤ I_{OUT} ≤ 500mA			1	20	mV
V_{TRLD}	Load Transient Response	I_{OUT} :1mA⇔250mA (tr=tf=0.5μs)	C_{OUT}=1μF		−75 +45		mV
			C_{OUT}=2.2μF		−55 +35		
		I_{OUT} 1mA⇔250mA (tr=tf=5.0μs)	C_{OUT}=1μF		−20 +15		
V_{DIF}	Dropout Voltage	Please refer to “Dropout Voltage”.					
I_{SS}	Supply Current	I_{OUT}=0mA			80	125	μA
$I_{standby}$	Standby Current	V_{CE}=0V			0.1	1.0	μA
$\Delta V_{OUT}/\Delta V_{IN}$	Line Regulation	Set V_{OUT}+0.5V ≤ V_{IN} ≤ 5.25V, V_{IN} ≥ 1.4V			0.02	0.10	%/V
V_{TRLN}	Input Transient Response	V_{IN} : Set V_{OUT}+0.5V⇔ Set V_{OUT}+1.5V(tr=tf=5.0μs), V_{IN} ≥ 1.4V,I_{OUT}=30mA			−1.5 +1.5		mV
RR	Ripple Rejection	f=1kHz,Ripple0.2Vp-p, V_{IN}=Set V_{OUT}+1.0V,I_{OUT}=30mA (V_{OUT} ≤ 2.0V, V_{IN}=3.0V)			75		dB
V_{IN}	Input Voltage*			1.4		5.25	V
$\Delta V_{OUT}/\Delta Ta$	Output Voltage Temperature Coefficient	40°C ≤ Ta ≤ 85°C	V_{OUT} ≥ 1.8V		±30		ppm /°C
			V_{OUT} < 1.8V		±100		
I_{SC}	Short Current Limit	V_{OUT}=0V			50		mA
I_{PD}	CE Pull-down Current				0.3	0.6	μA
V_{CEH}	CE Input Voltage "H"			1.0			V
V_{CEL}	CE Input Voltage "L"					0.4	V
T_{TSD}	Thermal Shutdown Temperature	Junction Temperature			165		°C
T_{TSR}	Thermal Shutdown Released Temperature	Junction Temperature			100		
en	Output Noise	BW=10Hz~100kHz	V_{OUT} ≥ 1.8V		20× V_{OUT}		μVrms
			V_{OUT} < 1.8V		40× V_{OUT}		

ELECTRICAL CHARACTERISTICS

Unless otherwise noted, V_{IN}=Set V_{OUT} +1.0V(V_{OUT} >1.5), V_{IN}=2.5V(V_{OUT} ≤ 1.5V), I_{OUT}=1mA, C_{IN}=C_{OUT}=1.0μF.
The specifications surrounded by ▭ are guaranteed by Design Engineering at −40°C ≤ Ta ≤ 85°C.

- RP111xxx1B/D

Ta=25°C

Symbol	Item	Conditions	Min.	Typ.	Max.	Unit
R_{LOW}	Low Output Nch Tr. ON Resistance (of D version)	V_{IN}=4.0V, V_{CE}=0V		60		Ω

All of units are tested and specified under load conditions such that Tj≈Ta=25°C except for Output Voltage Temperature Coefficient, Load Transient Response, Input Transient Response, Output Noise and Ripple Rejection.
∗) When Input Voltage is 5.5V, the total operational time must be within 500hrs.

- **Dropout Voltage**


Ta=25°C

Output Voltage V_{OUT} (V)	Dropout Voltage V_{DIF} (V)		
	Condition	Typ.	Max.
0.7 ≤ V_{OUT} < 0.8	I_{OUT}=500mA	0.58	0.88
0.8 ≤ V_{OUT} < 0.9		0.52	0.80
0.9 ≤ V_{OUT} < 1.0		0.45	0.70
1.0 ≤ V_{OUT} < 1.2		0.42	0.64
1.2 ≤ V_{OUT} < 1.4		0.35	0.53
1.4 ≤ V_{OUT} < 1.8		0.31	0.48
1.8 ≤ V_{OUT} < 2.1		0.27	0.41
2.1 ≤ V_{OUT} < 2.5		0.25	0.38
2.5 ≤ V_{OUT} < 3.0		0.23	0.34
3.0 ≤ V_{OUT} ≤ 3.6		0.22	0.32

RECOMMENDED OPERATING CONDITIONS (ELECTRICAL CHARACTERISTICS)

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if they are used over such conditions by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

TYPICAL APPLICATIONS



External Parts Example:
C1, C2: Ceramic Capacitor 1.0µF, Murata, GRM155B31A105KE15

Under normal conditions, please connect the V_{OUT} pin to the V_{FB} pin. However, in the case of adjusting the output voltage with the V_{FB} pin, please follow the " ADJUSTABLE OUTPUT VOLTAGE SETTING".

TECHNICAL NOTES

Phase Compensation

In these ICs, phase compensation is made for securing stable operation even if the load current is varied. For this purpose, use a 1.0µF or more capacitor C2.

In case of using a tantalum capacitor, the output may be unstable due to inappropriate ESR. Therefore, the full range of operating conditions for the capacitor in the application should be considered.

PCB Layout

Make V_{DD} and GND lines sufficient. If their impedance is high, noise pickup or unstable operation may result. Connect a capacitor C1 with a capacitance value as much as 1.0µF or more between V_{DD} and GND pin, and as close as possible to the pins.

Set external components, especially the output capacitor C2, as close as possible to the ICs, and make wiring as short as possible.

ADJUSTABLE OUTPUT VOLTAGE SETTING

Output Voltage Setting

RP111x is capable of adjusting the output voltage by using the external divider resistors.
If the V_{FB} voltage fixed in the device is described as setV_{FB}, the output voltage can be set by using the following formulas.

$$I1 = I_{IC} + I2 \quad \cdots (1)$$
$$I2 = setV_{FB} / R2 \quad \cdots (2)$$

Thus,

$$I1 = I_{IC} + setV_{FB} / R2 \quad \cdots (3)$$

Therefore,

$$V_{OUT} = setV_{FB} + R1 \times I1 \quad \cdots (4)$$

Put formula (3) into formula (4), then

$$V_{OUT} = setV_{FB} + R1 \times (I_{IC} + setV_{FB} / R2)$$
$$= setV_{FB} \times (1 + R1/R2) + R1 \times I_{IC} \quad \cdots (5)$$

In formula (5), R1x I_{IC} is the error-causing factor in V_{OUT}.
As for I_{IC},


$$I_{IC} = setV_{FB} / R_{IC} \quad \cdots (6)$$

Therefore, the error-causing factor R1x I_{IC} can be described as follows.

$$R1 \times I_{IC} = R1 \times setV_{FB} / R_{IC}$$
$$= setV_{FB} \times R1 / R_{IC} \quad \cdots (7)$$


For better accuracy, choosing R1 (<<R_{IC}) reduces this error.
Without the error-causing factor R1x I_{IC}, the output voltage can be calculated by the following formula.

$$V_{OUT} = setV_{FB} \times ((R1 + R2) / R2) \quad \cdots (8)$$




The output voltage of the externally adjustable output voltage type should be set to 3.6 V or less.
The resistance of R2 should be 16 kΩ or less.

The graph below shows the relation between the V_{FB} pin voltage (setV_{FB}) and the internal resistance of the V_{FB} pin (R_{IC}). For example, R_{IC} will be 200 kΩ typically if setV_{FB} is 0.7 V.



V_{FB} Pin Voltage (setV_{FB}) vs. Internal Resistance (R_{IC})

Typical Applications for Adjustable Output Voltage Setting



Phase Compensation

Similar to the Fixed Output Voltage Type, Phase compensation is made for the Adjustable Output Voltage Type for securing stable operation even if the load current is varied. For this purpose, use a 4.7µF or more capacitor C2 between V_{OUT} pin and GND pin, and as close as possible to the pins.

PCB Layout

Make V_{DD} and GND lines sufficient. If their impedance is high, noise pickup or unstable operation may result. Connect a capacitor C1 with a capacitance value as much as 1.0µF or more between V_{DD} and GND pin, and as close as possible to the pins.

Transient Response

When using the Adjustable Output Voltage Type, the transient response could be affected by the external resistors. Evaluate the circuit taking the actual conditions of use into account.


TRANSIENT RESPONSE


The RP111x Series have been improved in overall output voltage characteristics including temperature and transient response. The load transient response indicated under the Electrical Characteristics is guaranteed by design based on the condition when I_{OUT} changes from 1mA to 250mA or 250mA to1mA. The output voltage variations under the other load conditions, the characteristic examples are shown below.

RP111x151x


V_{IN}=2.5V, -40°C≦Ta≦85°C


C_{IN}=1.0µF, C_{OUT}=1.0µF, I_{OUT}=1mA⇔Peak Output Current (tr=tf=0.5µs)







C_{IN}=1.0µF, C_{OUT}=2.2µF, I_{OUT}=1mA⇔ Peak Output Current (tr=tf=0.5µs)





C_{IN}=1.0µF, C_{OUT}=1.0µF, I_{OUT}=1mA⇔ Peak Output Current (tr=tf=5.0µs)







RP111x281x


V_{IN}=3.8V, -40°C≦Ta≦85°C


C_{IN}=1.0µF, C_{OUT}=1.0µF, I_{OUT}=1mA⇔ Peak Output Current (tr=tf=0.5µs)







C_{IN}=1.0µF, C_{OUT}=2.2µF, I_{OUT}=1mA⇔ Peak Output Current (tr=tf=0.5µs)






C_{IN}=1.0µF, C_{OUT}=1.0µF, I_{OUT}=1mA⇔ Peak Output Current (tr=tf=5.0µs)






Input Transient Response has the output voltage dependency. Please refer to the characteristics examples below.

V_{IN}: Set V_{OUT}+0.5V⇔Set V_{OUT}+1.5V (tr=tf=5.0µs), V_{IN}≧1.4V,
C_{OUT}=1.0µF, I_{OUT}=30mA





The graphs shown above are reference data.

For the better transient response, a capacitor with higher capacitance is recommended and the wire impedance of GND and V_{OUT} should be minimized as possible.

The transient response characteristics depend on the external parts and PCB layout. Therefore, the operating conditions for the transient response in the application should be considered and evaluation is necessary.

Package Information

- **Power Dissipation (DFN1212-6)**


Power Dissipation (P_D) depends on conditions of mounting on board. This specification is based on the measurement at the condition below:


Measurement Conditions

	Standard Test Land Pattern
Environment	Mounting on Board (Wind velocity=0m/s)
Board Material	Glass cloth epoxy plastic (Double-sided)
Board Dimensions	40mm x 40mm x 1.6mm
Copper Ratio	Top side: Approx. 50%, Back side: Approx. 50%
Through-holes	ϕ 0.5mm x 28pcs

Measurement Result (Ta=25ºC, Tjmax=125ºC)

	Standard Test Land Pattern
Power Dissipation	600mW (Tjmax=125°C) 750mW (Tjmax=150°C)
Thermal Resistance	θja=(125-25°C)/0.6W=167°C/W
	θjc=30°C/W






Measurement Board Pattern


IC Mount Area (Unit: mm)

Note: The above graph shows the power dissipation of the package based on Tjmax=125ºC and Tjmax=150ºC.
Operating the IC within the shaded area in the graph might have an influence on its lifetime.
Operating time must be within the time limit described in the table below.

Operating Time	**Estimated Years (Operating 4 hrs/ day)**
13,000 hours	9 Years

- **Package Dimensions (DFN1212-6)**






Bottom View (Unit : mm)

* The tab is substrate level (GND).
The tab is better to be connected to the GND, but leaving it open is also acceptable.

- **Mark Specification (DFN1212-6)**

①②: Product Code …Refer to "RP111L Series Mark Specification Table (DFN1212-6)".
③④: Lot Number … Alphanumeric Serial Number



- **RP111L Series Mark Specification Table (DFN1212-6)**

RP111Lxx1B

Product Name	①②	Vset
RP111L071B	**7A**	0.7V
RP111L071B5	**7B**	0.75V
RP111L081B	**7C**	0.8V
RP111L091B	**7D**	0.9V
RP111L101B	**7E**	1.0V
RP111L111B	**7F**	1.1V
RP111L121B	**7G**	1.2V
RP111L121B5	**7H**	1.25V
RP111L131B	**7J**	1.3V
RP111L141B	**7K**	1.4V
RP111L151B	**7L**	1.5V
RP111L161B	**7M**	1.6V
RP111L171B	**7N**	1.7V
RP111L181B	**7P**	1.8V
RP111L181B5	**7Q**	1.85V
RP111L191B	**7R**	1.9V
RP111L201B	**7S**	2.0V
RP111L211B	**7T**	2.1V
RP111L221B	**7U**	2.2V
RP111L231B	**7V**	2.3V
RP111L241B	**7W**	2.4V
RP111L251B	**7X**	2.5V
RP111L261B	**7Y**	2.6V
RP111L271B	**7Z**	2.7V
RP111L281B	**8A**	2.8V
RP111L281B5	**8B**	2.85V
RP111L291B	**8C**	2.9V
RP111L301B	**8D**	3.0V
RP111L311B	**8E**	3.1V
RP111L321B	**8F**	3.2V
RP111L331B	**8G**	3.3V
RP111L341B	**8H**	3.4V
RP111L351B	**8J**	3.5V
RP111L361B	**8K**	3.6V
RP111L101B5	**8L**	1.05V

RP111Lxx1D

Product Name	①②	Vset
RP111L071D	**9A**	0.7V
RP111L071D5	**9B**	0.75V
RP111L081D	**9C**	0.8V
RP111L091D	**9D**	0.9V
RP111L101D	**9E**	1.0V
RP111L111D	**9F**	1.1V
RP111L121D	**9G**	1.2V
RP111L121D5	**9H**	1.25V
RP111L131D	**9J**	1.3V
RP111L141D	**9K**	1.4V
RP111L151D	**9L**	1.5V
RP111L161D	**9M**	1.6V
RP111L171D	**9N**	1.7V
RP111L181D	**9P**	1.8V
RP111L181D5	**9Q**	1.85V
RP111L191D	**9R**	1.9V
RP111L201D	**9S**	2.0V
RP111L211D	**9T**	2.1V
RP111L221D	**9U**	2.2V
RP111L231D	**9V**	2.3V
RP111L241D	**9W**	2.4V
RP111L251D	**9X**	2.5V
RP111L261D	**9Y**	2.6V
RP111L271D	**9Z**	2.7V
RP111L281D	**0A**	2.8V
RP111L281D5	**0B**	2.85V
RP111L291D	**0C**	2.9V
RP111L301D	**0D**	3.0V
RP111L311D	**0E**	3.1V
RP111L321D	**0F**	3.2V
RP111L331D	**0G**	3.3V
RP111L341D	**0H**	3.4V
RP111L351D	**0J**	3.5V
RP111L361D	**0K**	3.6V
RP111L101D5	**0L**	1.05V

• Power Dissipation (SOT-23-5)


Power Dissipation (P_D) depends on conditions of mounting on board. This specification is based on the measurement at the condition below:
(Power Dissipation (SOT-23-5) is substitution of SOT-23-6.)

Measurement Conditions


	Standard Test Land Pattern
Environment	Mounting on Board (Wind velocity=0m/s)
Board Material	Glass cloth epoxy plastic (Double-sided)
Board Dimensions	40mm x 40mm x 1.6mm
Copper Ratio	Top side: Approx. 50%, Back side: Approx. 50%
Through-holes	ϕ 0.5mm x 44pcs

Measurement Result (Ta=25°C)

	Standard Land Pattern	Free Air
Power Dissipation	420mW (Tjmax=125°C) 525mW (Tjmax=150°C)	250mW (Tjmax=125°C)
Thermal Resistance	θja=(125-25°C)/0.42W=238°C/W	400°C/W



Power Dissipation




Measurement Board Pattern

IC Mount Area (Unit: mm)

Note: The above graph shows the power dissipation of the package based on Tjmax=125ºC and Tjmax=150ºC.
Operating the IC within the shaded area in the graph might have an influence on its lifetime.
Operating time must be within the time limit described in the table below.

Operating Time	Estimated Years (Operating 4 hrs/ day)
13,000 hours	9 Years


- **Package Dimensions (SOT-23-5)**



Unit : mm

- **Mark Specification (SOT-23-5)**

①②③: Product Code … Refer to “RP111N Series Mark Specification Table”.
④⑤ : Lot Number … Alphanumeric Serial Number.



- **RP111N Series Mark Specification Table (SOT-23-5)**

RP111Nxx1B

Product Name	①②③	Vset
RP111N071B	**H07**	0.7V
RP111N081B	**H08**	0.8V
RP111N091B	**H09**	0.9V
RP111N101B	**H10**	1.0V
RP111N111B	**H11**	1.1V
RP111N121B	**H12**	1.2V
RP111N131B	**H13**	1.3V
RP111N141B	**H14**	1.4V
RP111N151B	**H15**	1.5V
RP111N161B	**H16**	1.6V
RP111N171B	**H17**	1.7V
RP111N181B	**H18**	1.8V
RP111N191B	**H19**	1.9V
RP111N201B	**H20**	2.0V
RP111N211B	**H21**	2.1V
RP111N221B	**H22**	2.2V
RP111N231B	**H23**	2.3V
RP111N241B	**H24**	2.4V
RP111N251B	**H25**	2.5V
RP111N261B	**H26**	2.6V
RP111N271B	**H27**	2.7V
RP111N281B	**H28**	2.8V
RP111N291B	**H29**	2.9V
RP111N301B	**H30**	3.0V
RP111N311B	**H31**	3.1V
RP111N321B	**H32**	3.2V
RP111N331B	**H33**	3.3V
RP111N341B	**H34**	3.4V
RP111N351B	**H35**	3.5V
RP111N361B	**H36**	3.6V
RP111N071B5	**H37**	0.75V
RP111N121B5	**H38**	1.25V
RP111N181B5	**H39**	1.85V
RP111N281B5	**H40**	2.85V
RP111N101B5	**H41**	1.05V

RP111Nxx1D

Product Name	①②③	Vset
RP111N071D	**J07**	0.7V
RP111N081D	**J08**	0.8V
RP111N091D	**J09**	0.9V
RP111N101D	**J10**	1.0V
RP111N111D	**J11**	1.1V
RP111N121D	**J12**	1.2V
RP111N131D	**J13**	1.3V
RP111N141D	**J14**	1.4V
RP111N151D	**J15**	1.5V
RP111N161D	**J16**	1.6V
RP111N171D	**J17**	1.7V
RP111N181D	**J18**	1.8V
RP111N191D	**J19**	1.9V
RP111N201D	**J20**	2.0V
RP111N211D	**J21**	2.1V
RP111N221D	**J22**	2.2V
RP111N231D	**J23**	2.3V
RP111N241D	**J24**	2.4V
RP111N251D	**J25**	2.5V
RP111N261D	**J26**	2.6V
RP111N271D	**J27**	2.7V
RP111N281D	**J28**	2.8V
RP111N291D	**J29**	2.9V
RP111N301D	**J30**	3.0V
RP111N311D	**J31**	3.1V
RP111N321D	**J32**	3.2V
RP111N331D	**J33**	3.3V
RP111N341D	**J34**	3.4V
RP111N351D	**J35**	3.5V
RP111N361D	**J36**	3.6V
RP111N071D5	**J37**	0.75V
RP111N121D5	**J38**	1.25V
RP111N181D5	**J39**	1.85V
RP111N281D5	**J40**	2.85V
RP111N101D5	**J41**	1.05V

• Power Dissipation (SOT-89-5)


Power Dissipation (P_D) depends on conditions of mounting on board. This specification is based on the Measurement Conditions below.


Measurement Conditions

	High Wattage Land Pattern	Standard Land Pattern
Environment	Mounting on Board (Wind Velocity=0m/s)	Mounting on Board (Wind Velocity=0m/s)
Board Material	Glass Cloth Epoxy Plastic (Double-sided)	Glass Cloth Epoxy Plastic (Double-sided)
Board Dimensions	30mm x 30mm x 1.6mm	50mm x 50mm x 1.6mm
Copper Ratio	Topside: Approx. 20% Backside: Approx. 100%	Topside: Approx. 10% Backside: Approx. 100%
Through-hole	ϕ0.85mm x 10pcs	-


Measurement Result (Ta=25°C)

	High Wattage Land Pattern	Standard Land Pattern	Free Air
Power Dissipation	1300mW	900mW (Tjmax=125°C) 1125mW (Tjmax=150°C)	500mW
Thermal Resistance	77°C/W	111°C/W	200°C/W





Power Dissipation




IC Mount Area Unit: mm

Note: The above graph shows the power dissipation of the package based on Tjmax=125°C and Tjmax=150°C. Operating the IC within the shaded area in The graph might have an influence on its lifetime. Operating time must be within the time limit described in the table below.

Operating Time	Estimated years (Operating four hours/day)
13,000 hours	9 years


Package Dimensions (SOT-89-5)



Unit : mm

- **Mark Specification (SOT-89-5)**

①②③④: Product Code …Refer to “RP111H Series Mark Specification Table”.
⑤⑥ : Lot Number … Alphanumeric Serial Number



RP111H Series Mark Specification Table (SOT-89-5)


RP111Hxx1B

Product Name	①②③④	Vset
RP111H071B	**A07B**	0.7V
RP111H081B	**A08B**	0.8V
RP111H091B	**A09B**	0.9V
RP111H101B	**A10B**	1.0V
RP111H111B	**A11B**	1.1V
RP111H121B	**A12B**	1.2V
RP111H131B	**A13B**	1.3V
RP111H141B	**A14B**	1.4V
RP111H151B	**A15B**	1.5V
RP111H161B	**A16B**	1.6V
RP111H171B	**A17B**	1.7V
RP111H181B	**A18B**	1.8V
RP111H191B	**A19B**	1.9V
RP111H201B	**A20B**	2.0V
RP111H211B	**A21B**	2.1V
RP111H221B	**A22B**	2.2V
RP111H231B	**A23B**	2.3V
RP111H241B	**A24B**	2.4V
RP111H251B	**A25B**	2.5V
RP111H261B	**A26B**	2.6V
RP111H271B	**A27B**	2.7V
RP111H281B	**A28B**	2.8V
RP111H291B	**A29B**	2.9V
RP111H301B	**A30B**	3.0V
RP111H311B	**A31B**	3.1V
RP111H321B	**A32B**	3.2V
RP111H331B	**A33B**	3.3V
RP111H341B	**A34B**	3.4V
RP111H351B	**A35B**	3.5V
RP111H361B	**A36B**	3.6V
RP111H071B5	**A37B**	0.75V
RP111H121B5	**A38B**	1.25V
RP111H181B5	**A39B**	1.85V
RP111H281B5	**A40B**	2.85V
RP111H101B5	**A41B**	1.05V


RP111Hxx1D

Product Name	①②③④	Vset
RP111H071D	**A07D**	0.7V
RP111H081D	**A08D**	0.8V
RP111H091D	**A09D**	0.9V
RP111H101D	**A10D**	1.0V
RP111H111D	**A11D**	1.1V
RP111H121D	**A12D**	1.2V
RP111H131D	**A13D**	1.3V
RP111H141D	**A14D**	1.4V
RP111H151D	**A15D**	1.5V
RP111H161D	**A16D**	1.6V
RP111H171D	**A17D**	1.7V
RP111H181D	**A18D**	1.8V
RP111H191D	**A19D**	1.9V
RP111H201D	**A20D**	2.0V
RP111H211D	**A21D**	2.1V
RP111H221D	**A22D**	2.2V
RP111H231D	**A23D**	2.3V
RP111H241D	**A24D**	2.4V
RP111H251D	**A25D**	2.5V
RP111H261D	**A26D**	2.6V
RP111H271D	**A27D**	2.7V
RP111H281D	**A28D**	2.8V
RP111H291D	**A29D**	2.9V
RP111H301D	**A30D**	3.0V
RP111H311D	**A31D**	3.1V
RP111H321D	**A32D**	3.2V
RP111H331D	**A33D**	3.3V
RP111H341D	**A34D**	3.4V
RP111H351D	**A35D**	3.5V
RP111H361D	**A36D**	3.6V
RP111H071D5	**A37D**	0.75V
RP111H121D5	**A38D**	1.25V
RP111H181D5	**A39D**	1.85V
RP111H281D5	**A40D**	2.85V
RP111H101D5	**A41D**	1.05V


TEST CIRCUIT




Basic Test Circuit



Test Circuit for Supply Current



Test Circuit for Ripple Rejection




Test Circuit for Load Transient Response


TYPICAL CHARACTERISTICS

1）Output Voltage vs. Output Current（C1=1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




2）Output Voltage vs. Input Voltage（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




3）Supply Current vs. Input Voltage（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




4）Output Voltage vs. Temperature（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, I_{OUT}=1mA）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




5）Supply Current vs. Temperature（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, I_{OUT}=0mA）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




6）Dropout Voltage vs. Output Current（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF）


RP111x071x




RP111x171x




RP111x181x




RP111x281x



RP111x361x




7）Dropout Voltage vs. Set Output Voltage（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）




8）Dropout Voltage vs. Temperature（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF）


RP111x071x




RP111x171xx




RP111x181x



RP111x281x




RP111x361x




9）Ripple Rejection vs. Input Voltage（C1=none, C2=Ceramic 1.0μF, Ripple=0.2Vp-p, Ta=25°C）


RP111x071x




RP111x071x




RP111x171x




RP111x171x




RP111x181x




RP111x181x




RP111x281x




RP111x281x



RP111x361x




RP111x361x




10）Ripple Rejection vs. Frequency（C1=none, C2=Ceramic 1.0μF, Ripple=0.2Vp-p, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




11）Input Transient Response（C1=none, C2=Ceramic 1.0μF, I_{OUT}=30mA, tr=tf=5μs, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361x




12）Load Transient Response（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071x




RP111x071x




RP111x071x




RP111x071x




RP111x071x




RP111x071x




RP111x171x




RP111x171x




RP111x171x




RP111x171x




RP111x171x




RP111x171x




RP111x181x




RP111x181x




RP111x181x




RP111x181x




RP111x181x




RP111x181x




RP111x281x




RP111x281x




RP111x281x




RP111x281x




RP111x281x




RP111x281x




RP111x361x




RP111x361x




RP111x361x




RP111x361x



RP111x361x




RP111x361x




13）Turn on Speed with CE pin（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071x




RP111x171x




RP111x181x



RP111x281x




RP111x361




14) Turn off Speed with CE pin（C1=Ceramic 1.0μF, C2=Ceramic 1.0μF, Ta=25°C）


RP111x071D




RP111x171D




RP111x181D



RP111x281D




RP111x361D




15）Inrush Current（C1=Ceramic 1.0μF, I_{OUT}=0mA, Ta=25°C）


RP111x071x




RP111x071x




RP111x171x




RP111x171x




RP111x181x




RP111x181x




RP111x281x




RP111x281x



RP111x361x



RP111x361x




ESR vs. Output Current

When using these ICs, consider the following points: The relations between I_{OUT} (Output Current) and ESR of an output capacitor are shown below. The conditions when the white noise level is under 40µV (Avg.) are marked as the hatched area in the graph.


Measurement Conditions

Frequency Band : 10Hz to 2MHz
Temperature : −40˚C to 85˚C
C1,C2 :1.0µF or more


RP111x071x




RP111x171x




RP111x181x



RP111x281x



RP111x361x



1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to our sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of our company.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under our company's or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for use as general electronic components in standard applications (office equipment, telecommunication equipment, measuring instruments, consumer electronic products, amusement equipment etc.). Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death (aircraft, spacevehicle, nuclear reactor control system, traffic control system, automotive and transportation equipment, combustion equipment, safety devices, life support system etc.) should first contact us.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, fire containment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. The X-ray exposure can influence functions and characteristics of the products. Confirm the product functions and characteristics in the evaluation stage.
9. WLCSP products should be used in light shielded environments. The light exposure can influence functions and characteristics of the products under operation or storage.
10. There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact our sales or our distributor before attempting to use AOI.
11. Please contact our sales representatives should you have any questions or comments concerning the products or the technical information.

NISSHINBO

Nisshinbo Micro Devices Inc.

Official website
https://www.nisshinbo-microdevices.co.jp/en/
Purchase information
https://www.nisshinbo-microdevices.co.jp/en/buy/

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.