TLV700xx-Q1 Automotive, 200mA, Low-I_Q, Low-Dropout Regulator (LDO) for Portable Devices

1 Features

- AEC-Q100 qualified for automotive applications:
  - Temperature grade 1: –40°C to 125°C, T_A
  - Device HBM ESD classification level H2
  - Device CDM ESD classification level C4B
- 2% accuracy
- Low I_Q: 31µA
- Fixed output voltage combination possible from 1.9V to 4.8V
- High PSRR: 68dB at 1kHz
- Stable with effective capacitance of 0.1µF
- Thermal shutdown and overcurrent protection
- Latch-up performance meets 100mA per AEC-Q100, level I
- Available in SOT-23-5 and SC70 packages

2 Applications

- Automotive camera modules
- Image sensor power
- Microprocessor rails
- Automotive infotainment head units
- Automotive body electronics

3 Description

The TLV700xx-Q1 family of low-dropout (LDO) linear regulators are low-quiescent-current devices with excellent line and load transient performance. These LDOs are designed for power-sensitive applications. A precision band-gap and error amplifier provides overall 2% accuracy. Low output noise, very high power-supply rejection ratio (PSRR), and low dropout voltage make this series of devices designed for for most battery-operated handheld equipment. All device versions have thermal shutdown and current limit for safety.


Furthermore, these devices are stable with an effective output capacitance of only 0.1µF. This feature enables the use of cost-effective capacitors that have higher bias voltages and temperature derating. The devices regulate to specified accuracy with no output load.

The TLV700xx-Q1 LDOs are available in SOT-23-5 and SC70 packages.

Package Information

PART NUMBER	PACKAGE(1)	PACKAGE SIZE(2)
TLV700xx-Q1	DCK (SC70, 5)	2mm × 2.1mm
	DDC (SOT, 5)	2.9mm × 2.8mm

(1) For more information, see the *Mechanical, Packaging, and Orderable Information*.
(2) The package size (length × width) is a nominal value and includes pins, where applicable.



Typical Application Circuit (Fixed-Voltage Versions)

An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

Table of Contents

1 Features....1
2 Applications....1
3 Description....1
4 Pin Configuration and Functions....3
5 Specifications....4
5.1 Absolute Maximum Ratings....4
5.2 ESD Ratings....4
5.3 Recommended Operating Conditions....4
5.4 Thermal Information....4
5.5 Electrical Characteristics....5
5.6 Typical Characteristics....6
6 Detailed Description....10
6.1 Overview....10
6.2 Functional Block Diagram....10
6.3 Feature Description....10
6.4 Device Functional Modes....11
7 Application and Implementation....12
7.1 Application Information....12
7.2 Typical Application....13
7.3 Power Supply Recommendations....14
7.4 Layout....15
8 Device and Documentation Support....16
8.1 Device Support....16
8.2 Documentation Support....16
8.3 Receiving Notification of Documentation Updates....16
8.4 Support Resources....16
8.5 Trademarks....16
8.6 Electrostatic Discharge Caution....16
8.7 Glossary....16
9 Revision History....16
10 Mechanical, Packaging, and Orderable Information....17

Copyright © 2025 Texas Instruments Incorporated

4 Pin Configuration and Functions




Figure 4-1. DDC and DCK Packages, 5-Pin SOT (Top View)

Table 4-1. Pin Functions

PIN			I/O	DESCRIPTION
NAME	SC70	SOT		
EN	3	3	I	Enable pin. Driving EN over 0.9V turns on the regulator. Driving EN below 0.4V puts the regulator into shutdown mode and reduces operating current to 1µA, nominal.
GND	2	2	—	Ground pin
IN	1	1	I	Input pin. A small 1µF ceramic capacitor is recommended from this pin to ground to provide stability and good transient performance. See the *Input and Output Capacitor Requirements* section for more details.
NC	4	4	—	No connection. This pin can be tied to ground to improve thermal dissipation.
OUT	5	5	O	Regulated output voltage pin. A small 1µF ceramic capacitor is needed from this pin to ground to provide stability. See the *Input and Output Capacitor Requirements* section for more details.

Copyright © 2025 Texas Instruments Incorporated

5 Specifications

5.1 Absolute Maximum Ratings

at T_A = –40°C to +125°C (unless otherwise noted); all voltages are with respect to GND(1)

		MIN	MAX	UNIT
V_{IN}	Input voltage	–0.3	6	V
V_{EN}	Enable voltage	–0.3	V_{IN} + 0.3	V
V_{OUT}	Output voltage	–0.3	6	V
I_{OUT}	Maximum output current	Internally limited		
	Output short-circuit duration	Indefinite		
T_A	Operating ambient temperature	–40	150	°C
T_J	Operating junction temperature	–40	150	°C
T_{stg}	Storage temperature	–55	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

5.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per AEC Q100-002(1)	±2000	V
		Charged-device model (CDM), per AEC Q100-011	±750	

(1) AEC Q100-002 indicates that HBM stressing shall be in accordance with the ANSI/ESDA/JEDEC JS-001 specification.

5.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
V_{IN}	Input voltage	2		5.5	V
V_{EN}	Enable voltage	0		5.5	V
I_{OUT}	Output current		200		mA
C_{IN}	Input capacitor	0	1		µF
C_{OUT}	Output capacitor	0.22	1		µF
T_A	Operating ambient temperature	–40		125	°C

5.4 Thermal Information

THERMAL METRIC(1)		TLV700xx-Q1 DDC (SOT) 5 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	262.8	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	68.2	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	81.6	°C/W
ψ_{JT}	Junction-to-top characterization parameter	1.1	°C/W
ψ_{JB}	Junction-to-board characterization parameter	80.9	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	n/a	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application note.

Copyright © 2025 Texas Instruments Incorporated

5.5 Electrical Characteristics

at T_A = –40°C to +125°C, V_{IN} = $V_{OUT(TYP)}$ + 0.3V or 2V (whichever is greater), I_{OUT} = 10mA, V_{EN} = V_{IN}, and C_{OUT} = 1µF (unless otherwise noted); typical values are at T_A = 25°C

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{IN}	Input voltage range		2		5.5	V
V_{OUT}	DC output accuracy	–40°C ≤ T_A ≤ +125°C, V_{OUT} ≥ 1V	–2%		2%	
$\Delta V_O/\Delta V_{IN}$	Line regulation	$V_{OUT(NOM)}$ + 0.5V ≤ V_{IN} ≤ 5.5V, I_{OUT} = 10mA		1	5	mV
$\Delta V_O/\Delta I_{OUT}$	Load regulation	0mA ≤ I_{OUT} ≤ 200mA			15	mV
V_{DO}	Dropout voltage(1)	V_{IN} = 0.98 × $V_{OUT(NOM)}$, I_{OUT} = 200mA		175	250	mV
I_{CL}	Output current limit	V_{OUT} = 0.9 × $V_{OUT(NOM)}$	220	350	860	mA
I_{GND}	Ground pin current	I_{OUT} = 0mA		31	55	µA
		I_{OUT} = 200mA, V_{IN} = V_{OUT} + 0.5V		270		
I_{SHDN}	Ground pin current (shutdown)	V_{EN} ≤ 0.4V, 2.0V ≤ V_{IN} ≤ 4.5V		1	2.5	µA
PSRR	Power-supply rejection ratio	V_{IN} = 2.3V, V_{OUT} = 1.8V, I_{OUT} = 10mA, f = 1kHz		68		dB
V_N	Output noise voltage	BW = 100Hz to 100kHz, V_{IN} = 2.3V, V_{OUT} = 1.8V, I_{OUT} = 10mA		48		μV_{RMS}
t_{STR}	Startup time(2)	C_{OUT} = 1µF, I_{OUT} = 200mA		100		µs
$V_{EN(HI)}$	Enable pin high (enabled)		0.9		V_{IN}	V
$V_{EN(LO)}$	Enable pin low (disabled)		0		0.4	V
I_{EN}	Enable pin current	V_{EN} = 5.5V , I_{OUT} = 10µA		0.04	0.5	µA
UVLO	Undervoltage lockout	V_{IN} rising		1.9		V
T_{SD}	Thermal shutdown temperature	Shutdown, temperature increasing		160		°C
		Reset, temperature decreasing		140		
T_A	Operating ambient temperature		–40		125	°C

(1) V_{DO} is measured for devices with $V_{OUT(NOM)}$ ≥ 2.35V.
(2) Startup time = time from EN assertion to 0.98 × $V_{OUT(NOM)}$.

Copyright © 2025 Texas Instruments Incorporated

5.6 Typical Characteristics

at T_J = –40°C to +125°C, V_{IN} = $V_{OUT(TYP)}$ + 0.5V or 2V (whichever is greater), I_{OUT} = 10mA, V_{EN} = V_{IN}, C_{IN} = 1µF, and C_{OUT} = 1µF (unless otherwise noted); typical values are at T_J = 25°C




Figure 5-1. TLV70028-Q1 Line Regulation




Figure 5-2. TLV70028-Q1 Line Regulation




Figure 5-3. TLV70028-Q1 Load Regulation




Figure 5-4. TLV70028-Q1 Accuracy vs Temperature




Figure 5-5. TLV70028-Q1 Current Limit vs Input Voltage




Figure 5-6. TLV70028-Q1 Shutdown Current vs Input Voltage

Copyright © 2025 Texas Instruments Incorporated

5.6 Typical Characteristics (continued)

at T_J = –40°C to +125°C, V_{IN} = $V_{OUT(TYP)}$ + 0.5V or 2V (whichever is greater), I_{OUT} = 10mA, V_{EN} = V_{IN}, C_{IN} = 1µF, and C_{OUT} = 1µF (unless otherwise noted); typical values are at T_J = 25°C




Figure 5-7. TLV70028-Q1 Ground Pin Current vs Output Current






Figure 5-8. TLV70028-Q1 Ground Pin Current vs Temperature



I_{OUT} = 0mA

Figure 5-9. TLV70048-Q1 Ground Pin Current vs Input Voltage



I_{OUT} = 200mA

Figure 5-10. TLV70048-Q1 Dropout Voltage vs Input Voltage




Figure 5-11. TLV70028-Q1 Dropout Voltage vs Output Current




Figure 5-12. TLV70028-Q1 Power-Supply Rejection Ratio vs Frequency

Copyright © 2025 Texas Instruments Incorporated

5.6 Typical Characteristics (continued)

at T_J = –40°C to +125°C, V_{IN} = $V_{OUT(TYP)}$ + 0.5V or 2V (whichever is greater), I_{OUT} = 10mA, V_{EN} = V_{IN}, C_{IN} = 1µF, and C_{OUT} = 1µF (unless otherwise noted); typical values are at T_J = 25°C




Figure 5-13. TLV70028-Q1 Power-Supply Rejection Ratio vs Output Voltage




Figure 5-14. TLV70033-Q1 PSRR Ratio






Figure 5-15. TLV70028-Q1 Output Spectral Noise Density vs Frequency




t_R = t_F = 1µs, V_{IN} = 2.1V

Figure 5-16. Load Transient Response



t_R = t_F = 1µs, V_{IN} = 2.3V

Figure 5-17. Load Transient Response




t_R = t_F = 1µs, V_{IN} = 2.3V

Figure 5-18. Load Transient Response

Copyright © 2025 Texas Instruments Incorporated


5.6 Typical Characteristics (continued)

at T_J = –40°C to +125°C, V_{IN} = $V_{OUT(TYP)}$ + 0.5V or 2V (whichever is greater), I_{OUT} = 10mA, V_{EN} = V_{IN}, C_{IN} = 1µF, and C_{OUT} = 1µF (unless otherwise noted); typical values are at T_J = 25°C




Slew rate = 1V/µs, I_{OUT} = 200mA

Figure 5-19. Line Transient Response



Slew rate = 1V/µs, I_{OUT} = 200mA

Figure 5-20. Line Transient Response



Slew rate = 1V/µs, I_{OUT} = 200mA


Figure 5-21. Line Transient Response

6 Detailed Description

6.1 Overview

The TLV700xx-Q1 low-dropout (LDO) linear regulators are low-quiescent-current devices with excellent line and load transient performance. These LDOs are designed for power-sensitive applications. A precision band-gap and error amplifier provides overall 2% accuracy together with low output noise, very high power-supply rejection ratio (PSRR), and low dropout voltage.

6.2 Functional Block Diagram



6.3 Feature Description

6.3.1 Internal Current Limit

The TLV700xx-Q1 internal current limit helps protect the regulator during fault conditions. During current limit, the output sources a fixed amount of current that is largely independent of the output voltage. In such a case, the output voltage is not regulated, and is $V_{OUT} = I_{LIMIT} \times R_{LOAD}$. The PMOS pass transistor dissipates $(V_{IN} – V_{OUT}) \times I_{LIMIT}$ until thermal shutdown is triggered and the device turns off. When the TLV700xx-Q1 cools down, the device is turned on by the internal thermal-shutdown circuit. If the fault condition continues, the device cycles between current limit and thermal shutdown; see the *Thermal Protection* section for more details.

The PMOS pass transistor in the TLV700xx-Q1 has a built-in body diode that conducts current when the voltage at OUT exceeds the voltage at IN. This current is not limited, so if extended reverse voltage operation is anticipated, external limiting to 5% of the rated output current is recommended.

6.3.2 Shutdown

The enable pin (EN) is active high and is compatible with standard and low-voltage transistor-transistor logic, complementary metal oxide semiconductor (TTL-CMOS) levels. When shutdown capability is not required, EN can be connected to the IN pin.

6.3.3 Dropout Voltage

The TLV700xx-Q1 uses a PMOS pass transistor to achieve low dropout. When $(V_{IN} – V_{OUT})$ is less than the dropout voltage (V_{DO}), the PMOS pass device is in the linear region of operation and the input-to-output

Copyright © 2025 Texas Instruments Incorporated

resistance is the $r_{DS(on)}$ of the PMOS pass element. V_{DO} scales approximately with output current because the PMOS device behaves as a resistor in dropout.

As with any linear regulator, PSRR and transient response are degraded when (V_{IN} – V_{OUT}) approaches dropout. This effect is illustrated in Figure 5-13 in the *Typical Characteristics* section.

6.3.4 Undervoltage Lockout (UVLO)

The TLV700xx-Q1 uses an undervoltage lockout circuit to keep the output shut off until the internal circuitry is operating properly.

6.4 Device Functional Modes

6.4.1 Operation with V_{IN} Less Than 2V

The TLV700xx-Q1 family of devices operates with input voltages above 2V. The typical UVLO voltage is 1.9V and the device operates at an input voltage above 2V. When the input voltage falls below the UVLO voltage, the device is shutdown.

6.4.2 Operation with V_{IN} Greater Than 2V

When V_{IN} is greater than 2V, if the input voltage is higher than the desired output voltage plus dropout voltage, the output voltage is equal to the desired value. Otherwise, the output voltage is V_{IN} minus the dropout voltage.

Copyright © 2025 Texas Instruments Incorporated

7 Application and Implementation

Note

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes, as well as validating and testing their design implementation to confirm system functionality.

7.1 Application Information

The TLV700xx-Q1 devices belong to a family of next-generation-value LDO regulators. The devices consume low quiescent current and deliver excellent line and load transient performance. These characteristics, combined with low noise snd very good PSRR with little (V_{IN} – V_{OUT}) headroom, make this device family designed for for RF portable applications. This family of regulators offers sub-band-gap output voltages down to 0.7V, current limit, and thermal protection, and is specified from –40°C to +125°C.

7.1.1 Input and Output Capacitor Requirements

Ceramic, 1.0µF, X5R- and X7R-type capacitors are recommended because these capacitors have minimal variation in value and equivalent series resistance (ESR) over temperature.

However, the TLV700xx-Q1 devices are designed to be stable with an effective capacitance of 0.1µF or larger at the output. Thus, these devices are stable with capacitors of other dielectric types as well, as long as the effective capacitance under operating bias voltage and temperature is greater than 0.1µF. This effective capacitance refers to the capacitance under the operating bias voltage and temperature conditions; that is, the capacitance after taking both bias voltage and temperature derating into consideration. In addition to allowing the use of cheaper dielectrics, this capability of being stable with 0.1µF effective capacitances also enables the use of smaller-footprint capacitors that have higher derating in size- and space-constrained applications.

Note that using a 0.1µF rated capacitor at the output of the LDO does not provide stability because the effective capacitance under the specified operating conditions is less than 0.1µF. Maximum ESR must be less than 200mΩ.

Although an input capacitor is not required for stability, good analog design practice is to connect a 0.1µF to 1µF, low-ESR capacitor across the IN pin and the GND pin of the regulator. This capacitor counteracts reactive input sources and improves transient response, noise rejection, and ripple rejection. A higher-value capacitor may be necessary if large, fast, rise-time load transients are anticipated, or if the device is not located close to the power source. If source impedance is more than 2Ω, a 0.1µF input capacitor may be necessary to provide stability.

7.1.2 Transient Response

As with any regulator, increasing the size of the output capacitor reduces over- and undershoot magnitude but increases the duration of the transient response.

7.1.3 Thermal Protection

Thermal protection disables the output when the junction temperature rises to approximately 160°C, allowing the device to cool. When the junction temperature cools to approximately 140°C, the output circuitry is again enabled. Depending on power dissipation, thermal resistance, and ambient temperature, the thermal protection circuit can cycle on and off. This cycling limits the dissipation of the regulator, protecting the regulator from damage as a result of overheating.

Any tendency to activate the thermal protection circuit indicates excessive power dissipation or an inadequate heatsink. For reliable operation, limit junction temperature to 125°C (maximum). To estimate the margin of safety in a complete design (including heatsink), increase the ambient temperature until the thermal protection is triggered; use worst-case loads and signal conditions. For good reliability, thermal protection must trigger at least 35°C above the maximum expected ambient condition of the particular application. This configuration produces a worst-case junction temperature of 125°C at the highest-expected ambient temperature and worst-case load.

Copyright © 2025 Texas Instruments Incorporated

The internal protection circuitry of the TLV700xx-Q1 is designed to protect against overload conditions. This circuitry is not intended to replace proper heatsinking. Continuously running the TLV700xx-Q1 into thermal shutdown degrades device reliability.

7.2 Typical Application

The TLV700xx-Q1 devices are 200mA, low quiescent current, low-noise, high-PSRR, fast start-up LDO linear regulators with excellent line and load transient response. The *TLV700xxEVM-503* user's guideevaluation module (EVM) helps designers evaluate the operation and performance of the TLV700xx-Q1 family.

Figure 7-1 shows a typical application for the TLV700xx-Q1 device.




Figure 7-1. TLV700xx-Q1 Typical Application

7.2.1 Design Requirements

Table 7-1 shows example design parameters and values for this typical application.

Table 7-1. Design Parameters

PARAMETER	VALUE
Input voltage range	2V to 5.5V
Output voltage	2.2V, 2.8V, 3.2V
Output current rating	200mA
Effective output capacitor range	> 0.1µF
Maximum output capacitor ESR range	< 200mΩ

7.2.2 Detailed Design Procedure

7.2.2.1 Input Capacitance

Although not required for stability, connecting a 0.1µF to 1µF low-ESR capacitor across the IN pin and GND pin the regulator is good analog design practice.

7.2.2.2 Output Capacitance

Effect capacitance of 0.1µF or larger is required to provide stable operation. The maximum ESR must be less than 200mΩ.

Copyright © 2025 Texas Instruments Incorporated

7.2.2.3 Thermal Calculation

Equation 1 shows the thermal calculation.

$$P_D = I_{OUT} \times (V_{IN} - V_{OUT}) + I_Q \times V_{IN} \quad (1)$$

where:

- P_D = Continuous power dissipation
- I_{OUT} = Output current
- V_{IN} = Input voltage
- V_{OUT} = Output voltage
- Because I_Q << I_{OUT}, the term $I_Q \times V_{IN}$ is always ignored

For a device under operation at a given ambient air temperature (T_A), use Equation 2 to calculate the junction temperature (T_J).

$$T_J = T_A + (R_{\theta JA} \times P_D) \quad (2)$$

where:

- $Z_{\theta JA}$ = Junction-to-ambient air thermal impedance

Use Equation 3 to calculate the rise in junction temperature because of power dissipation.

$$\Delta T = T_J - T_A = (R_{\theta JA} \times P_D) \quad (3)$$

For a given maximum junction temperature (T_{Jmax}), use Equation 4 to calculate the maximum ambient air temperature (T_{Amax}) at which the device can operate.

$$T_{Amax} = T_{Jmax} - (R_{\theta JA} \times P_D) \quad (4)$$

7.2.3 Application Curve




Figure 7-2. Power-Up

7.3 Power Supply Recommendations

The device is designed to operate from an input-voltage supply range between 2V and 5.5V. This input supply must be well regulated. If the input supply is located more than a few inches from the TPS7B69xx-Q1 device, a capacitor with a value of 0.1µF and a ceramic bypass capacitor are recommended to be added at the input.

Copyright © 2025 Texas Instruments Incorporated

7.4 Layout

7.4.1 Layout Guidelines

When laying out the board for the TLV700xx-Q1, the board is recommended to be designed with separate ground planes for V_{IN} and V_{OUT} that are only connected at the GND pin of the device, as shown in Figure 7-3. Also, the ground connection for the bypass capacitor must be connected directly to the GND pin of the device. Improve the PSRR performance of the TLV700xx-Q1 by following these layout guidelines.

7.4.2 Board Layout Recommendations to Improve PSRR and Noise Performance

Place input and output capacitors as close to the device pins as possible. To improve ac performance (such as PSRR, output noise, and transient response), the board is recommended to be designed with separate ground planes for V_{IN} and V_{OUT}, with the ground plane connected only at the GND pin of the device. In addition, connect the ground connection for the output capacitor directly to the GND pin of the device. High-ESR capacitors can degrade PSRR performance.

7.4.3 Layout Example




Figure 7-3. TLV700xx-Q1 Layout Example

Copyright © 2025 Texas Instruments Incorporated

8 Device and Documentation Support

8.1 Device Support

8.1.1 Device Nomenclature

Table 8-1. Device Nomenclature

PRODUCT(1)	DESCRIPTION
TLV700**xxQyyyzQ1**	**xx** is the nominal output voltage (for example, 28 = 2.8V). **Q** indicates that this device is a grade-1 device in accordance with the AEC-Q100 standard. **yyy** is the package designator. **z** is the tape and reel quantity (R = 3000, T = 250). **Q1** indicates that this device is an automotive grade (AEC-Q100) device.

(1) For the most current package and ordering information see the Package Option Addendum at the end of this document, or see the device product folder at www.ti.com.

8.2 Documentation Support

8.2.1 Related Documentation

For related documentation see the following:

- Texas Instruments, *TLV700xxEVM-503* user's guide

8.3 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. Click on *Notifications* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

8.4 Support Resources

TI E2E™ support forums are an engineer's go-to source for fast, verified answers and design help — straight from the experts. Search existing answers or ask your own question to get the quick design help you need.

Linked content is provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

8.5 Trademarks

TI E2E™ is a trademark of Texas Instruments.
All trademarks are the property of their respective owners.

8.6 Electrostatic Discharge Caution



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

8.7 Glossary

TI Glossary — This glossary lists and explains terms, acronyms, and definitions.

9 Revision History

Changes from Revision C (June 2018) to Revision D (January 2025)	Page
• Updated the numbering format for tables, figures, and cross-references throughout the document	1
• Added *Device Nomenclature* table	16

Copyright © 2025 Texas Instruments Incorporated

Changes from Revision B (October 2016) to Revision C (June 2018) **Page**

- Added DCK (SC70) package to document; note that TLV70025-Q1 and TLV70033-Q1 were previously listed in SLVSA61 1
- Changed *Fixed Output Voltages* bullet to *Fixed Output Voltage Combination* in *Features* section 1
- Changed last paragraph of Description section to include the SC70 package 1
- Added SC70 row to *Device Information* table 1
- Added T_J parameter to *Absolute Maximum Ratings* table 4
- Changed T_J parameter to T_A in *Recommended Operating Conditions* table and changed *junction* to *ambient* in parameter name 4
- Added *TLV70033-Q1 PSRR Ratio* figure 6

10 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Copyright © 2025 Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
TLV70025QDDCRQ1	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	QVC
TLV70025QDDCRQ1.A	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	QVC
TLV70025QDDCRQ1.B	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	QVC
TLV70028QDDCRQ1	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SJU
TLV70028QDDCRQ1.A	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SJU
TLV70028QDDCRQ1.B	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SJU
TLV70032QDDCRQ1	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SKA
TLV70032QDDCRQ1.A	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SKA
TLV70032QDDCRQ1.B	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	SKA
TLV70033QDDCRQ1	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	OFL
TLV70033QDDCRQ1.A	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	OFL
TLV70033QDDCRQ1.B	Active	Production	SOT-23-THIN (DDC) | 5	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	OFL

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.


Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS




TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers


QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TLV70025QDDCRQ1	SOT-23-THIN	DDC	5	3000	179.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
TLV70028QDDCRQ1	SOT-23-THIN	DDC	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
TLV70032QDDCRQ1	SOT-23-THIN	DDC	5	3000	179.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
TLV70033QDDCRQ1	SOT-23-THIN	DDC	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal


Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TLV70025QDDCRQ1	SOT-23-THIN	DDC	5	3000	213.0	191.0	35.0
TLV70028QDDCRQ1	SOT-23-THIN	DDC	5	3000	213.0	191.0	35.0
TLV70032QDDCRQ1	SOT-23-THIN	DDC	5	3000	213.0	191.0	35.0
TLV70033QDDCRQ1	SOT-23-THIN	DDC	5	3000	213.0	191.0	35.0


PACKAGE OUTLINE

DDC0005A

SOT-23 - 1.1 max height

SMALL OUTLINE TRANSISTOR







4220752/C 08/2024

NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. Reference JEDEC MO-193.
4. Support pin may differ or may not be present.



LAND PATTERN EXAMPLE
EXPLOSED METAL SHOWN
SCALE:15X




SOLDERMASK DETAILS

4220752/C 08/2024

NOTES: (continued)

4. Publication IPC-7351 may have alternate designs.
5. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 THICK STENCIL
SCALE:15X

4220752/C 08/2024

NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
7. Board assembly site may have different recommendations for stencil design.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI’s products are provided subject to TI’s Terms of Sale, TI’s General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI’s provision of these resources does not expand or otherwise alter TI’s applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.