HD14050B

Hex Buffer

The HD14050B noninverting hex buffer finds primary use where low power dissipation and/or high noise immunity is desired. This devices provides logic-level conversion using only one supply voltage, V_{CC}. The input-signal high level (V_{IH}) can exceed the V_{CC} supply voltage for logic-level conversions. Two TTL Loads can be driven when the devices are used as CMOS-to-TTL converters (V_{CC} = 5V, $V_{OL} \leqq 0.4V$, $I_{OL} \geqq 3.2mA$).

■ FEATURES

- High Source and Sink Currents
- High-to-Low Level Converter
- Quiescent Current = 2nA/pkg typ. @5V
- Supply Voltage Range = 3 to 18V
- Pin-for-Pin Replacement for MC14050B

■ PIN ARRANGEMENT



(Top View)

■ CIRCUIT SCHEMATIC (1/6)



■ MAXIMUM RATINGS (Voltages referenced to V_{SS})

Characteristic	Symbol	Value	Unit
DC Supply Voltage	V_{DD}	−0.5~+18	V
Input Voltage	V_{in}	−0.5~+18	V
DC Current Drain per Input Pin	I_{in}	10	mA
DC Current Drain per Output Pin.	I_{out}	45	mA
Operating Temperature Range	T_A	−40~+85	℃
Storage Temperature Ranga	T_{stg}	−65~+150	℃
Power Dissipation	P_D	300	mW

■ SWITCHING TIME TEST CIRCUIT





■ ELECTRICAL CHARACTERISTICS

Characteristic	Symbol	V_{DD}(V)	Test Conditions	−40°C min	−40°C max	25°C min	25°C typ	25°C max	85°C min	85°C max	Unit
Output Voltage	V_{OL}	5.0	V_{in} = 0	—	0.05	—	0	0.05	—	0.05	V
		10		—	0.05	—	0	0.05	—	0.05	
		15		—	0.05	—	0	0.05	—	0.05	
	V_{OH}	5.0	V_{in} = V_{DD}	4.95	—	4.95	5.0	—	4.95	—	V
		10		9.95	—	9.95	10	—	9.95	—	
		15		14.95	—	14.95	15	—	14.95	—	
Input Voltage	V_{IL}	5.0	V_{out} = 0.5V	—	1.5	—	2.25	1.5	—	1.5	V
		10	V_{out} = 1.0V	—	3.0	—	4.50	3.0	—	3.0	
		15	V_{out} = 1.5V	—	4.0	—	6.75	4.0	—	4.0	
	V_{IH}	5.0	V_{out} = 4.5V	3.5	—	3.5	2.75	—	3.5	—	V
		10	V_{out} = 9.0V	7.0	—	7.0	5.50	—	7.0	—	
		15	V_{out} = 13.5V	11.0	—	11.0	8.25	—	11.0	—	
Output Drive Current	I_{OH}	5.0	V_{OH} = 2.5V	−1.5	—	−1.25	−2.5	—	−1.0	—	mA
		10	V_{OH} = 9.5V	−1.5	—	−1.25	−2.5	—	−1.0	—	
		15	V_{OH} = 13.5V	−4.5	—	−3.75	−10	—	−3.0	—	
	I_{OL}	5.0	V_{OL} = 0.4V	3.6	—	3.2	6.0	—	2.5	—	mA
		10	V_{OL} = 0.5V	9.6	—	8.0	16	—	6.6	—	
		15	V_{OL} = 1.5V	28	—	24	40	—	19	—	
Input Current	I_{in}	15		—	±0.3	—	±0.00001	±0.3	—	±1.0	μA
Input Capacitance	C_{in}	—	V_{in} = 0	—	—	—	10	15	—	—	pF
Quiescent Current	I_{DD}	5.0	Zero Signal, per Package	—	4.0	—	0.002	4.0	—	30	μA
		10		—	8.0	—	0.004	8.0	—	60	
		15		—	16	—	0.006	16	—	120	
Total Supply Current*	I_T	5.0	Dynamic + I_{DD}, per Gate C_L = 50pF, f = 1 kHz	—	—	—	1.77	—	—	—	μA
		10		—	—	—	3.54	—	—	—	
		15		—	—	—	5.31	—	—	—	

* To calculate total supply current at frequency other than 1kHz.

@ V_{DD} = 5.0V I_T = (1.77μA/kHz) f + I_{DD} @ V_{DD} = 10V I_T = (3.54μA/kHz) f + I_{DD} @ V_{DD} = 15V I_T = (5.31μA/kHz) f + I_{DD}

■ SWITCHING CHARACTERISTICS (C_L = 50pF, Ta = 25°C)

Characteristic	Symbol	V_{DD}(V)	min	typ	max	Unit
Output Rise Time	t_r	5.0	—	100	200	ns
		10	—	50	100	
		15	—	40	80	
Output Fall Time	t_f	5.0	—	40	80	ns
		10	—	20	40	
		15	—	15	30	
Propagation Delay Time	t_{PLH}	5.0	—	80	160	ns
		10	—	40	80	
		15	—	30	60	
	t_{PHL}	5.0	—	60	100	ns
		10	—	30	50	
		15	—	20	35	

Unit: mm









Hitachi Code	DP-16
JEDEC	Conforms
EIAJ	Conforms
Weight (reference value)	1.07 g

Unit: mm







*Dimension including the plating thickness
Base material dimension

Hitachi Code	FP-16DA
JEDEC	—
EIAJ	Conforms
Weight (reference value)	0.24 g

Unit: mm



Hitachi Code	FP-16DN
JEDEC	Conforms
EIAJ	Conforms
Weight (reference value)	0.15 g

*Dimension including the plating thickness
Base material dimension

Cautions

1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
5. This product is not designed to be radiation resistant.
6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

HITACHI

Hitachi, Ltd.
Semiconductor & Integrated Circuits.
Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan
Tel: Tokyo (03) 3270-2111 Fax: (03) 3270-5109

URL
NorthAmerica : http:semiconductor.hitachi.com/
Europe : http://www.hitachi-eu.com/hel/ecg
Asia (Singapore) : http://www.has.hitachi.com.sg/grp3/sicd/index.htm
Asia (Taiwan) : http://www.hitachi.com.tw/E/Product/SICD_Frame.htm
Asia (HongKong) : http://www.hitachi.com.hk/eng/bo/grp3/index.htm
Japan : http://www.hitachi.co.jp/Sicd/indx.htm

For further information write to:

Hitachi Semiconductor
(America) Inc.
179 East Tasman Drive,
San Jose,CA 95134
Tel: <1> (408) 433-1990
Fax: <1>(408) 433-0223

Hitachi Europe GmbH
Electronic components Group
Dornacher Straße 3
D-85622 Feldkirchen, Munich
Germany
Tel: <49> (89) 9 9180-0
Fax: <49> (89) 9 29 30 00

Hitachi Europe Ltd.
Electronic Components Group.
Whitebrook Park
Lower Cookham Road
Maidenhead
Berkshire SL6 8YA, United Kingdom
Tel: <44> (1628) 585000
Fax: <44> (1628) 778322

Hitachi Asia Pte. Ltd.
16 Collyer Quay #20-00
Hitachi Tower
Singapore 049318
Tel: 535-2100
Fax: 535-1533

Hitachi Asia Ltd.
Taipei Branch Office
3F, Hung Kuo Building. No.167,
Tun-Hwa North Road, Taipei (105)
Tel: <886> (2) 2718-3666
Fax: <886> (2) 2718-8180

Hitachi Asia (Hong Kong) Ltd.
Group III (Electronic Components)
7/F., North Tower, World Finance Centre,
Harbour City, Canton Road, Tsim Sha Tsui,
Kowloon, Hong Kong
Tel: <852> (2) 735 9218
Fax: <852> (2) 730 0281
Telex: 40815 HITEC HX

Copyright ' Hitachi, Ltd., 1999. All rights reserved. Printed in Japan.

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.