ALPHA & OMEGA SEMICONDUCTOR

# AOTF260L

## 60V N-Channel MOSFET

## General Description

The AOTF260L uses Trench MOSFET technology that is uniquely optimized to provide the most efficient high frequency switching performance. Both conduction and switching power losses are minimized due to an extremely low combination of $R_{DS(ON)}$, Ciss and Coss. This device is ideal for boost converters and synchronous rectifiers for consumer, telecom, industrial power supplies and LED backlighting.

## Product Summary


| | |
|---|---|
| $V_{DS}$ | 60V |
| $I_D$ (at $V_{GS}$=10V) | 92A |
| $R_{DS(ON)}$ (at $V_{GS}$=10V) | < 2.6mΩ |
| $R_{DS(ON)}$ (at $V_{GS}$=6V) | < 3.0mΩ |

100% UIS Tested
100% $R_g$ Tested


Green Product


TO220F

Top View




Bottom View




**Absolute Maximum Ratings $T_A$=25°C unless otherwise noted**

| Parameter | | Symbol | Maximum | Units |
|---|---|---|---|---|
| Drain-Source Voltage | | $V_{DS}$ | 60 | V |
| Gate-Source Voltage | | $V_{GS}$ | ±20 | V |
| Continuous Drain Current [G] | $T_C$=25°C | $I_D$ | 92 | A |
| | $T_C$=100°C | | 66.5 | |
| Pulsed Drain Current [C] | | $I_{DM}$ | 368 | |
| Continuous Drain Current | $T_A$=25°C | $I_{DSM}$ | 19 | A |
| | $T_A$=70°C | | 15 | |
| Avalanche Current [C] | | $I_{AS}$ | 128 | A |
| Avalanche energy L=0.1mH [C] | | $E_{AS}$ | 819 | mJ |
| Power Dissipation [B] | $T_C$=25°C | $P_D$ | 46.5 | W |
| | $T_C$=100°C | | 23.5 | |
| Power Dissipation [A] | $T_A$=25°C | $P_{DSM}$ | 1.9 | W |
| | $T_A$=70°C | | 1.2 | |
| Junction and Storage Temperature Range | | $T_J$, $T_{STG}$ | -55 to 175 | °C |

**Thermal Characteristics**

| Parameter | | Symbol | Typ | Max | Units |
|---|---|---|---|---|---|
| Maximum Junction-to-Ambient [A] | t ≤ 10s | $R_{\theta JA}$ | 12 | 15 | °C/W |
| Maximum Junction-to-Ambient [A D] | Steady-State | | 54 | 65 | °C/W |
| Maximum Junction-to-Case | Steady-State | $R_{\theta JC}$ | 2.6 | 3.2 | °C/W |

## Electrical Characteristics ($T_J$=25°C unless otherwise noted)

| Symbol | Parameter | Conditions | Min | Typ | Max | Units |
|---|---|---|---|---|---|---|
| **STATIC PARAMETERS** | | | | | | |
| $BV_{DSS}$ | Drain-Source Breakdown Voltage | $I_D$=250µA, $V_{GS}$=0V | 60 | | | V |
| $I_{DSS}$ | Zero Gate Voltage Drain Current | $V_{DS}$=60V, $V_{GS}$=0V | | | 1 | µA |
| | | $T_J$=55°C | | | 5 | |
| $I_{GSS}$ | Gate-Body leakage current | $V_{DS}$=0V, $V_{GS}$=±20V | | | ±100 | nA |
| $V_{GS(th)}$ | Gate Threshold Voltage | $V_{DS}$=$V_{GS}$, $I_D$=250µA | 2.2 | 2.7 | 3.2 | V |
| $I_{D(ON)}$ | On state drain current | $V_{GS}$=10V, $V_{DS}$=5V | 368 | | | A |
| $R_{DS(ON)}$ | Static Drain-Source On-Resistance | $V_{GS}$=10V, $I_D$=20A | | 2.1 | 2.6 | mΩ |
| | | $T_J$=125°C | | 3.5 | 4.3 | |
| | | $V_{GS}$=6V, $I_D$=20A | | 2.3 | 3.0 | |
| $g_{FS}$ | Forward Transconductance | $V_{DS}$=5V, $I_D$=20A | | 68 | | S |
| $V_{SD}$ | Diode Forward Voltage | $I_S$=1A,$V_{GS}$=0V | | 0.65 | 1 | V |
| $I_S$ | Maximum Body-Diode Continuous Current | | | | 55 | A |
| **DYNAMIC PARAMETERS** | | | | | | |
| $C_{iss}$ | Input Capacitance | $V_{GS}$=0V, $V_{DS}$=30V, f=1MHz | | 11800 | | pF |
| $C_{oss}$ | Output Capacitance | | | 1360 | | pF |
| $C_{rss}$ | Reverse Transfer Capacitance | | | 40 | | pF |
| $R_g$ | Gate resistance | $V_{GS}$=0V, $V_{DS}$=0V, f=1MHz | 0.5 | 1 | 1.5 | Ω |
| **SWITCHING PARAMETERS** | | | | | | |
| $Q_g$(10V) | Total Gate Charge | $V_{GS}$=10V, $V_{DS}$=30V, $I_D$=20A | | 150 | 210 | nC |
| $Q_{gs}$ | Gate Source Charge | | | 40 | | nC |
| $Q_{gd}$ | Gate Drain Charge | | | 15 | | nC |
| $t_{D(on)}$ | Turn-On DelayTime | $V_{GS}$=10V, $V_{DS}$=30V, $R_L$=1.5Ω, $R_{GEN}$=3Ω | | 30 | | ns |
| $t_r$ | Turn-On Rise Time | | | 27 | | ns |
| $t_{D(off)}$ | Turn-Off DelayTime | | | 74 | | ns |
| $t_f$ | Turn-Off Fall Time | | | 12 | | ns |
| $t_{rr}$ | Body Diode Reverse Recovery Time | $I_F$=20A, dI/dt=500A/µs | | 32 | | ns |
| $Q_{rr}$ | Body Diode Reverse Recovery Charge | $I_F$=20A, dI/dt=500A/µs | | 200 | | nC |

A. The value of $R_{\theta JA}$ is measured with the device mounted on 1in² FR-4 board with 2oz. Copper, in a still air environment with $T_A$ =25° C. The Power dissipation $P_{DSM}$ is based on $R_{\theta JA}$ and the maximum allowed junction temperature of 150° C. The value in any given application depends on the user's specific board design, and the maximum temperature of 175° C may be used if the PCB allows it.

B. The power dissipation $P_D$ is based on $T_{J(MAX)}$=175° C, using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used.

C. Repetitive rating, pulse width limited by junction temperature $T_{J(MAX)}$=175° C. Ratings are based on low frequency and duty cycles to keep initial $T_J$ =25° C.

D. The $R_{\theta JA}$ is the sum of the thermal impedance from junction to case $R_{\theta JC}$ and case to ambient.

E. The static characteristics in Figures 1 to 6 are obtained using <300µs pulses, duty cycle 0.5% max.

F. These curves are based on the junction-to-case thermal impedance which is measured with the device mounted to a large heatsink, assuming a maximum junction temperature of $T_{J(MAX)}$=175° C. The SOA curve provides a single pulse rating.

G. The maximum current rating is package limited.

H. These tests are performed with the device mounted on 1 in² FR-4 board with 2oz. Copper, in a still air environment with $T_A$=25° C.

APPLICATIONS OR USES AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS ARE NOT AUTHORIZED. AOS DOES NOT ASSUME ANY LIABILITY ARISING OUT OF SUCH APPLICATIONS OR USES OF ITS PRODUCTS. AOS RESERVES THE RIGHT TO MAKE CHANGES TO PRODUCT SPECIFICATIONS WITHOUT NOTICE. IT IS THE RESPONSIBILITY OF THE CUSTOMER TO EVALUATE SUITABILITY OF THE PRODUCT FOR THEIR INTENDED APPLICATION. CUSTOMER SHALL COMPLY WITH APPLICABLE LEGAL REQUIREMENTS, INCLUDING ALL APPLICABLE EXPORT CONTROL RULES, REGULATIONS AND LIMITATIONS.

AOS' products are provided subject to AOS' terms and conditions of sale which are set forth at:
http://www.aosmd.com/terms_and_conditions_of_sale

## TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS





**Fig 1: On-Region Characteristics (Note E)**





**Figure 2: Transfer Characteristics (Note E)**





**Figure 3: On-Resistance vs. Drain Current and Gate Voltage (Note E)**





**Figure 4: On-Resistance vs. Junction Temperature (Note E)**





**Figure 5: On-Resistance vs. Gate-Source Voltage (Note E)**





**Figure 6: Body-Diode Characteristics (Note E)**

## TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS





**Figure 7: Gate-Charge Characteristics**





**Figure 8: Capacitance Characteristics**





**Figure 9: Maximum Forward Biased Safe Operating Area (Note F)**





**Figure 10: Single Pulse Power Rating Junction-to-Case (Note F)**





**Figure 11: Normalized Maximum Transient Thermal Impedance (Note F)**

## TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS





**Figure 12: Single Pulse Avalanche capability (Note C)**





**Figure 13: Power De-rating (Note F)**





**Figure 14: Current De-rating (Note F)**





**Figure 15: Single Pulse Power Rating Junction-to-Ambient (Note H)**







**Figure 16: Normalized Maximum Transient Thermal Impedance (Note H)**


## Gate Charge Test Circuit & Waveform





## Resistive Switching Test Circuit & Waveforms




## Unclamped Inductive Switching (UIS) Test Circuit & Waveforms




## Diode Recovery Test Circuit & Waveforms



ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

# Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

### Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

**www.entegreci.com**

### Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

**Kategorilere göz atın**

### Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

**Üreticileri görün**

### Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

**Teklif isteyin**

**www.entegreci.com** | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.