# Voltage Regulator - Low Power Low, Dropout

## 100 mA

# LP2950, LP2951, NCV2951

The LP2950 and LP2951 are micropower voltage regulators that are specifically designed to maintain proper regulation with an extremely low input−to−output voltage differential. These devices feature a very low quiescent bias current of 75 μA and are capable of supplying output currents in excess of 100 mA. Internal current and thermal limiting protection is provided.

The LP2951 has three additional features. The first is the $\overline{\text{Error}}$ Output that can be used to signal external circuitry of an out of regulation condition, or as a microprocessor power−on reset. The second feature allows the output voltage to be preset to 5.0 V, 3.3 V or 3.0 V output (depending on the version) or programmed from 1.25 V to 29 V. It consists of a pinned out resistor divider along with direct access to the Error Amplifier feedback input. The third feature is a Shutdown input that allows a logic level signal to turn−off or turn−on the regulator output.

Due to the low input−to−output voltage differential and bias current specifications, these devices are ideally suited for battery powered computer, consumer, and industrial equipment where an extension of useful battery life is desirable. The LP2950 is available in the three pin case 29 and DPAK packages, and the LP2951 is available in the eight pin dual−in−line, SOIC−8 and Micro8 surface mount packages. The 'A' suffix devices feature an initial output voltage tolerance ±0.5%.


### Features

- Low Quiescent Bias Current of 75 μA
- Low Input−to−Output Voltage Differential of 50 mV at 100 μA and 380 mV at 100 mA
- 5.0 V, 3.3 V or 3.0 V ±0.5% Allows Use as a Regulator or Reference
- Extremely Tight Line and Load Regulation
- Requires Only a 1.0 μF Output Capacitor for Stability
- Internal Current and Thermal Limiting
- NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable
- These Devices are Pb−Free and RoHS Compliant

### LP2951 Additional Features

- $\overline{\text{Error}}$ Output Signals an Out of Regulation Condition
- Output Programmable from 1.25 V to 29 V
- Logic Level Shutdown Input


(See Following Page for Device Information.)





**TO−92**
**CASE 29−10**

Pin: 1. Output
2. Ground
3. Input

### PIN CONNECTIONS




**DPAK**
**CASE 369C**





(Top View)

Pin: 1. Input
2. Ground
3. Output

Heatsink surface (shown as terminal 4 in case outline drawing) is connected to Pin 2.




**SOIC−8**
**CASE 751**





**PDIP−8**
**CASE 626**




**Micro8**
**CASE 846A**

### PIN CONNECTIONS




(Top View)

### ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on pages 14 and 15 of this data sheet.

### DEVICE MARKING INFORMATION


See general marking information in the device marking section on page 16 of this data sheet.

© Semiconductor Components Industries, LLC, 1995

## DEVICE INFORMATION

| Package | Output Voltage | | | | Operating Ambient Temperature Range |
|---|---|---|---|---|---|
| | 3.0 V | 3.3 V | 5.0 V | Adjustable | |
| TO−92 Suffix Z | LP2950ACZ−3.0G | LP2950ACZ−3.3G | LP2950ACZ−5.0G | Not Available | $T_A$ = −40° to +125°C |
| | LP2950ACZ−3.0RAG | LP2950ACZ−3.3RAG | LP2950ACZ−5.0RAG | | |
| | LP2950CZ−3.0G | LP2950CZ−3.3G | LP2950CZ−5.0G | | |
| | LP2950CZ−3.0RAG | LP2950CZ−3.3RAG | LP2950CZ−5.0RAG | | |
| | | | LP2950CZ−5.0RPG | | |
| DPAK Suffix DT | LP2950CDT−3.0RKG | LP2950ACDT−3.3RG | LP2950ACDT−5.0G | Not Available | $T_A$ = −40° to +125°C |
| | | LP2950CDT−3.3G | LP2950ACDT−5RKG | | |
| | | LP2950CDT−3.3RKG | LP2950CDT−5.0G | | |
| | | | LP2950CDT−5.0RKG | | |
| SOIC−8 Suffix D | LP2951ACD−3.0R2G | LP2951ACD−3.3R2G | LP2951ACDR2G | LP2951ACDR2G | $T_A$ = −40° to +125°C |
| | LP2951CD−3.0R2G | LP2951CD−3.3R2G | LP2951CDR2G | LP2951CDR2G | |
| | | NCV2951ACD−3.3R2G* | NCV2951ACDR2G* | NCV2951ACDR2G* | |
| | | | NCV2951CDR2G* | NCV2951CDR2G* | |
| Micro8 Suffix DM | LP2951ACDM−3.0RG | LP2951ACDM−3.3RG | LP2951ACDMR2G | LP2951ACDMR2G | $T_A$ = −40° to +125°C |
| | | | LP2951CDMR2G | LP2951CDMR2G | |
| | | | NCV2951ACDMR2G* | NCV2951ACDMR2G* | |

*NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable.
LP2950Cx−xx / LP2951Cxx−xx / NCV2951Cx−xx 1% Output Voltage Precision at $T_A$ = 25°C
LP2950ACx−xx / LP2951ACxx−xx / NCV2951Ax−xx 0.5% Output Voltage Precision at $T_A$ = 25°C




This device contains 34 active transistors.

**Figure 1. Representative Block Diagrams**



Share Feedback
Your Opinion Matters

**MAXIMUM RATINGS** ($T_A$ = 25°C, unless otherwise noted.)

| Rating | Symbol | Value | Unit |
|---|---|---|---|
| Input Voltage | $V_{CC}$ | 30 | Vdc |
| Peak Transient Input Voltage (t < 300 ms) | $V_{CC}$ | 32 | Vdc |
| Power Dissipation and Thermal Characteristics | | | |
| Maximum Power Dissipation | $P_D$ | Internally Limited | W |
| Case 751(SOIC−8) D Suffix | | | |
| Thermal Resistance, Junction−to−Ambient | $R_{\theta JA}$ | 180 | °C/W |
| Thermal Resistance, Junction−to−Case | $R_{\theta JC}$ | 45 | °C/W |
| Case 369A (DPAK) DT Suffix (Note 1) | | | |
| Thermal Resistance, Junction−to−Ambient | $R_{\theta JA}$ | 92 | °C/W |
| Thermal Resistance, Junction−to−Case | $R_{\theta JC}$ | 6.0 | °C/W |
| Case 29 (TO−226AA/TO−92) Z Suffix | | | |
| Thermal Resistance, Junction−to−Ambient | $R_{\theta JA}$ | 160 | °C/W |
| Thermal Resistance, Junction−to−Case | $R_{\theta JC}$ | 83 | °C/W |
| Case 626 N Suffix | | | |
| Thermal Resistance, Junction−to−Ambient | $R_{\theta JA}$ | 105 | °C/W |
| Case 846A (Micro8) DM Suffix | | | |
| Thermal Resistance, Junction−to−Ambient | $R_{\theta JA}$ | 240 | °C/W |
| Feedback Input Voltage | $V_{fb}$ | −1.5 to +30 | Vdc |
| Shutdown Input Voltage | $V_{sd}$ | −0.3 to +30 | Vdc |
| Error Comparator Output Voltage | $V_{err}$ | −0.3 to +30 | Vdc |
| Operating Ambient Temperature Range | $T_A$ | −40 to +125 | °C |
| Maximum Die Junction Temperature Range | $T_J$ | +150 | °C |
| Storage Temperature Range | $T_{stg}$ | −65 to +150 | °C |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.



Share Feedback
Your Opinion Matters

## ELECTRICAL CHARACTERISTICS

($V_{in}$ = $V_O$ + 1.0 V, $I_O$ = 100 μA, $C_O$ = 1.0 μF, $T_A$ = 25°C [Note 3], unless otherwise noted.)

| Characteristic | Symbol | Min | Typ | Max | Unit |
|---|---|---|---|---|---|
| Output Voltage, 5.0 V Versions | $V_O$ | | | | V |
| $V_{in}$ = 6.0 V, $I_O$ = 100 μA, $T_A$ = 25°C | | | | | |
| LP2950C−5.0/LP2951C/NCV2951C* | | 4.950 | 5.000 | 5.050 | |
| LP2950AC−5.0/LP2951AC/NCV2951AC* | | 4.975 | 5.000 | 5.025 | |
| $T_A$ = −40 to +125°C | | | | | |
| LP2950C−5.0/LP2951C/NCV2951C* | | 4.900 | – | 5.100 | |
| LP2950AC−5.0/LP2951AC/NCV2951AC* | | 4.940 | – | 5.060 | |
| $V_{in}$ = 6.0 to 30 V, $I_O$ = 100 μA to 100 mA, $T_A$ = −40 to +125°C | | | | | |
| LP2950C−5.0/LP2951C/NCV2951C* | | 4.880 | – | 5.120 | |
| LP2950AC−5.0/LP2951AC/NCV2951AC* | | 4.925 | – | 5.075 | |
| Output Voltage, 3.3 V Versions | $V_O$ | | | | V |
| $V_{in}$ = 4.3 V, $I_O$ = 100 μA, $T_A$ = 25°C | | | | | |
| LP2950C−3.3/LP2951C−3.3 | | 3.267 | 3.300 | 3.333 | |
| LP2950AC−3.3/LP2951AC−3.3/NCV2951AC−3.3* | | 3.284 | 3.300 | 3.317 | |
| $T_A$ = −40 to +125°C | | | | | |
| LP2950C−3.3/LP2951C−3.3 | | 3.234 | – | 3.366 | |
| LP2950AC−3.3/LP2951AC−3.3/NCV2951AC−3.3* | | 3.260 | – | 3.340 | |
| $V_{in}$ = 4.3 to 30 V, $I_O$ = 100 μA to 100 mA, $T_A$ = −40 to +125°C | | | | | |
| LP2950C−3.3/LP2951C−3.3 | | 3.221 | – | 3.379 | |
| LP2950AC−3.3/LP2951AC−3.3/NCV2951AC−3.3* | | 3.254 | – | 3.346 | |
| Output Voltage, 3.0 V Versions | $V_O$ | | | | V |
| $V_{in}$ = 4.0 V, $I_O$ = 100 μA, $T_A$ = 25°C | | | | | |
| LP2950C−3.0/LP2951C−3.0 | | 2.970 | 3.000 | 3.030 | |
| LP2950AC−3.0/LP2951AC−3.0 | | 2.985 | 3.000 | 3.015 | |
| $T_A$ = −40 to +125°C | | | | | |
| LP2950C−3.0/LP2951C−3.0 | | 2.940 | – | 3.060 | |
| LP2950AC−3.0/LP2951AC−3.0 | | 2.964 | – | 3.036 | |
| $V_{in}$ = 4.0 to 30 V, $I_O$ = 100 μA to 100 mA, $T_A$ = −40 to +125°C | | | | | |
| LP2950C−3.0/LP2951C−3.0 | | 2.928 | – | 3.072 | |
| LP2950AC−3.0/LP2951AC−3.0 | | 2.958 | – | 3.042 | |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

1. The Junction−to−Ambient Thermal Resistance is determined by PCB copper area per Figure 29.
2. This device series contains ESD protection and exceeds the following tests:
   Human Body Model (HBM), 2000 V, Class 2, JESD22 A114−C
   Machine Model (MM), 200 V, Class B, JESD22 A115−A
   Charged Device Model (CDM), 2000 V, Class IV, JESD22 C101−C
3. Low duty pulse techniques are used during test to maintain junction temperature as close to ambient as possible.
4. $V_{O(nom)}$ is the part number voltage option.
5. Noise tests on the LP2951 are made with a 0.01 μF capacitor connected across Pins 7 and 1.
6. Latch−up Current Maximum Rating tested per JEDEC standard: JESD78
   − Inputs Low: passing positive current 100 mA and negative current −100 mA
   − Inputs High: passing positive current 100 mA and negative current −10 mA.

*NCV prefix is for automotive and other applications requiring site and change control.



Share Feedback
Your Opinion Matters

**ELECTRICAL CHARACTERISTICS** (continued)
($V_{in}$ = $V_O$ + 1.0 V, $I_O$ = 100 μA, $C_O$ = 1.0 μF, $T_A$ = 25°C [Note 9], unless otherwise noted.)

| Characteristic | Symbol | Min | Typ | Max | Unit |
|---|---|---|---|---|---|
| Line Regulation ($V_{in}$ = $V_{O(nom)}$ +1.0 V to 30 V) (Note 10) | $Reg_{line}$ | | | | % |
| LP2950C−XX/LP2951C/LP2951C−XX/NCV2951C* | | – | 0.08 | 0.20 | |
| LP2950AC−XX/LP2951AC/LP2951AC−XX/NCV2951AC* | | – | 0.04 | 0.10 | |
| Load Regulation ($I_O$ = 100 μA to 100 mA) | $Reg_{load}$ | | | | % |
| LP2950C−XX/LP2951C/LP2951C−XX/NCV2951C* | | – | 0.13 | 0.20 | |
| LP2950AC−XX/LP2951AC/LP2951AC−XX/NCV2951AC* | | – | 0.05 | 0.10 | |
| Dropout Voltage | $V_I - V_O$ | | | | mV |
| $I_O$ = 100 μA | | – | 30 | 80 | |
| $I_O$ = 100 mA | | – | 350 | 450 | |
| Supply Bias Current | $I_{CC}$ | | | | |
| $I_O$ = 100 μA | | – | 93 | 120 | μA |
| $I_O$ = 100 mA | | – | 4.0 | 12 | mA |
| Dropout Supply Bias Current ($V_{in}$ = $V_{O(nom)}$ − 0.5 V, $I_O$ = 100 μA) (Note 10) | $I_{CCdropout}$ | – | 110 | 170 | μA |
| Current Limit ($V_O$ Shorted to Ground) | $I_{Limit}$ | – | 220 | 300 | mA |
| Thermal Regulation | $Reg_{thermal}$ | – | 0.05 | 0.20 | %/W |
| Output Noise Voltage (10 Hz to 100 kHz) (Note 11) | $V_n$ | | | | μVrms |
| $C_L$ = 1.0 μF | | – | 126 | – | |
| $C_L$ = 100 μF | | – | 56 | – | |
| **LP2951A/LP2951AC Only** | | | | | |
| Reference Voltage ($T_A$ = 25°C) | $V_{ref}$ | | | | V |
| LP2951C/LP2951C−XX/NCV2951C* | | 1.210 | 1.235 | 1.260 | |
| LP2951AC/LP2951AC−XX/NCV2951AC* | | 1.220 | 1.235 | 1.250 | |
| Reference Voltage ($T_A$ = −40 to +125°C) | $V_{ref}$ | | | | V |
| LP2951C/LP2951C−XX/NCV2951C* | | 1.200 | – | 1.270 | |
| LP2951AC/LP2951AC−XX/NCV2951AC* | | 1.200 | – | 1.260 | |
| Reference Voltage ($T_A$ = −40 to +125°C) | $V_{ref}$ | | | | V |
| $I_O$ = 100 μA to 100 mA, $V_{in}$ = 23 to 30 V | | | | | |
| LP2951C/LP2951C−XX/NCV2951C* | | 1.185 | – | 1.285 | |
| LP2951AC/LP2951AC−XX/NCV2951AC* | | 1.190 | – | 1.270 | |
| Feedback Pin Bias Current | $I_{FB}$ | – | 15 | 40 | nA |
| **Error Comparator** | | | | | |
| Output Leakage Current ($V_{OH}$ = 30 V) | $I_{lkg}$ | – | 0.01 | 1.0 | μA |
| Output Low Voltage ($V_{in}$ = 4.5 V, $I_{OL}$ = 400 μA) | $V_{OL}$ | – | 150 | 250 | mV |
| Upper Threshold Voltage ($V_{in}$ = 6.0 V) | $V_{thu}$ | 40 | 45 | – | mV |
| Lower Threshold Voltage ($V_{in}$ = 6.0 V) | $V_{thl}$ | – | 60 | 95 | mV |
| Hysteresis ($V_{in}$ = 6.0 V) | $V_{hy}$ | – | 15 | – | mV |
| **Shutdown Input** | | | | | |
| Input Logic Voltage | $V_{shtdn}$ | | | | V |
| Logic “0” (Regulator “On”) | | 0 | – | 0.7 | |
| Logic “1” (Regulator “Off”) | | 2.0 | – | 30 | |
| Shutdown Pin Input Current | $I_{shtdn}$ | | | | μA |
| $V_{shtdn}$ = 2.4 V | | – | 35 | 50 | |
| $V_{shtdn}$ = 30 V | | – | 450 | 600 | |
| Regulator Output Current in Shutdown Mode ($V_{in}$ = 30 V, $V_{shtdn}$ = 2.0 V, $V_O$ = 0, Pin 6 Connected to Pin 7) | $I_{off}$ | – | 3.0 | 10 | μA |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

7. The Junction−to−Ambient Thermal Resistance is determined by PCB copper area per Figure 29.
8. ESD data available upon request.
9. Low duty pulse techniques are used during test to maintain junction temperature as close to ambient as possible.
10. $V_{O(nom)}$ is the part number voltage option.
11. Noise tests on the LP2951 are made with a 0.01 μF capacitor connected across Pins 7 and 1.

*NCV prefix is for automotive and other applications requiring site and change control.



Share Feedback
Your Opinion Matters

## DEFINITIONS

**Dropout Voltage** – The input/output voltage differential at which the regulator output no longer maintains regulation against further reductions in input voltage. Measured when the output drops 100 mV below its nominal value (which is measured at 1.0 V differential), dropout voltage is affected by junction temperature, load current and minimum input supply requirements.

**Line Regulation** – The change in output voltage for a change in input voltage. The measurement is made under conditions of low dissipation or by using pulse techniques such that average chip temperature is not significantly affected.

**Load Regulation** – The change in output voltage for a change in load current at constant chip temperature.

**Maximum Power Dissipation** – The maximum total device dissipation for which the regulator will operate within specifications.

**Bias Current** – Current which is used to operate the regulator chip and is not delivered to the load.

**Output Noise Voltage** – The RMS ac voltage at the output, with constant load and no input ripple, measured over a specified frequency range.

**Leakage Current** – Current drawn through a bipolar transistor collector−base junction, under a specified collector voltage, when the transistor is “off”.

**Upper Threshold Voltage** – Voltage applied to the comparator input terminal, below the reference voltage which is applied to the other comparator input terminal, which causes the comparator output to change state from a logic “0” to “1”.

**Lower Threshold Voltage** – Voltage applied to the comparator input terminal, below the reference voltage which is applied to the other comparator input terminal, which causes the comparator output to change state from a logic “1” to “0”.

**Hysteresis** – The difference between Lower Threshold voltage and Upper Threshold voltage.





**Figure 2. Quiescent Current**





**Figure 3. 5.0 V Dropout Characteristics over Load**





**Figure 4. Output Voltage versus Temperature**





**Figure 5. 5.0 V Dropout Characteristics with $R_L$ = 50 Ω**



Share Feedback
Your Opinion Matters





**Figure 6. Input Current**





**Figure 7. Dropout Voltage versus Output Current**





**Figure 8. Dropout Voltage versus Temperature**





**Figure 9. Error Comparator Output**





**Figure 10. Line Transient Response**





**Figure 11. LP2951 Enable Transient**



Share Feedback
Your Opinion Matters





**Figure 12. Load Transient Response**





**Figure 13. Ripple Rejection**





**Figure 14. Output Noise**





**Figure 15. Shutdown Threshold Voltage versus Temperature**





**Figure 16. Maximum Rated Output Current**





**Figure 17. Output Stability versus Output Capacitor Change**



Share Feedback
Your Opinion Matters

## APPLICATIONS INFORMATION

### Introduction

The LP2950/LP2951 regulators are designed with internal current limiting and thermal shutdown making them user−friendly. Typical application circuits for the LP2950 and LP2951 are shown in Figures 20 through 28.

These regulators are not internally compensated and thus require a 1.0 μF (or greater) capacitance between the LP2950/LP2951 output terminal and ground for stability. Most types of aluminum, tantalum or multilayer ceramic will perform adequately. Solid tantalums or appropriate multilayer ceramic capacitors are recommended for operation below 25°C.

At lower values of output current, less output capacitance is required for output stability. The capacitor can be reduced to 0.33 μF for currents less than 10 mA, or 0.1 μF for currents below 1.0 mA. Using the 8 pin versions at voltages less than 5.0 V operates the error amplifier at lower values of gain, so that more output capacitance is needed for stability. For the worst case operating condition of a 100 mA load at 1.23 V output (output Pin 1 connected to the feedback Pin 7) a minimum capacitance of 3.3 μF is recommended.

The LP2950 will remain stable and in regulation when operated with no output load. When setting the output voltage of the LP2951 with external resistors, the resistance values should be chosen to draw a minimum of 1.0 μA.

A bypass capacitor is recommended across the LP2950/LP2951 input to ground if more than 4 inches of wire connects the input to either a battery or power supply filter capacitor.

Input capacitance at the LP2951 Feedback Pin 7 can create a pole, causing instability if high value external resistors are used to set the output voltage. Adding a 100 pF capacitor between the Output Pin 1 and the Feedback Pin 7 and increasing the output filter capacitor to at least 3.3 μF will stabilize the feedback loop.

### Error Detection Comparator

The comparator switches to a positive logic low whenever the LP2951 output voltage falls more than approximately 5.0% out of regulation. This value is the comparator's designed−in offset voltage of 60 mV divided by the 1.235 V internal reference. As shown in the representative block diagram. This trip level remains 5.0% below normal regardless of the value of regulated output voltage. For example, the error flag trip level is 4.75 V for a normal 5.0 V regulated output, or 9.50 V for a 10 V output voltage.

Figure 2 is a timing diagram which shows the $\overline{\text{ERROR}}$ signal and the regulated output voltage as the input voltage to the LP2951 is ramped up and down. The $\overline{\text{ERROR}}$ signal becomes valid (low) at about 1.3 V input. It goes high when the input reaches about 5.0 V ($V_{out}$ exceeds about 4.75 V). Since the LP2951's dropout voltage is dependent upon the load current (refer to the curve in the Typical Performance Characteristics), the input voltage trip point will vary with load current. The output voltage trip point does not vary with load.

The error comparator output is an open collector which requires an external pullup resistor. This resistor may be returned to the output or some other voltage within the system. The resistance value should be chosen to be consistent with the 400 μA sink capability of the error comparator. A value between 100 kΩ and 1.0 MΩ is suggested. No pullup resistance is required if this output is unused.

When operated in the power down mode ($V_{in}$ = 0 V), the error comparator output will go high if it has been pulled up to an external supply (the output transistor is in high impedance state). To avoid this invalid response, the error comparator output should be pulled up to $V_{out}$ (see Figure 18).





**Figure 18. $\overline{\text{ERROR}}$ Output Timing**

### Programming the Output Voltage (LP2951)

The LP2951CX may be pin−strapped for the nominal fixed output voltage using its internal voltage divider by tying Pin 1 (output) to Pin 2 (sense) and Pin 7 (feedback) to Pin 6 (5.0 V tap). Alternatively, it may be programmed for any output voltage between its 1.235 reference voltage and its 30 V maximum rating. An external pair of resistors is required, as shown in Figure 19.



Share Feedback
Your Opinion Matters





**Figure 19. Adjustable Regulator**

The complete equation for the output voltage is:

$$V_{out} = V_{ref}(1 + R1/R2) + I_{FB} R1$$

where $V_{ref}$ is the nominal 1.235 V reference voltage and $I_{FB}$ is the feedback pin bias current, nominally −20 nA. The minimum recommended load current of 1.0 μA forces an upper limit of 1.2 MΩ on the value of R2, if the regulator must work with no load. $I_{FB}$ will produce a 2% typical error in $V_{out}$ which may be eliminated at room temperature by adjusting R1. For better accuracy, choosing R2 = 100 k reduces this error to 0.17% while increasing the resistor program current to 12 μA. Since the LP2951 typically draws 75 μA at no load with Pin 2 open circuited, the extra 12 μA of current drawn is often a worthwhile tradeoff for eliminating the need to set output voltage in test.

### Output Noise

In many applications it is desirable to reduce the noise present at the output. Reducing the regulator bandwidth by increasing the size of the output capacitor is the only method for reducing noise on the 3 lead LP2950. However, increasing the capacitor from 1.0 μF to 220 μF only decreases the noise from 430 μV to 160 μVrms for a 100 kHz bandwidth at the 5.0 V output.

Noise can be reduced fourfold by a bypass capacitor across R1, since it reduces the high frequency gain from 4 to unity. Pick

$$C_{Bypass} \approx \frac{1}{2\pi R1 \times 200\ Hz}$$

or about 0.01 μF. When doing this, the output capacitor must be increased to 3.3 μF to maintain stability. These changes reduce the output noise from 430 μV to 126 μVrms for a 100 kHz bandwidth at 5.0 V output. With bypass capacitor added, noise no longer scales with output voltage so that improvements are more dramatic at higher output voltages.





**Figure 20. 1.0 A Regulator with 1.2 V Dropout**



Share Feedback
Your Opinion Matters

## TYPICAL APPLICATIONS





**Figure 21. Lithium Ion Battery Cell Charger**






**Figure 22. Low Drift Current Sink**




Error flag occurs when $V_{in}$ is too low to maintain $V_{out}$, or if $V_{out}$ is reduced by excessive load current.

**Figure 23. Latch Off When Error Flag Occurs**






**Figure 24. 5.0 V Regulator with 2.5 V Sleep Function**



Share Feedback
Your Opinion Matters




All diodes are 1N4148.


Early Warning flag on low input voltage.

Main output latches off at lower input voltages.

Battery backup on auxiliary output.

Operation: Regulator #1's $V_{out}$ is programmed one diode drop above 5.0 V. Its error flag becomes active when $V_{in} \leq 5.7$ V. When $V_{in}$ drops below 5.3 V, the error flag of regulator #2 becomes active and via Q1 latches the main output "off". When $V_{in}$ again exceeds 5.7 V, regulator #1 is back in regulation and the early warning signal rises, unlatching regulator #2 via D3.

**Figure 25. Regulator with Early Warning and Auxiliary Output**




$V_{out} = 1.25V\ (1.0 + R1/R2)$

For 5.0 V output, use internal resistors. Wire Pin 6 to 7, and wire Pin 2 to $+V_{out}$ Bus.

**Figure 26. 2.0 A Low Dropout Regulator**



Share Feedback
Your Opinion Matters





**Figure 27. Open Circuit Detector for 4.0 to 20 mA Current Loop**





**Figure 28. Low Battery Disconnect**





**Figure 29. DPAK Thermal Resistance and Maximum Power Dissipation versus PCB Copper Length**



Share Feedback
Your Opinion Matters

## ORDERING INFORMATION (LP2950)

| Part Number | Output Voltage (Volts) | Tolerance (%) | Package | Shipping† |
|---|---|---|---|---|
| LP2950CZ−3.0G | 3.0 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950CZ−3.0RAG | 3.0 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950ACZ−3.0G | 3.0 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950ACZ−3.0RAG | 3.0 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950CZ−3.3G | 3.3 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950CZ−3.3RAG | 3.3 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950ACZ−3.3G | 3.3 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950ACZ−3.3RAG | 3.3 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950CZ−5.0G | 5.0 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950CZ−5.0RAG | 5.0 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950CZ−5.0RPG | 5.0 | 1.0 | TO−92 (Pb−Free) | 2000 Units / Ammo Pack |
| LP2950ACZ−5.0G | 5.0 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Bag |
| LP2950ACZ−5.0RAG | 5.0 | 0.5 | TO−92 (Pb−Free) | 2000 Units / Tape & Reel |
| LP2950CDT−3.0RKG | 3.0 | 1.0 | DPAK (Pb−Free) | 2500 Units / Tape & Reel |
| LP2950CDT−3.3G | 3.3 | 1.0 | DPAK (Pb−Free) | 75 Units / Rail |
| LP2950CDT−3.3RKG | 3.3 | 1.0 | DPAK (Pb−Free) | 2500 Units / Tape & Reel |
| LP2950ACDT−3.3RG | 3.3 | 0.5 | DPAK (Pb−Free) | 2500 Units / Tape & Reel |
| LP2950CDT−5.0G | 5.0 | 1.0 | DPAK (Pb−Free) | 75 Units / Rail |
| LP2950CDT−5.0RKG | 5.0 | 1.0 | DPAK (Pb−Free) | 2500 Units / Tape & Reel |
| LP2950ACDT−5.0G | 5.0 | 0.5 | DPAK (Pb−Free) | 75 Units / Rail |
| LP2950ACDT−5RKG | 5.0 | 0.5 | DPAK (Pb−Free) | 2500 Units / Tape & Reel |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.



Share Feedback
Your Opinion Matters

## ORDERING INFORMATION (LP2951)

| Part Number | Output Voltage (Volts) | Tolerance (%) | Package | Shipping† |
|---|---|---|---|---|
| LP2951CD−3.0R2G | 3.0 | 1.0 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951ACD−3.0R2G | 3.0 | 0.5 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951CD−3.3R2G | 3.3 | 1.0 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951ACD−3.3G | 3.3 | 0.5 | SOIC−8 (Pb−Free) | 98 Units / Rail |
| LP2951ACD−3.3R2G | 3.3 | 0.5 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951CDG | 5.0 or Adj. | 1.0 | SOIC−8 (Pb−Free) | 98 Units / Rail |
| LP2951CDR2G | 5.0 or Adj. | 1.0 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951ACDG | 5.0 or Adj. | 0.5 | SOIC−8 (Pb−Free) | 98 Units / Rail |
| LP2951ACDR2G | 5.0 or Adj. | 0.5 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| LP2951ACDM−3.0RG | 3.0 | 0.5 | Micro8 (Pb−Free) | 4000 Units / Tape & Reel |
| LP2951ACDM−3.3RG | 3.3 | 0.5 | Micro8 (Pb−Free) | 4000 Units / Tape & Reel |
| LP2951CDMR2G | 5.0 or Adj. | 1.0 | Micro8 (Pb−Free) | 4000 Units / Tape & Reel |
| LP2951ACDMR2G | 5.0 or Adj. | 0.5 | Micro8 (Pb−Free) | 4000 Units / Tape & Reel |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

## ORDERING INFORMATION (NCV2951)


| Part Number | Output Voltage (Volts) | Tolerance (%) | Package | Shipping† |
|---|---|---|---|---|
| NCV2951ACD3.3R2G* | 3.3 | 0.5 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| NCV2951ACDR2G* | 5.0 or Adj. | 0.5 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| NCV2951CDR2G* | 5.0 or Adj. | 1.0 | SOIC−8 (Pb−Free) | 2500 Units / Tape & Reel |
| NCV2951ACDMR2G* | 5.0 or Adj. | 0.5 | Micro8 (Pb−Free) | 4000 Units / Tape & Reel |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.
*NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable.



Share Feedback
Your Opinion Matters

## MARKING DIAGRAMS


**TO−92**
**CASE 029**





**DPAK**
**CASE 369C**





**SOIC−8**
**CASE 751**




**PDIP−8**
**CASE 626**




**Micro8**
**CASE 846A**




xx = 3.0, 3.3, or 5.0
y = 3 or 5
yy = 30, 33, or 50
z = A or C
A = Assembly Location
WL, L = Wafer Lot
YY, Y = Year
WW, W = Work Week
G = Pb−Free Package
▪ = Pb−Free Package
(Note: Microdot may be in either location)

*This marking diagram also applies to NCV2951.




Share Feedback
Your Opinion Matters


**TO−92 (TO−226) 1 WATT**
CASE 29−10
ISSUE D

DATE 05 MAR 2021


SCALE 1:1




## STRAIGHT LEAD




END VIEW




TOP VIEW

NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH OR GATE PROTRUSIONS.
4. DIMENSION b AND b2 DOES NOT INCLUDE DAMBAR PROTRUSION. LEAD WIDTH INCLUDING PROTRUSION SHALL NOT EXCEED 0.20. DIMENSION b2 LOCATED ABOVE THE DAMBAR PORTION OF MIDDLE LEAD.

| | MILLIMETERS | | |
|---|---|---|---|
| DIM | MIN. | NOM. | MAX. |
| A | 3.75 | 3.90 | 4.05 |
| A1 | 1.28 | 1.43 | 1.58 |
| b | 0.38 | 0.465 | 0.55 |
| b2 | 0.62 | 0.70 | 0.78 |
| c | 0.35 | 0.40 | 0.45 |
| D | 7.85 | 8.00 | 8.15 |
| E | 4.75 | 4.90 | 5.05 |
| E2 | 3.90 | --- | --- |
| e | 1.27 BSC | | |
| L | 13.80 | 14.00 | 14.20 |

**STYLES AND MARKING ON PAGE 3**




**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2019

**TO−92 (TO−226) 1 WATT**
CASE 29−10
ISSUE D

DATE 05 MAR 2021

FORMED LEAD




NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH OR GATE PROTRUSIONS.
4. DIMENSION b AND b2 DOES NOT INCLUDE DAMBAR PROTRUSION. LEAD WIDTH INCLUDING PROTRUSION SHALL NOT EXCEED 0.20. DIMENSION b2 LOCATED ABOVE THE DAMBAR PORTION OF MIDDLE LEAD.

| | MILLIMETERS | | |
|---|---|---|---|
| DIM | MIN. | NOM. | MAX. |
| A | 3.75 | 3.90 | 4.05 |
| A1 | 1.28 | 1.43 | 1.58 |
| b | 0.38 | 0.465 | 0.55 |
| b2 | 0.62 | 0.70 | 0.78 |
| c | 0.35 | 0.40 | 0.45 |
| D | 7.85 | 8.00 | 8.15 |
| E | 4.75 | 4.90 | 5.05 |
| E2 | 3.90 | --- | --- |
| e | 2.50 BSC | | |
| L | 13.80 | 14.00 | 14.20 |
| L2 | 13.20 | 13.60 | 14.00 |
| L3 | 3.00 REF | | |

**STYLES AND MARKING ON PAGE 3**



**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2019

**TO−92 (TO−226) 1 WATT**
CASE 29−10
ISSUE D

DATE 05 MAR 2021

STYLE 1:
PIN 1. EMITTER
2. BASE
3. COLLECTOR

STYLE 2:
PIN 1. BASE
2. EMITTER
3. COLLECTOR

STYLE 3:
PIN 1. ANODE
2. ANODE
3. CATHODE

STYLE 4:
PIN 1. CATHODE
2. CATHODE
3. ANODE

STYLE 5:
PIN 1. DRAIN
2. SOURCE
3. GATE

STYLE 6:
PIN 1. GATE
2. SOURCE & SUBSTRATE
3. DRAIN

STYLE 7:
PIN 1. SOURCE
2. DRAIN
3. GATE

STYLE 8:
PIN 1. DRAIN
2. GATE
3. SOURCE & SUBSTRATE

STYLE 9:
PIN 1. BASE 1
2. EMITTER
3. BASE 2

STYLE 10:
PIN 1. CATHODE
2. GATE
3. ANODE

STYLE 11:
PIN 1. ANODE
2. CATHODE & ANODE
3. CATHODE

STYLE 12:
PIN 1. MAIN TERMINAL 1
2. GATE
3. MAIN TERMINAL 2

STYLE 13:
PIN 1. ANODE 1
2. GATE
3. CATHODE 2

STYLE 14:
PIN 1. EMITTER
2. COLLECTOR
3. BASE

STYLE 15:
PIN 1. ANODE 1
2. CATHODE
3. ANODE 2

STYLE 16:
PIN 1. ANODE
2. GATE
3. CATHODE

STYLE 17:
PIN 1. COLLECTOR
2. BASE
3. EMITTER

STYLE 18:
PIN 1. ANODE
2. CATHODE
3. NOT CONNECTED

STYLE 19:
PIN 1. GATE
2. ANODE
3. CATHODE

STYLE 20:
PIN 1. NOT CONNECTED
2. CATHODE
3. ANODE

STYLE 21:
PIN 1. COLLECTOR
2. EMITTER
3. BASE

STYLE 22:
PIN 1. SOURCE
2. GATE
3. DRAIN

STYLE 23:
PIN 1. GATE
2. SOURCE
3. DRAIN

STYLE 24:
PIN 1. EMITTER
2. COLLECTOR/ANODE
3. CATHODE

STYLE 25:
PIN 1. MT 1
2. GATE
3. MT 2

STYLE 26:
PIN 1. $V_{CC}$
2. GROUND 2
3. OUTPUT

STYLE 27:
PIN 1. MT
2. SUBSTRATE
3. MT

STYLE 28:
PIN 1. CATHODE
2. ANODE
3. GATE

STYLE 29:
PIN 1. NOT CONNECTED
2. ANODE
3. CATHODE

STYLE 30:
PIN 1. DRAIN
2. GATE
3. SOURCE

STYLE 31:
PIN 1. GATE
2. DRAIN
3. SOURCE

STYLE 32:
PIN 1. BASE
2. COLLECTOR
3. EMITTER

STYLE 33:
PIN 1. RETURN
2. INPUT
3. OUTPUT

STYLE 34:
PIN 1. INPUT
2. GROUND
3. LOGIC

STYLE 35:
PIN 1. GATE
2. COLLECTOR
3. EMITTER

## GENERIC MARKING DIAGRAM*




XXXX = Specific Device Code
A = Assembly Location
L = Wafer Lot
Y = Year
W = Work Week
▪ = Pb−Free Package


(Note: Microdot may be in either location)

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.




**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.


© Semiconductor Components Industries, LLC, 2019





**SCALE 1:1**

**DPAK−3 6.10x6.54x2.28, 2.29P**
CASE 369C
ISSUE L

DATE 24 AUG 2026





TOP VIEW





SIDE VIEW

| MILLIMETERS | | | |
|---|---|---|---|
| DIM | MIN | NOM | MAX |
| A | 2.18 | 2.28 | 2.38 |
| A1 | 0.00 | −−− | 0.13 |
| b | 0.63 | 0.76 | 0.89 |
| b2 | 0.72 | 0.93 | 1.14 |
| b3 | 4.57 | 5.02 | 5.46 |
| c | 0.46 | 0.54 | 0.61 |
| c2 | 0.46 | 0.54 | 0.61 |
| D | 5.97 | 6.10 | 6.22 |
| E | 6.35 | 6.54 | 6.73 |
| e | 2.29 BSC | | |
| H | 9.40 | 9.91 | 10.41 |
| L | 1.40 | 1.59 | 1.78 |
| L1 | 2.90 REF | | |
| L2 | 0.51 BSC | | |
| L3 | 0.89 | −−− | 1.27 |
| L4 | −−− | −−− | 1.01 |
| Z | 3.93 | −−− | −−− |





BOTTOM VIEW





ALTERNATE CONSTRUCTIONS

NOTES:

1. DIMENSIONING AND TOLERANCING ASME Y14.5M, 2018.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. THERMAL PAD CONTOUR OPTIONAL WITHIN DIMENSIONS b3, L3, AND Z.
4. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR BURRS.
5. DIMENSIONS D AND E ARE DETERMINED AT THE OUTERMOST EXTREMES OF THE PLASTIC BODY.
6. DATUMS A AND B ARE DETERMINED AT DATUM PLANE H.
7. OPTIONAL MOLD FEATURE.




DETAIL A
ROTATED 90° CW




RECOMMENDED MOUNTING FOOTPRINT*
*For additional information on our Pb−Free strategy and soldering details, please download the onsemi Soldering and Mounting Techniques reference manual, SOLDERRM/D.


| | | |
|---|---|---|
| **DOCUMENT NUMBER:** | **98AON10527D** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |
| **DESCRIPTION:** | **DPAK−3 6.10x6.54x2.28, 2.29P** | **PAGE 1 OF 2** |

**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

**DPAK−3 6.10x6.54x2.28, 2.29P**
CASE 369C
ISSUE L

DATE 24 AUG 2026

## GENERIC MARKING DIAGRAM*




**IC** **Discrete**

| | |
|---|---|
| XXXXXX | = Device Code |
| A | = Assembly Location |
| L | = Wafer Lot |
| Y | = Year |
| WW | = Work Week |
| G | = Pb−Free Package |

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

STYLE 1:
PIN 1. BASE
2. COLLECTOR
3. EMITTER
4. COLLECTOR

STYLE 2:
PIN 1. GATE
2. DRAIN
3. SOURCE
4. DRAIN

STYLE 3:
PIN 1. ANODE
2. CATHODE
3. ANODE
4. CATHODE

STYLE 4:
PIN 1. CATHODE
2. ANODE
3. GATE
4. ANODE

STYLE 5:
PIN 1. GATE
2. ANODE
3. CATHODE
4. ANODE

STYLE 6:
PIN 1. MT1
2. MT2
3. GATE
4. MT2

STYLE 7:
PIN 1. GATE
2. COLLECTOR
3. EMITTER
4. COLLECTOR

STYLE 8:
PIN 1. N/C
2. CATHODE
3. ANODE
4. CATHODE

STYLE 9:
PIN 1. ANODE
2. CATHODE
3. RESISTOR ADJUST
4. CATHODE

STYLE 10:
PIN 1. CATHODE
2. ANODE
3. CATHODE
4. ANODE




**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.


© Semiconductor Components Industries, LLC, 2011




**SCALE 1:1**

**PDIP–8**
CASE 626–05
ISSUE P


DATE 22 APR 2015





**TOP VIEW**




**END VIEW**
**WITH LEADS CONSTRAINED**
**NOTE 5**




**SIDE VIEW**





**END VIEW**
**NOTE 6**

NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: INCHES.
3. DIMENSIONS A, A1 AND L ARE MEASURED WITH THE PACKAGE SEATED IN JEDEC SEATING PLANE GAUGE GS–3.
4. DIMENSIONS D, D1 AND E1 DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS. MOLD FLASH OR PROTRUSIONS ARE NOT TO EXCEED 0.10 INCH.
5. DIMENSION E IS MEASURED AT A POINT 0.015 BELOW DATUM PLANE H WITH THE LEADS CONSTRAINED PERPENDICULAR TO DATUM C.
6. DIMENSION eB IS MEASURED AT THE LEAD TIPS WITH THE LEADS UNCONSTRAINED.
7. DATUM PLANE H IS COINCIDENT WITH THE BOTTOM OF THE LEADS, WHERE THE LEADS EXIT THE BODY.
8. PACKAGE CONTOUR IS OPTIONAL (ROUNDED OR SQUARE CORNERS).

| | INCHES | | MILLIMETERS | |
|---|---|---|---|---|
| DIM | MIN | MAX | MIN | MAX |
| A | ---- | 0.210 | --- | 5.33 |
| A1 | 0.015 | ---- | 0.38 | --- |
| A2 | 0.115 | 0.195 | 2.92 | 4.95 |
| b | 0.014 | 0.022 | 0.35 | 0.56 |
| b2 | 0.060 TYP | | 1.52 TYP | |
| C | 0.008 | 0.014 | 0.20 | 0.36 |
| D | 0.355 | 0.400 | 9.02 | 10.16 |
| D1 | 0.005 | ---- | 0.13 | --- |
| E | 0.300 | 0.325 | 7.62 | 8.26 |
| E1 | 0.240 | 0.280 | 6.10 | 7.11 |
| e | 0.100 BSC | | 2.54 BSC | |
| eB | ---- | 0.430 | --- | 10.92 |
| L | 0.115 | 0.150 | 2.92 | 3.81 |
| M | ---- | 10° | --- | 10° |

STYLE 1:
PIN 1. AC IN
2. DC + IN
3. DC – IN
4. AC IN
5. GROUND
6. OUTPUT
7. AUXILIARY
8. $V_{CC}$

**GENERIC**
**MARKING DIAGRAM***




XXXX = Specific Device Code
A = Assembly Location
WL = Wafer Lot
YY = Year
WW = Work Week
G = Pb–Free Package

*This information is generic. Please refer to device data sheet for actual part marking. Pb–Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

| | | |
|---|---|---|
| **DOCUMENT NUMBER:** | **98ASB42420B** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red. |
| **DESCRIPTION:** | **PDIP–8** | **PAGE 1 OF 1** |

**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.


© Semiconductor Components Industries, LLC, 2019



**SCALE 1:1**

**SOIC−8 NB**
CASE 751−07
ISSUE AK


DATE 16 FEB 2011




NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: MILLIMETER.
3. DIMENSION A AND B DO NOT INCLUDE MOLD PROTRUSION.
4. MAXIMUM MOLD PROTRUSION 0.15 (0.006) PER SIDE.
5. DIMENSION D DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL BE 0.127 (0.005) TOTAL IN EXCESS OF THE D DIMENSION AT MAXIMUM MATERIAL CONDITION.
6. 751−01 THRU 751−06 ARE OBSOLETE. NEW STANDARD IS 751−07.

| | MILLIMETERS | | INCHES | |
|---|---|---|---|---|
| DIM | MIN | MAX | MIN | MAX |
| A | 4.80 | 5.00 | 0.189 | 0.197 |
| B | 3.80 | 4.00 | 0.150 | 0.157 |
| C | 1.35 | 1.75 | 0.053 | 0.069 |
| D | 0.33 | 0.51 | 0.013 | 0.020 |
| G | 1.27 BSC | | 0.050 BSC | |
| H | 0.10 | 0.25 | 0.004 | 0.010 |
| J | 0.19 | 0.25 | 0.007 | 0.010 |
| K | 0.40 | 1.27 | 0.016 | 0.050 |
| M | 0° | 8° | 0° | 8° |
| N | 0.25 | 0.50 | 0.010 | 0.020 |
| S | 5.80 | 6.20 | 0.228 | 0.244 |


## SOLDERING FOOTPRINT*




SCALE 6:1 (mm / inches)

*For additional information on our Pb−Free strategy and soldering details, please download the **onsemi** Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

## GENERIC MARKING DIAGRAM*




XXXXX = Specific Device Code
A = Assembly Location
L = Wafer Lot
Y = Year
W = Work Week
▪ = Pb−Free Package

XXXXXX = Specific Device Code
A = Assembly Location
Y = Year
WW = Work Week
▪ = Pb−Free Package

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, "G" or microdot "▪", may or may not be present. Some products may not follow the Generic Marking.

**STYLES ON PAGE 2**

| | | | |
|---|---|---|---|
| **DOCUMENT NUMBER:** | **98ASB42564B** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. | |
| **DESCRIPTION:** | **SOIC−8 NB** | | **PAGE 1 OF 2** |

**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

**SOIC−8 NB**
CASE 751−07
ISSUE AK

DATE 16 FEB 2011

STYLE 1:
PIN 1. EMITTER
2. COLLECTOR
3. COLLECTOR
4. EMITTER
5. EMITTER
6. BASE
7. BASE
8. EMITTER

STYLE 2:
PIN 1. COLLECTOR, DIE, #1
2. COLLECTOR, #1
3. COLLECTOR, #2
4. COLLECTOR, #2
5. BASE, #2
6. EMITTER, #2
7. BASE, #1
8. EMITTER, #1

STYLE 3:
PIN 1. DRAIN, DIE #1
2. DRAIN, #1
3. DRAIN, #2
4. DRAIN, #2
5. GATE, #2
6. SOURCE, #2
7. GATE, #1
8. SOURCE, #1

STYLE 4:
PIN 1. ANODE
2. ANODE
3. ANODE
4. ANODE
5. ANODE
6. ANODE
7. ANODE
8. COMMON CATHODE

STYLE 5:
PIN 1. DRAIN
2. DRAIN
3. DRAIN
4. DRAIN
5. GATE
6. GATE
7. SOURCE
8. SOURCE

STYLE 6:
PIN 1. SOURCE
2. DRAIN
3. DRAIN
4. SOURCE
5. SOURCE
6. GATE
7. GATE
8. SOURCE

STYLE 7:
PIN 1. INPUT
2. EXTERNAL BYPASS
3. THIRD STAGE SOURCE
4. GROUND
5. DRAIN
6. GATE 3
7. SECOND STAGE Vd
8. FIRST STAGE Vd

STYLE 8:
PIN 1. COLLECTOR, DIE #1
2. BASE, #1
3. BASE, #2
4. COLLECTOR, #2
5. COLLECTOR, #2
6. EMITTER, #2
7. EMITTER, #1
8. COLLECTOR, #1

STYLE 9:
PIN 1. EMITTER, COMMON
2. COLLECTOR, DIE #1
3. COLLECTOR, DIE #2
4. EMITTER, COMMON
5. EMITTER, COMMON
6. BASE, DIE #2
7. BASE, DIE #1
8. EMITTER, COMMON

STYLE 10:
PIN 1. GROUND
2. BIAS 1
3. OUTPUT
4. GROUND
5. GROUND
6. BIAS 2
7. INPUT
8. GROUND

STYLE 11:
PIN 1. SOURCE 1
2. GATE 1
3. SOURCE 2
4. GATE 2
5. DRAIN 2
6. DRAIN 2
7. DRAIN 1
8. DRAIN 1

STYLE 12:
PIN 1. SOURCE
2. SOURCE
3. SOURCE
4. GATE
5. DRAIN
6. DRAIN
7. DRAIN
8. DRAIN

STYLE 13:
PIN 1. N.C.
2. SOURCE
3. SOURCE
4. GATE
5. DRAIN
6. DRAIN
7. DRAIN
8. DRAIN

STYLE 14:
PIN 1. N−SOURCE
2. N−GATE
3. P−SOURCE
4. P−GATE
5. P−DRAIN
6. P−DRAIN
7. N−DRAIN
8. N−DRAIN

STYLE 15:
PIN 1. ANODE 1
2. ANODE 1
3. ANODE 1
4. ANODE 1
5. CATHODE, COMMON
6. CATHODE, COMMON
7. CATHODE, COMMON
8. CATHODE, COMMON

STYLE 16:
PIN 1. EMITTER, DIE #1
2. BASE, DIE #1
3. EMITTER, DIE #2
4. BASE, DIE #2
5. COLLECTOR, DIE #2
6. COLLECTOR, DIE #2
7. COLLECTOR, DIE #1
8. COLLECTOR, DIE #1

STYLE 17:
PIN 1. VCC
2. V2OUT
3. V1OUT
4. TXE
5. RXE
6. VEE
7. GND
8. ACC

STYLE 18:
PIN 1. ANODE
2. ANODE
3. SOURCE
4. GATE
5. DRAIN
6. DRAIN
7. CATHODE
8. CATHODE

STYLE 19:
PIN 1. SOURCE 1
2. GATE 1
3. SOURCE 2
4. GATE 2
5. DRAIN 2
6. MIRROR 2
7. DRAIN 1
8. MIRROR 1

STYLE 20:
PIN 1. SOURCE (N)
2. GATE (N)
3. SOURCE (P)
4. GATE (P)
5. DRAIN
6. DRAIN
7. DRAIN
8. DRAIN

STYLE 21:
PIN 1. CATHODE 1
2. CATHODE 2
3. CATHODE 3
4. CATHODE 4
5. CATHODE 5
6. COMMON ANODE
7. COMMON ANODE
8. CATHODE 6

STYLE 22:
PIN 1. I/O LINE 1
2. COMMON CATHODE/VCC
3. COMMON CATHODE/VCC
4. I/O LINE 3
5. COMMON ANODE/GND
6. I/O LINE 4
7. I/O LINE 5
8. COMMON ANODE/GND

STYLE 23:
PIN 1. LINE 1 IN
2. COMMON ANODE/GND
3. COMMON ANODE/GND
4. LINE 2 IN
5. LINE 2 OUT
6. COMMON ANODE/GND
7. COMMON ANODE/GND
8. LINE 1 OUT

STYLE 24:
PIN 1. BASE
2. EMITTER
3. COLLECTOR/ANODE
4. COLLECTOR/ANODE
5. CATHODE
6. CATHODE
7. COLLECTOR/ANODE
8. COLLECTOR/ANODE

STYLE 25:
PIN 1. VIN
2. N/C
3. REXT
4. GND
5. IOUT
6. IOUT
7. IOUT
8. IOUT

STYLE 26:
PIN 1. GND
2. dv/dt
3. ENABLE
4. ILIMIT
5. SOURCE
6. SOURCE
7. SOURCE
8. VCC

STYLE 27:
PIN 1. ILIMIT
2. OVLO
3. UVLO
4. INPUT+
5. SOURCE
6. SOURCE
7. SOURCE
8. DRAIN

STYLE 28:
PIN 1. SW_TO_GND
2. DASIC_OFF
3. DASIC_SW_DET
4. GND
5. V_MON
6. VBULK
7. VBULK
8. VIN


STYLE 29:
PIN 1. BASE, DIE #1
2. EMITTER, #1
3. BASE, #2
4. EMITTER, #2
5. COLLECTOR, #2
6. COLLECTOR, #2
7. COLLECTOR, #1
8. COLLECTOR, #1

STYLE 30:
PIN 1. DRAIN 1
2. DRAIN 1
3. GATE 2
4. SOURCE 2
5. SOURCE 1/DRAIN 2
6. SOURCE 1/DRAIN 2
7. SOURCE 1/DRAIN 2
8. GATE 1

| | | | |
|---|---|---|---|
| **DOCUMENT NUMBER:** | **98ASB42564B** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. | |
| **DESCRIPTION:** | **SOIC−8 NB** | | **PAGE 2 OF 2** |

**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.


© Semiconductor Components Industries, LLC, 2019




**SCALE 2:1**

**Micro8**
CASE 846A–02
ISSUE K


DATE 16 JUL 2020




NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DIMENSION b DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE PROTRUSION SHALL BE 0.10 mm IN EXCESS OF MAXIMUM MATERIAL CONDITION.
4. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSION OR GATE BURRS. MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED 0.15 mm PER SIDE. DIMENSION E DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION. INTERLEAD FLASH OR PROTRUSION SHALL NOT EXCEED 0.25 mm PER SIDE. DIMENSIONS D AND E ARE DETERMINED AT DATUM F.
5. DATUMS A AND B ARE TO BE DETERMINED AT DATUM F.
6. A1 IS DEFINED AS THE VERTICAL DISTANCE FROM THE SEATING PLANE TO THE LOWEST POINT ON THE PACKAGE BODY.





RECOMMENDED
MOUNTING FOOTPRINT

For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

| DIM | MILLIMETERS | | |
|---|---|---|---|
| | MIN. | NOM. | MAX. |
| A | --- | --- | 1.10 |
| A1 | 0.05 | 0.08 | 0.15 |
| b | 0.25 | 0.33 | 0.40 |
| c | 0.13 | 0.18 | 0.23 |
| D | 2.90 | 3.00 | 3.10 |
| E | 2.90 | 3.00 | 3.10 |
| e | 0.65 BSC | | |
| $H_E$ | 4.75 | 4.90 | 5.05 |
| L | 0.40 | 0.55 | 0.70 |

## GENERIC MARKING DIAGRAM*




XXXX = Specific Device Code
A = Assembly Location
Y = Year
W = Work Week
▪ = Pb–Free Package

(Note: Microdot may be in either location)

*This information is generic. Please refer to device data sheet for actual part marking. Pb–Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

STYLE 1:
PIN 1. SOURCE
2. SOURCE
3. SOURCE
4. GATE
5. DRAIN
6. DRAIN
7. DRAIN
8. DRAIN

STYLE 2:
PIN 1. SOURCE 1
2. GATE 1
3. SOURCE 2
4. GATE 2
5. DRAIN 2
6. DRAIN 2
7. DRAIN 1
8. DRAIN 1

STYLE 3:
PIN 1. N-SOURCE
2. N-GATE
3. P-SOURCE
4. P-GATE
5. P-DRAIN
6. P-DRAIN
7. N-DRAIN
8. N-DRAIN

| | | |
|---|---|---|
| **DOCUMENT NUMBER:** | **98ASB14087C** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red. |
| **DESCRIPTION:** | **MICRO8** | **PAGE 1 OF 1** |

**onsemi** and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

**onsemi**, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS**:
**Technical Library:** www.onsemi.com/design/resources/technical−documentation
**onsemi Website:** www.onsemi.com

**ONLINE SUPPORT**: www.onsemi.com/support
**For additional information, please contact your local Sales Representative at** www.onsemi.com/support/sales

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

# Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

### Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

**www.entegreci.com**

### Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

**Kategorilere göz atın**

### Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

**Üreticileri görün**

### Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

**Teklif isteyin**

**www.entegreci.com** | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.