Voltage Regulator - Low-Drop, Reset

450 mA

NCV4275C

The NCV4275C is an integrated low dropout regulator designed for use in harsh automotive environments. It includes wide operating temperature and input voltage ranges. The output is regulated at 5.0 V or 3.3 V and is rated to 450 mA of output current. It also provides a number of features, including overcurrent protection, overtemperature protection and a programmable microprocessor reset. The NCV4275C is available in the DPAK and D^2PAK surface mount packages. The output is stable over a wide output capacitance and ESR range. The NCV4275C is pin for pin compatible with NCV4275A.

Features

- 5.0 V or 3.3 V ±2% Output Voltage Options
- 450 mA Output Current
- Very Low Current Consumption
- Active Reset Output
- Reset Low Down to V_Q = 1.0 V
- 500 mV (max) Dropout Voltage
- Fault Protection
  - +45 V Peak Transient Voltage
  - −42 V Reverse Voltage
  - Short Circuit Protection
  - Thermal Overload Protection
- AEC-Q100 Qualified and PPAP Capable
- These are Pb-Free Devices

Applications

- Auto Body Electronics



Figure 1. Block Diagram

MARKING DIAGRAMS



DPAK
5-PIN
DT SUFFIX
CASE 175AA





D^2PAK
5-PIN
DS SUFFIX
CASE 936A-02



x	= 5 (5.0 V Output) or 3 (3.3 V Output)
A	= Assembly Location
WL, L	= Wafer Lot
Y	= Year
WW	= Work Week
G	= Pb-Free Package

ORDERING INFORMATION

See detailed ordering and shipping information on page 13 of this data sheet.

NOTE: Some of the devices on this data sheet have been **DISCONTINUED**. Please refer to the table on page 13.

© Semiconductor Components Industries, LLC, 2014

PIN FUNCTION DESCRIPTION

Pin No. DPAK-5 D2PAK-5	Symbol	Description
1	I	Input; Battery Supply Input Voltage. Bypass to ground with a ceramic capacitor.
2	RO	Reset Output; Open Collector Active Reset (accurate when I > 1.0 V).
3, TAB	GND	Ground; Pin 3 internally connected to tab.
4	D	Reset Delay; timing capacitor to GND for Reset Delay function.
5	Q	Output; ±2.0%, 450 mA output. Bypass with 22 μF capacitor, ESR < 4.5 Ω (5.0 V Version), 3.5 Ω (3.3 V Version).

MAXIMUM RATINGS

Rating	Symbol	Min	Max	Unit
Input Voltage	V_I	−42	45	V
Input Peak Transient Voltage	V_I	–	45	V
Output Voltage	V_Q	−1.0	16	V
Reset Output Voltage	V_{RO}	−0.3	25	V
Reset Output Current	I_{RO}	−5.0	5.0	mA
Reset Delay Voltage	V_D	−0.3	7.0	V
Reset Delay Current	I_D	−2.0	2.0	mA
ESD Susceptibility (Note 1) – Human Body Model – Machine Model – Charge Device Model	ESD_{HBM} ESD_{MM} ESD_{CDM}	4.0 200 1000	– – –	kV V V
Junction Temperature	T_J	−40	150	°C
Storage Temperature	T_{stg}	−55	150	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected. Operating the device outside its recommended conditions, but still within its maximum rated limits may not cause immediate damage. However, doing so can lead to reduced performance, unpredictable behavior, and potentially shorten the device's lifespan or reliability.

1. This device incorporates ESD protection and is tested by the followign methods: ESD Human Body Model tested per AEC-Q100-002, ESD Machine Model tested per AEC-Q100-003, ESD Charged Device Model tested per AEC-Q100-011, Latch-up tested per AEC-Q100-004.

OPERATING RANGE

Rating	Symbol	Min	Max	Unit
Input Voltage Operating Range, 5.0 V Output	V_I	5.5	42	V
Input Voltage Operating Range, 3.3 V Output	V_I	4.4	42	V
Junction Temperature	T_J	−40	150	°C

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

LEAD TEMPERATURE SOLDERING REFLOW AND MSL (Note 2)

Rating	Symbol	Min	Max	Unit
Lead Free, 60 sec−150 sec above 217 °C	T_{SLD}	–	265 Peak	°C
Moisture Sensitivity Level	MSL	1		

Share Feedback
Your Opinion Matters

THERMAL CHARACTERISTICS

Characteristic	Test Conditions (Typical Value)		Unit
DPAK 5-PIN PACKAGE			
	Min Pad Board (Note 3)	1 in Pad Board (Note 4)	
Junction-to-Tab ($R_{\theta JT}$)	5.1	5.5	°C/W
Junction-to-Ambient ($R_{\theta JA}$)	82.4	58.1	°C/W
D^2PAK 5-PIN PACKAGE			
	0.4 sq. in. Spreader Board (Note 5)	1.2 sq. in. Spreader Board (Note 6)	
Junction-to-Tab ($R_{\theta JT}$)	4.5	4.8	°C/W
Junction-to-Ambient ($R_{\theta JA}$)	66.0	49.0	°C/W

2. PR_R IPC / JEDEC J-STD-020C
3. 1 oz. copper, 0.26 $inch^2$ (168 mm^2) copper area, 0.062″ thick FR4.
4. 1 oz. copper, 1.14 $inch^2$ (736 mm^2) copper area, 0.062″ thick FR4.
5. 1 oz. copper, 0.373 $inch^2$ (241 mm^2) copper area, 0.062″ thick FR4.
6. 1 oz. copper, 1.222 $inch^2$ (788 mm^2) copper area, 0.062″ thick FR4.

Share Feedback
Your Opinion Matters

ELECTRICAL CHARACTERISTICS (V_I = 13.5 V; −40 °C < T_J < 150 °C; unless otherwise noted.)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit
Output						
Output Voltage	V_Q	100 μA ≤ I_Q ≤ 400 mA 6.0 V ≤ V_I ≤ 28 V (5.0 V Version) 4.4 V ≤ V_I ≤ 28 V (3.3 V version)	 4.9 3.23 (2%)	 5.0 3.3	 5.1 3.37 (2%)	V
Output Voltage	V_Q	100 μA ≤ I_Q ≤ 200 mA 6.0 V ≤ V_I ≤ 40 V (5.0 V Version) 4.4 V ≤ V_I ≤ 40 V (3.3 V version)	 4.9 3.23 (2%)	 5.0 3.3	 5.1 3.37 (2%)	V
Output Current Limitation	I_Q	V_Q = 0.9 x $V_{Q,typ}$	450	650	–	mA
Quiescent Current $I_q = I_I - I_Q$	I_q	I_Q = 1.0 mA, T_J = 25 °C	–	135	150	μA
		I_Q = 1.0 mA	–	150	200	μA
		I_Q = 250 mA	–	10	15	mA
		I_Q = 400 mA	–	23	35	mA
Dropout Voltage (Note 7)	V_{dr}	I_Q = 300 mA $V_{dr} = V_I - V_Q$	–	250	500	mV
Load Regulation	ΔV_Q	I_Q = 5.0 mA to 400 mA	−30	15	30	mV
Line Regulation	ΔV_Q	ΔV_I = 8.0 V to 32 V, I_Q = 5.0 mA	−15	5.0	15	mV
Power Supply Ripple Rejection	PSRR	f_r = 100 Hz, V_r = 0.5 V_{pp}	–	60	–	dB
Temperature Output Voltage Drift	dV_Q/dT	––	–	0.5	–	mV/K
Reset Timing D and Output RO						
Reset Switching Threshold 5.0 V Version 3.3 V Version	$V_{Q,rt}$	V_{out} decreasing V_{in} > 5.5 V V_{in} > 4.4 V	 90 90	 93 93	 96 96	% V_{out}
Reset Output Low Voltage	V_{ROL}	$R_{ext} \geq$ 5.0 kΩ, $V_Q \geq$ 1.0 V	–	0.2	0.4	V
Reset Output Leakage Current	I_{ROH}	V_{ROH} = 5.0 V	–	0	10	μA
Reset Charging Current	$I_{D,C}$	V_D = 1.0 V	3.0	5.5	9.0	μA
Upper Timing Threshold	V_{DU}	––	1.5	1.8	2.2	V
Lower Timing Threshold	V_{DL}	––	0.2	0.4	0.7	V
Reset Delay Time	t_{rd}	C_D = 47 nF	10	16	22	ms
Reset Reaction Time	t_{rr}	C_D = 47 nF	–	1.5	4.0	μs
Thermal Shutdown						
Shutdown Temperature (Note 8)	T_{SD}	––	150	–	210	°C

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

7. Only for 5 V Version. Measured when the output voltage V_Q has dropped 100 mV from the nominal value obtained at V_I = 13.5 V.
8. Guaranteed by design, not tested in production.

Share Feedback
Your Opinion Matters

TYPICAL PERFORMANCE CHARACTERISTICS



Figure 2. Output Stability with Output Capacitor ESR



Figure 3. Output Stability with Output Capacitor ESR



Figure 4. Output Stability with Output Capacitor ESR



Figure 5. Output Stability with Output Capacitor ESR



Figure 6. Output Voltage V_Q vs. Temperature T_J



Figure 7. Output Voltage V_Q vs. Temperature T_J

Share Feedback
Your Opinion Matters

TYPICAL PERFORMANCE CHARACTERISTICS



Figure 8. Output Voltage V_Q vs. Input Voltage V_{IN}



Figure 9. Output Voltage V_Q vs. Input Voltage V_{IN}



Figure 10. Output Current I_Q vs. Temperature T_J



Figure 11. Output Current I_Q vs. Temperature T_J



Figure 12. Output Current I_Q vs. Input Voltage V_{IN}



Figure 13. Output Current I_Q vs. Input Voltage V_{IN}

Share Feedback
Your Opinion Matters

TYPICAL PERFORMANCE CHARACTERISTICS



Figure 14. Current Consumption I_q vs. Output Current I_Q



Figure 15. Current Consumption I_q vs. Output Current I_Q



Figure 16. Current Consumption I_q vs. Output Current I_Q



Figure 17. Current Consumption I_q vs. Output Current I_Q



Figure 18. Charge Current $I_{D,C}$ vs. Temperature T_J



Figure 19. Delay Switching Threshold V_{DU}, V_{DL} vs. Temperature T_J

Share Feedback
Your Opinion Matters

TYPICAL PERFORMANCE CHARACTERISTICS



Figure 20. Drop Voltage V_{dr} vs. Output Current I_Q

Share Feedback
Your Opinion Matters

APPLICATION INFORMATION



Figure 21. Test Circuit

CIRCUIT DESCRIPTION

The NCV4275C is an integrated low dropout regulator that provides 5.0 V or 3.3 V, 450 mA protected output and a signal for power on reset. The regulation is provided by a PNP pass transistor controlled by an error amplifier with a bandgap reference, which gives it the lowest possible drop out voltage and best possible temperature stability. The output current capability is 450 mA, and the base drive quiescent current is controlled to prevent over saturation when the input voltage is low or when the output is overloaded. The regulator is protected by both current limit and thermal shutdown. Thermal shutdown occurs above 150 °C to protect the IC during overloads and extreme ambient temperatures. The delay time for the reset output is adjustable by selection of the timing capacitor. See Figure 21, Test Circuit, for circuit element nomenclature illustration.

REGULATOR

The error amplifier compares the reference voltage to a sample of the output voltage (V_Q) and drives the base of a PNP series pass transistor by a buffer. The reference is a bandgap design to give it a temperature-stable output. Saturation control of the PNP is a function of the load current and input voltage. Over saturation of the output power device is prevented, and quiescent current in the ground pin is minimized.

REGULATOR STABILITY CONSIDERATIONS

The input capacitors (C_{I1} and C_{I2}) are necessary to stabilize the input impedance to avoid voltage line influences. Using a resistor of approximately 1.0 Ω in series with C_{I2} can stop potential oscillations caused by stray inductance and capacitance.

The output capacitor helps determine three main characteristics of a linear regulator: startup delay, load transient response and loop stability. The capacitor value and type should be based on cost, availability, size and temperature constraints. A tantalum, aluminum or ceramic capacitors can be used. The range of stability versus capacitance, load current and capacitive ESR is illustrated in Figures 2 to 5. Minimum ESR for C_Q = 22 μF is native ESR of ceramic capacitors. The aluminum electrolytic capacitor is the least expensive solution, but, if the circuit operates at low temperatures (−25 °C to −40 °C), both the capacitance and ESR of the capacitor will vary considerably. The capacitor manufacturer's data sheet usually provides this information.

The value for the output capacitor C_Q shown in Figure 21, Test Circuit, should work for most applications; however, it is not necessarily the optimized solution. Stability is guaranteed for $C_Q \geq 22$ μF and an ESR ≤ 4.5 Ω (5.0 V Version), 3.5 Ω (3.3 V Version). ESR characteristics were measured with ceramic capacitors and additional resistors to emulate ESR. Murata ceramic capacitors were used, GRM32ER71A226ME20 (22 μF, 10 V, X7R, 1210), GRM31MR71E105KA01 (1 μF, 25 V, X7R, 1206).

RESET OUTPUT

The reset output is used as the power on indicator to the microcontroller. This signal indicates when the output voltage is suitable for reliable operation of the controller. It pulls low when the output is not considered to be ready. RO is pulled up to V_Q by an external resistor, typically 5.0 kΩ in value. The input and output conditions that control the Reset Output and the relative timing are illustrated in Figure 22, Reset Timing.

Output voltage regulation must be maintained for the delay time before the reset output signals a valid condition. The delay for the reset output is defined as the amount of time it takes the timing capacitor on the delay pin to charge from a residual voltage of 0.0 V to the upper timing threshold voltage V_{DU}. The charging current for this is $I_{D,C}$ and D pin voltage in steady state is typically 2.4 V. By using typical IC parameters with a 47 nF capacitor on the D pin, the following time delay for 5.0 V regulator is derived:

$t_{RD} = C_D V_{DU} / I_{D,C}$

t_{RD} = 47 nF (1.8 V) / 5.5 μA = 15.4 ms

Other time delays can be obtained by changing the capacitor value.

Share Feedback
Your Opinion Matters



Figure 22. Reset Timing

Share Feedback
Your Opinion Matters

CALCULATING POWER DISSIPATION IN A SINGLE OUTPUT LINEAR REGULATOR

The maximum power dissipation for a single output regulator (Figure 23) is:

$$P_{D(max)} = [V_{I(max)} - V_{Q(min)}]I_{Q(max)} + V_{I(max)}I_q \quad (1)$$

where

$V_{I(max)}$ is the maximum input voltage,

$V_{Q(min)}$ is the minimum output voltage,

$I_{Q(max)}$ is the maximum output current for the application,

I_q is the quiescent current the regulator consumes at $I_{Q(max)}$.

Once the value of $P_{D(max)}$ is known, the maximum permissible value of $R_{\theta JA}$ can be calculated:

$$R_{\theta JA} = \frac{150^\circ C - T_A}{P_D} \quad (2)$$

The value of $R_{\theta JA}$ can then be compared with those in the package section of the data sheet. Those packages with $R_{\theta JA}$'s less than the calculated value in Equation 2 will keep the die temperature below 150 °C.

In some cases, none of the packages will be sufficient to dissipate the heat generated by the IC, and an external heatsink will be required.



Figure 23. Single Output Regulator with Key Performance Parameters Labeled

HEATSINKS

A heatsink effectively increases the surface area of the package to improve the flow of heat away from the IC and into the surrounding air.

Each material in the heat flow path between the IC and the outside environment will have a thermal resistance. Like series electrical resistances, these resistances are summed to determine the value of $R_{\theta JA}$:

$$R_{\theta JA} = R_{\theta JC} + R_{\theta CS} + R_{\theta SA} \quad (3)$$

where

$R_{\theta JC}$ is the junction-to-case thermal resistance,

$R_{\theta CS}$ is the case-to-heatsink thermal resistance,

$R_{\theta SA}$ is the heatsink-to-ambient thermal resistance.

$R_{\theta JC}$ appears in the package section of the data sheet. Like $R_{\theta JA}$, it too is a function of package type. $R_{\theta CS}$ and $R_{\theta SA}$ are functions of the package type, heatsink and the interface between them. These values appear in heatsink data sheets of heatsink manufacturers.

Thermal, mounting, and heatsinking considerations are discussed in the **onsemi** application note AN1040/D.



Figure 24. θJA vs. Copper Spreader Area, DPAK 5-Lead



Figure 25. θJA vs. Copper Spreader Area, D²PAK 5-Lead

Share Feedback
Your Opinion Matters



Figure 26. Single-Pulse Heating Curves, DPAK 5-Lead



Figure 27. Single-Pulse Heating Curves, D^2PAK 5-Lead

Share Feedback
Your Opinion Matters



Figure 28. Duty Cycle for 1” Spreader Boards, DPAK 5-Lead



Figure 29. Duty Cycle for 1” Spreader Boards, D²PAK 5-Lead

ORDERING INFORMATION

Device	Output Voltage	Package	Shipping†
NCV4275CDS50R4G	5.0 V	D2PAK 5-LEAD (Pb-Free)	800 / Tape & Reel
NCV4275CDT50RKG		DPAK-5 (Pb-Free)	2500 / Tape & Reel
NCV4275CDT33RKG	3.3 V	DPAK-5 (Pb-Free)	2500 / Tape & Reel

DISCONTINUED (Note 9)

NCV4275CDS33R4G	3.3 V	D2PAK 5-LEAD (Pb-Free)	800 / Tape & Reel

† For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

9. **DISCONTINUED:** This device is not available. Please contact your **onsemi** representative for information. The most current information on this device may be available on www.onsemi.com.

Share Feedback
Your Opinion Matters

REVISION HISTORY

Revision	Description of Changes	Date
0	Initial production document version release.	1/21/2014
1	Document rebranded to **onsemi** format. OPN NCV4275CDS33R4G marked as discontinued.	2/10/2026

Share Feedback
Your Opinion Matters



SCALE 1:1

DPAK−5, CENTER LEAD CROP
CASE 175AA
ISSUE B

DATE 15 MAY 2014



NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCH.

	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	0.235	0.245	5.97	6.22
B	0.250	0.265	6.35	6.73
C	0.086	0.094	2.19	2.38
D	0.020	0.028	0.51	0.71
E	0.018	0.023	0.46	0.58
F	0.024	0.032	0.61	0.81
G	0.180 BSC		4.56 BSC	
H	0.034	0.040	0.87	1.01
J	0.018	0.023	0.46	0.58
K	0.102	0.114	2.60	2.89
L	0.045 BSC		1.14 BSC	
R	0.170	0.190	4.32	4.83
R1	0.185	0.210	4.70	5.33
S	0.025	0.040	0.63	1.01
U	0.020	−−−	0.51	−−−
V	0.035	0.050	0.89	1.27
Z	0.155	0.170	3.93	4.32

RECOMMENDED SOLDERING FOOTPRINT*



*For additional information on our Pb−Free strategy and soldering details, please download the **onsemi** Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

GENERIC MARKING DIAGRAMS*



IC **Discrete**

XXXXXX	= Device Code
A	= Assembly Location
L	= Wafer Lot
Y	= Year
WW	= Work Week
G	= Pb−Free Package

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “ ▪”, may or may not be present.

DOCUMENT NUMBER:	**98AON12855D**	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red.
DESCRIPTION:	**DPAK−5 CENTER LEAD CROP**	**PAGE 1 OF 1**

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2003



D²PAK 5–LEAD
CASE 936A–02
ISSUE E

DATE 28 JUL 2021

SCALE 1:1



TOP VIEW



SIDE VIEW
DUAL GUAGE CONSTRUCTION



BOTTOM VIEW



SIDE VIEW
SINGLE GUAGE CONSTRUCTION



DETAIL C
TIP LEADFORM
ROTATED 90° CW



BOTTOM VIEW
OPTIONAL CONSTRUCTIONS

NOTES:

1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCHES
3. TAB CONTOUR OPTIONAL WITHIN DIMENSIONS A AND K.
4. DIMENSIONS U AND V ESTABLISH A MINIMUM MOUNTING SURFACE FOR TERMINAL 4.
5. DIMENSIONS A AND B DO NOT INCLUDE MOLD FLASH OR GATE PROTRUSIONS. MOLD FLASH AND GATE PROTRUSIONS NOT TO EXCEED 0.025 (0.635) MAXIMUM.

	INCHES		MILLIMETERS	
DIM	MIN.	MAX.	MIN.	MAX.
A	0.396	0.403	9.804	10.236
B	0.356	0.368	9.042	9.347
C	0.170	0.180	4.318	4.572
D	0.026	0.036	0.660	0.914
ED	0.045	0.055	1.143	1.397
ES	0.018	0.026	0.457	0.660
G	0.067 BSC		1.702 BSC	
H	0.539	0.579	13.691	14.707
K	0.050 REF		1.270 REF	
L	0.000	0.010	0.000	0.254
M	0.088	0.102	2.235	2.591
N	0.018	0.026	0.457	0.660
P	0.058	0.078	1.473	1.981
R	0°	8°	0°	8°
S	0.116 REF		2.946 REF	
U	0.200 MIN		5.080 MIN	
V	0.250 MIN		6.350 MIN	

GENERIC MARKING DIAGRAM*



XXXXXX	= Device Code
A	= Assembly Location
WL	= Wafer Lot
Y	= Year
WW	= Work Week
G	= Pb–Free Package

*This information is generic. Please refer to device data sheet for actual part marking. Pb–Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.



RECOMMENDED
MOUNTING FOOTPRINT *

* For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DOCUMENT NUMBER:	**98ASH01006A**	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red.	
DESCRIPTION:	**D2PAK 5–LEAD**		**PAGE 1 OF 1**

onsemi and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2019

onsemi, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:
Technical Library: www.onsemi.com/design/resources/technical−documentation
onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support
For additional information, please contact your local Sales Representative at www.onsemi.com/support/sales

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.