DATA SHEET

For a complete data sheet, please also download:

- The IC04 LOCMOS HE4000B Logic Family Specifications HEF, HEC
- The IC04 LOCMOS HE4000B Logic Package Outlines/Information HEF, HEC

HEF4521B
MSI
24-stage frequency divider and oscillator

Product specification
File under Integrated Circuits, IC04

January 1995

Philips Semiconductors

PHILIPS

24-stage frequency divider and oscillator

HEF4521B
MSI

DESCRIPTION

The HEF4521B consists of a chain of 24 toggle flip-flops with an overriding asynchronous master reset input (MR), and an input circuit that allows three modes of operation. The single inverting stage (I_2/O_2) will function as a crystal oscillator, or in combination with I_1 as an RC oscillator, or as an input buffer for an external oscillator. Low-power operation as a crystal oscillator is enabled by connecting external resistors to pins 3 (V_{SS}') and 5 (V_{DD}').
Each flip-flop divides the frequency of the previous flip-flop by two, consequently the HEF4521B will count up to 2^{24} = 16777216. The counting advances on the HIGH to LOW transition of the clock (I_2). The outputs of the last seven stages are available for additional flexibility.



Fig.1 Functional diagram.

FAMILY DATA, I_{DD} LIMITS category MSI

See Family Specifications



Fig.2 Pinning diagram.

COUNT CAPACITY

OUTPUT	COUNT CAPACITY
O_{18}	2^{18} = 262 144
O_{19}	2^{19} = 524 288
O_{20}	2^{20} = 1 048 576
O_{21}	2^{21} = 2 097 152
O_{22}	2^{22} = 4 194 304
O_{23}	2^{23} = 8 388 608
O_{24}	2^{24} = 16 777 216

HEF4521BP(N): 16-lead DIL; plastic (SOT38-1)
HEF4521BD(F): 16-lead DIL; ceramic (cerdip) (SOT74)
HEF4521BT(D): 16-lead SO; plastic (SOT109-1)
( ): Package Designator North America

FUNCTIONAL TEST SEQUENCE

INPUTS		CONTROL TERMINALS			OUTPUTS	REMARKS
MR	I_2	O_2	V_{SS}'	V_{DD}'	O_{18} to O_{24}	
H	L	L	V_{DD}	V_{SS}	L	counter is in three 8-stage sections in parallel mode; I_2 and O_2 are interconnected (O_2 is now input); counter is reset by MR
L	⎍	⎍	V_{DD}	V_{SS}	H	255 pulses are clocked into I_2, O_2 (the counter advances on the LOW to HIGH transition)
L	L	L	V_{SS}	V_{SS}	H	V_{SS}' is connected to V_{SS}
L	H	L	V_{SS}	V_{SS}	H	the input I_2 is made HIGH
L	H	L	V_{SS}	V_{DD}	H	V_{DD}' is connected to V_{DD}; O_2 is now made floating and becomes an output; the device is now in the 2^{24} mode
L	⎎		V_{SS}	V_{DD}	L	counter ripples from an all HIGH state to an all LOW state

A test function has been included for the reduction of the test time required to exercise all 24 counter stages. This test function divides the counter into three 8-stage sections by connecting V_{SS}' to V_{DD} and V_{DD}' to V_{SS}. Via I_2 (connected to O_2) 255 counts are loaded into each of the 8-stage sections in parallel. All flip-flops are now at a HIGH state.

The counter is now returned to the normal 24-stage in series configuration by connecting V_{SS}' to V_{SS} and V_{DD}' to V_{DD}. One more pulse is entered into input I_2, which will cause the counter to ripple from an all HIGH state to an all LOW state.



Fig.3 Logic diagram; for schematic diagram of clock circuit see Fig.4.



Fig.4 Schematic diagram of clock input circuitry.

AC CHARACTERISTICS

V_{SS} = 0 V; T_{amb} = 25 °C; C_L = 50 pF; input transition times ≤ 20 ns

	V_{DD} V	SYMBOL	MIN.	TYP.	MAX.		TYPICAL EXTRAPOLATION FORMULA
Propagation delays							
$I_2 \rightarrow O_{18}$	5			950	1900	ns	923 ns + (0,55 ns/pF) C_L
HIGH to LOW	10	t_{PHL}		350	700	ns	339 ns + (0,23 ns/pF) C_L
	15			220	440	ns	212 ns + (0,16 ns/pF) C_L
	5			950	1900	ns	923 ns + (0,55 ns/pF) C_L
LOW to HIGH	10	t_{PLH}		350	700	ns	339 ns + (0,23 ns/pF) C_L
	15			220	440	ns	212 ns + (0,16 ns/pF) C_L
$O_n \rightarrow O_n + 1$	5			40	80	ns	13 ns + (0,55 ns/pF) C_L
HIGH to LOW	10	t_{PHL}		15	30	ns	4 ns + (0,23 ns/pF) C_L
	15			10	20	ns	2 ns + (0,16 ns/pF) C_L
	5			40	80	ns	13 ns + (0,55 ns/pF) C_L
LOW to HIGH	10	t_{PLH}		15	30	ns	4 ns + (0,23 ns/pF) C_L
	15			10	20	ns	2 ns + (0,16 ns/pF) C_L
$MR \rightarrow O_n$	5			120	240	ns	93 ns + (0,55 ns/pF) C_L
HIGH to LOW	10	t_{PHL}		55	110	ns	44 ns + (0,23 ns/pF) C_L
	15			40	80	ns	32 ns + (0,16 ns/pF) C_L
$I_1 \rightarrow O_1$	5			90	180	ns	63 ns + (0,55 ns/pF) C_L
HIGH to LOW	10	t_{PHL}		35	70	ns	24 ns + (0,23 ns/pF) C_L
	15			25	50	ns	17 ns + (0,16 ns/pF) C_L
	5			60	120	ns	33 ns + (0,55 ns/pF) C_L
LOW to HIGH	10	t_{PLH}		30	60	ns	19 ns + (0,23 ns/pF) C_L
	15			20	40	ns	12 ns + (0,16 ns/pF) C_L

	V_{DD} V	SYMBOL	MIN.	TYP.	MAX.		TYPICAL EXTRAPOLATION FORMULA
Output transition times	5			60	120	ns	10 ns + (1,0 ns/pF) C_L
HIGH to LOW	10	t_{THL}		30	60	ns	9 ns + (0,42 ns/pF) C_L
	15			20	40	ns	6 ns + (0,28 ns/pF) C_L
	5			60	120	ns	10 ns + (1,0 ns/pF) C_L
LOW to HIGH	10	t_{TLH}		30	60	ns	9 ns + (0,42 ns/pF) C_L
	15			20	40	ns	6 ns + (0,28 ns/pF) C_L

AC CHARACTERISTICS

V_{SS} = 0 V; T_{amb} = 25 °C; C_L = 50 pF; input transition times ≤ 20 ns

	V_{DD} V	SYMBOL	MIN.	TYP.	MAX.		
Minimum I_2 pulse	5		80	40		ns	see also waveforms Fig.5
width; HIGH	10	t_{WI2H}	40	20		ns	
	15		30	15		ns	
Minimum MR	5		70	35		ns	
pulse width; HIGH	10	t_{WMRH}	40	20		ns	
	15		30	15		ns	
Recovery time	5		20	–10		ns	
for MR	10	t_{RMR}	15	–5		ns	
	15		15	0		ns	
Maximum clock	5		6	12		MHz	
pulse frequency	10	f_{max}	12	25		MHz	
	15		17	35		MHz	

	V_{DD} V	TYPICAL FORMULA FOR P (μW)	
Dynamic power	5	1 200 $f_i + \sum (f_o C_L) \times V_{DD}^2$	where
dissipation per	10	5 100 $f_i + \sum (f_o C_L) \times V_{DD}^2$	f_i = input freq. (MHz)
package (P)	15	13 050 $f_i + \sum (f_o C_L) \times V_{DD}^2$	f_o = output freq. (MHz)
			C_L = load capacitance (pF)
			$\sum (f_o C_L)$ = sum of outputs
			V_{DD} = supply voltage (V)



Fig.5 Waveforms showing minimum pulse widths for MR and I_2, recovery time for MR.

APPLICATION INFORMATION



(1) Optional for low power operation.

Fig.6 Crystal oscillator circuit.

Typical characteristics for crystal oscillator circuit (Fig.6):

	500 kHz CIRCUIT	**50 kHz CIRCUIT**	**UNIT**
Crystal characteristics			
resonance frequency	500	50	kHz
crystal cut	S	N	–
equivalent resistance; R_S	1	6,2	kΩ
External resistor/capacitor values			
R_o	47	750	kΩ
C_T	82	82	pF
C_S	20	20	pF



Fig.7 RC oscillator circuit;

$f \approx \frac{1}{2{,}3 \times R_{TC} \times C}$; $R_S \geq 2\ R_{TC}$, in which:

f in Hz, R in Ω, C in F.

$R_S + R_{TC} < \frac{V_{IL\ max}}{I_{LI}}$ (maximum input voltage LOW) / (input leakage current)



Fig.8 Oscillator frequency as a function of R_{TC} and C; V_{DD} = 10 V; test circuit is Fig.7.



Fig.9 Test set-up for measuring forward transconductance $g_{fs} = di_o/dv_i$ at v_o is constant (see also graph Fig.10).



A: average,
B: average + 2 s,
C: average – 2 s, in which: 's' is the observed standard deviation.

Fig.10 Typical forward transconductance g_{fs} as a function of the supply voltage at T_{amb} = 25 °C.



Fig.11 Voltage gain V_O/V_I as a function of supply voltage.



Fig.12 Supply current as a function of supply voltage.



Fig.13 Test set-up for measuring graphs of Figs 11 and 12.

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.

ENTEGRECİ

Bu belge www.entegreci.com üzerinden sunulmaktadır.

Elektronik komponent tedarikinde Entegreci

Entegreci, Eskişehir merkezli, Türkiye geneline satış yapan bir elektronik komponent mağazasıdır. Entegreler (IC), mikrodenetleyiciler, transistörler, diyotlar, pasif elemanlar, konnektörler, modüller ve geliştirme kartları tek adetten seri üretim adetlerine kadar satılır. Ürün sayfalarında güncel stok durumunu, fiyatı ve datasheet bağlantısını bulabilirsiniz.

Parça koduyla arama

Üretici parça numarasını yazın; stok ve fiyatı hemen görün.

www.entegreci.com

Ürün kategorileri

Entegreden kapasitöre tüm elektronik komponent kategorileri.

Kategorilere göz atın

Üreticiler

Aradığınız üreticinin ürünlerini tek sayfada inceleyin.

Üreticileri görün

Toplu alım ve teklif

Listede olmayan ya da yüksek adetli parçalar için teklif isteyin.

Teklif isteyin

www.entegreci.com | **destek@entegreci.com** | **0850 305 90 34**

Entegreci is an online electronic components store based in Türkiye. Search by manufacturer part number to see stock, prices and datasheets for integrated circuits, microcontrollers, transistors, passive components and connectors, or request a quote for parts that are not listed.

Bu sayfa Entegreci tarafından eklenmiştir. Belgenin önceki sayfaları asıl yayıncısına aittir ve içeriği değiştirilmemiştir; en güncel sürüm için belgenin yayıncısına başvurun.